

# The origin of transport barriers in toroidal plasmas

Fedor V.Prigara

*Institute of Microelectronics and Informatics, Russian Academy of Sciences,*

*21 Universitetskaya, Yaroslavl 150007, Russia\**

(Dated: November 20, 2018)

## Abstract

A transport barrier in a toroidal plasma is treated as the boundary region between the hot and cold phases of the plasma. These two phases possess essentially different collision and transport properties, so the boundary region between them corresponds to the minimum values of specific resistivity and transport coefficients of the plasma. The behavior of magnetic shear in the region of a transport barrier and some other specific properties of transport barriers are the consequences of the minimum plasma resistivity in this region. The origin of sawtooth oscillations in toroidal plasmas is shown to have a similar nature.

PACS numbers: 52.25.Fi, 52.55.Dy, 52.35.Py

Transport barriers in the tokamak plasmas, i.e. the regions of reduced particle and energy transport across magnetic surfaces, have been discovered as early as in 1982 [1]. There exist both edge and internal transport barriers in the tokamak and other toroidal plasmas. These transport barriers are normally associated with the poloidal rotation, low (in fact, zero) magnetic shear, and the generation of radial electric fields in the plasma [2]. With the edge transport barrier, the total energy confinement time of the plasma in tokamaks and other toroidal devices doubles (H-mode) over that for a plasma without the edge transport barrier (L-mode). The theory of the classical collisional transport losses does not explain these phenomena which are also a hard challenge for the turbulent transport models [3].

Here we show that the transport properties of a hot plasma (with the electron temperature exceeding the critical temperature  $T_{e,c} \cong 1keV$ ), interacting with thermal radiation, essentially differ from those of a cold plasma. A transport barrier in a toroidal plasma can be treated as the boundary region between the hot and cold phases of the plasma. The specific resistivity and the transport coefficients of the plasma have the minimum values in this boundary region. The minimum plasma resistivity produces a local maximum of the current density and, as a consequence, zero magnetic shear. Some other properties of transport barriers in toroidal plasmas are also related to the current density profile in the boundary region.

It has been shown recently [4] that the frequency of electron-ion collisions in a hot plasma interacting with thermal radiation is given by the formula

$$\nu_{ei} = nv_{Te}\sigma_{ei} \approx nv_{Te}\sigma_0, \quad (1)$$

where  $n = n_e = n_i$  is the plasma density,  $v_{Te}$  is the thermal velocity of electrons, and  $\sigma_{ei}$  is the cross-section of electron-ion collisions which is a constant,  $\sigma_0$ , determined by the atomic size. The origin of the constant cross-section  $\sigma_0$  is as follows. A hot plasma with the temperature  $T_e \geq T_0 \cong 3keV$  is intensely interacting with the field of thermal radiation. At temperatures  $T \geq T_0$  the stimulated radiation processes dominate this interaction [5]. Thermal radiation induces radiative transitions in the system of electron and ion which corresponds to the transition of electron from the free to the bounded state.

Thus, in a hot plasma interacting with thermal radiation, the bounded states of electrons and ions restore, leading to the change of collision properties of a hot plasma. In this case, the electron-ion collision cross-section has an order of magnitude of the atomic cross-section,

$$\sigma_0 \cong 10^{-15} \text{cm}^2.$$

Since the specific resistivity  $\eta$  of a plasma is proportional to the frequency of electron-ion collisions, as given by the formula

$$\eta = m_e \nu_{ei} / (n_e e^2), \quad (2)$$

where  $m_e$  and  $e$  are the mass and charge of an electron respectively, the resistivity of a hot plasma increases with the electron temperature as

$$\eta_H \propto T_e^{1/2}, \quad (3)$$

contrary to the relation for a cold plasma

$$\eta_C \propto T_e^{-3/2}. \quad (4)$$

The critical value  $T_{e,c}$  of the electron temperature corresponding to the transition from the cold to the hot phase of a plasma has an order of magnitude of the inversion temperature  $T_0 \cong 3 \text{keV}$  [5]. The studies of sawtooth oscillations by von Goeler, Stodiek, and Sauthoff [6] suggest that the critical temperature is approximately  $T_{e,c} \cong 0.8 \text{keV}$  (see below).

For a typical high-density discharge in a tokamak, the electron temperature is monotonously decreasing with the radius from the center of the plasma to the periphery. If the electron temperature at the center of the plasma,  $T_{e,0}$ , exceeds the critical value,  $T_{e,c}$ , then the region of the minimum resistivity exists, as it follows from the relations (3) and (4). The current density tends to concentrate in this region of low resistivity.

The diffusion coefficients,  $D_{\perp}$ , and thermal conductivity,  $\chi_{\perp}$ , describing the transport of particles and energy across the magnetic surfaces, are proportional to the Larmor radius,  $\rho$ , squared and to the frequency of electron-ion collisions:

$$\chi_{e,\perp} \propto \rho_e^2 \nu_{ei}; \quad \chi_{i,\perp} \propto \rho_i^2 \nu_{ei}, \quad (5)$$

for electrons and ions respectively.

The electron Larmor radius is

$$\rho_e = c (m_e T_e)^{1/2} / (eB), \quad (6)$$

where  $B$  is the magnetic field strength, and  $c$  is the speed of light, so  $\chi_{e,\perp} \propto T_e^{3/2}$  in the hot phase, and  $\chi_{e,\perp} \propto T_e^{-1/2}$  in the cold phase. Similar is the temperature dependence of the ion thermal conductivity.

Therefore, in the boundary region between the hot and cold phases of the plasma, both the specific resistivity and transport coefficients of the plasma have the minimum values. These regions of reduced particle and energy transport across magnetic surfaces have been indeed observed experimentally and called transport barriers. There exist edge and internal transport barriers in toroidal plasmas. The edge transport barrier corresponds to the hot phase of the plasma occupying almost all plasma column which has been symbolically called H-mode (here  $H$  originally denoted the confinement of the plasma, not the hot phase).

Returning to the resistivity profile of a toroidal plasma, we note that the local maximum of the current density,  $J$ , is associated with a transport barrier. It implies that in this region the derivative of the current density with respect to the radius,  $r$ , is zero, i.e.  $dJ/dr = 0$ . The safety factor,  $q$ , is defined by the formula

$$q(r) = B_T r / B_P R, \quad (7)$$

where  $B_T$  is the toroidal magnetic field,  $R$  is the major radius of the plasma, and

$$B_P = 2\pi \langle J \rangle r / c \quad (8)$$

is the poloidal magnetic field produced by the toroidal current in the plasma,  $\langle J \rangle$  being the current density averaged over the plasma column within the radius  $r$ . Substituting expression (8) in the equation (7), we obtain

$$q(r) = c B_T / (2\pi \langle J \rangle R). \quad (9)$$

Now if the current density is locally constant,  $dJ/dr = 0$ , then the averaged current density is also locally constant, and we find that the magnetic shear,  $S$ , defined by the formula

$$S = (r/q) dq/dr \quad (10)$$

is zero in the region of a transport barrier.

Exactly such a relation between transport barriers and the regions of low magnetic shear is observed experimentally in toroidal plasmas [2]. The additional current density parallel to the magnetic field in the region of a transport barrier and caused by the local minimum of plasma resistivity is responsible both for the magneto-hydrodynamic activity associated with the moving region of zero magnetic shear, and for the relation between the transport barriers and the rational magnetic surfaces with  $q = m/n$  for low  $m$  and  $n$  [7].

When the electron temperature at the center of the plasma column only slightly exceeds the critical value  $T_{e,c}$ , the sawtooth oscillations occur [6]. The sawtooth oscillations or internal disruptions have been observed both in high-density discharges near the high-density instability limit and at low densities near the electron runaway regime. It suggests that it is the value of the electron temperature which is crucial for the development of sawtooth oscillations, but not the electron density. The sawtooth oscillations occur only in the central region of the plasma column where the electron temperature is sufficiently high.

During the heating of the plasma, the plasma temperature profile in the plasma core sharpens until the region of the minimum plasma resistivity is formed, in accordance with above considerations. As a consequence, the current density profile and then the electron temperature profile flatten, causing a decrease inside and increase just outside the  $q = 1$  surface [6], indicating that the region of low plasma resistivity is connected to the rational  $q = 1$  magnetic surface. The latter connection explains the development of the sinusoidal  $m = 1, n = 1$  kink mode associated with the sawtooth oscillation [6].

To summarise, we show that the formation of a transport barrier in a toroidal plasma is caused by the minimum plasma resistivity and transport coefficients in the boundary region between the hot and cold phases of the plasma. The additional current density in the boundary region caused by the minimum plasma resistivity is responsible for the connection between the transport barriers and the rational magnetic surfaces. There exists a critical value of the electron temperature corresponding to the transition from the cold to the hot phase of the plasma. At some conditions, the sawtooth oscillations develop in the boundary region between the cold and hot phases of the plasma.

---

[1] F.Wagner et al. Phys. Rev. Lett. **49**, 1408 (1982).

[2] K.A.Razumova, Usp. Fiz. Nauk **171**, 329 (2001) [Physics-Uspekhi **44**, 311 (2001)].

- [3] A.C.C.Sips, Plasma Phys. Control. Fusion **47**, A19 (2005).
- [4] F.V.Prigara, Ann. Phys. (submitted), E-print archives, physics/0410102.
- [5] F.V.Prigara, in Gamow Memorial International Conference, 8-14 August 2004, Odessa, Ukraine, E-print archives, astro-ph/0310491.
- [6] S.von Goeler, W.Stodiek, and N.Sauthoff, Phys. Rev. Lett. **33**, 1201 (1974).
- [7] K.A.Razumova et al. Plasma Phys. Control. Fusion **42**, 973 (2000).
- 

\* Electronic address: [fprigara@imras.yar.ru](mailto:fprigara@imras.yar.ru)