

Toda lattice hierarchy and trigonometric Ruijsenaars-Schneider hierarchy

V. Prokofev^{*1,2} and A. Zabrodin^{†2,3,4}

¹Moscow Institute of Physics and Technology, Dolgoprudny, Institutsky per., 9, Moscow region, 141700, Russia

²Skolkovo Institute of Science and Technology, 143026 Moscow, Russian Federation

³National Research University Higher School of Economics, 20 Myasnitskaya Ulitsa, Moscow 101000, Russian Federation

⁴ITEP, 25 B.Chernomushkinskaya, Moscow 117218, Russian Federation

July 2019

Abstract

We consider solutions of the 2D Toda lattice hierarchy which are trigonometric functions of the “zeroth” time $t_0 = x$. It is known that their poles move as particles of the trigonometric Ruijsenaars-Schneider model. We extend this correspondence to the level of hierarchies: the dynamics of poles with respect to the m -th hierarchical time t_m (respectively, \bar{t}_m) of the 2D Toda lattice hierarchy is shown to be governed by the Hamiltonian which is proportional to the m -th Hamiltonian $\text{tr} L^m$ (respectively, $\text{tr} L^{-m}$) of the Ruijsenaars-Schneider model, where L is the Lax matrix.

Contents

1	Introduction	2
2	The 2D Toda lattice hierarchy	3
3	Trigonometric solutions to the mKP equation	7
4	The higher Hamiltonian equations	11
4.1	Positive times	11
4.2	Negative times	13

*vadim.prokofev@phystech.edu

†zabrodin@itep.ru

5	The generating form of equations of motion in higher times	16
6	The tau-function for trigonometric solutions	17
7	Conclusion	20
	References	20

1 Introduction

The 2D Toda lattice (2DTL) hierarchy is an infinite set of compatible nonlinear differential-difference equations involving infinitely many time variables $\mathbf{t} = \{t_1, t_2, t_3, \dots\}$ (“positive” times), $\bar{\mathbf{t}} = \{\bar{t}_1, \bar{t}_2, \bar{t}_3, \dots\}$ (“negative” times) in which the equations are differential and the “zeroth” time $t_0 = x$ in which the equations are difference. When the negative times are frozen, the equations involving x and \mathbf{t} variables form the modified Kadomtsev-Petviashvili (mKP) hierarchy which is a subhierarchy of the 2DTL one. Among all solutions to these equations, of special interest are solutions which have a finite number of poles in the variable x in a fundamental domain of the complex plane. In particular, one can consider solutions which are trigonometric or hyperbolic functions of x with poles depending on the times.

The investigation of dynamics of poles of singular solutions to nonlinear integrable equations was initiated in the seminal paper [1], where elliptic and rational solutions to the Korteweg-de Vries and Boussinesq equations were studied. It was shown that the poles move as particles of the integrable Calogero-Moser many-body system [2, 3, 4, 5] with some restrictions in the phase space. As it was proved in [6, 7], this connection becomes most natural for the more general Kadomtsev-Petviashvili (KP) equation, in which case there are no restrictions in the phase space for the Calogero-Moser dynamics of poles. The method suggested by Krichever [8] for elliptic solutions of the KP equation consists in substituting the solution not in the KP equation itself but in the auxiliary linear problem for it (this implies a suitable pole ansatz for the wave function). This method allows one to obtain the equations of motion together with their Lax representation.

The further progress was achieved in Shiota’s work [9]. Shiota has shown that the correspondence between rational solutions to the KP equation and the Calogero-Moser system with rational potential can be extended to the level of hierarchies. The evolution of poles with respect to the higher times t_k of the KP hierarchy was shown to be governed by the higher Hamiltonians $H_k = \text{tr } L^k$ of the integrable Calogero-Moser system, where L is the Lax matrix. Later this correspondence was generalized to trigonometric solutions of the KP hierarchy (see [10, 11]).

Dynamics of poles of elliptic solutions to the 2DTL and mKP hierarchies was studied in [12]. It was proved that the poles move as particles of the integrable Ruijsenaars-Schneider many-body system [13] which is a relativistic generalization of the Calogero-Moser system. The extension to the level of hierarchies for rational solutions to the mKP equation has been made in [14] (see also [15]): again, the evolution of poles with respect

to the higher times t_k of the mKP hierarchy is governed by the higher Hamiltonians $\text{tr } L^k$ of the Ruijsenaars-Schneider system.

In this paper we study the correspondence of the 2DTL hierarchy and the Ruijsenaars-Schneider hierarchy for trigonometric solutions of the former. Our method consists in a direct solution of the auxiliary linear problems for the wave function and its adjoint using a suitable pole ansatz. The tau-function of the 2DTL hierarchy for trigonometric solutions has the form

$$\tau(x, \mathbf{t}, \bar{\mathbf{t}}) = \exp\left(-\sum_{k \geq 1} k t_k \bar{t}_k\right) \prod_{i=1}^N \left(e^{2\gamma x} - e^{2\gamma x_i(\mathbf{t}, \bar{\mathbf{t}})}\right),$$

where γ is a complex parameter. (The zeros x_i of the tau-function are poles of the solution.) When γ is purely imaginary (respectively, real), one deals with trigonometric (respectively, hyperbolic) solutions. The limit $\gamma \rightarrow 0$ corresponds to rational solutions. We show that the evolution of the x_i 's with respect to the time t_m is governed by the Hamiltonian

$$H_m = -\frac{\sinh(m\gamma\eta)}{m\gamma\eta} \text{tr } L^m, \quad (1.1)$$

where the parameter η has the meaning of the inverse velocity of light and

$$L_{ij} = \frac{\gamma\eta e^{\eta p_i}}{\sinh(\gamma(x_i - x_j - \eta))} \prod_{l \neq i} \frac{\sinh(\gamma(x_i - x_l + \eta))}{\sinh(\gamma(x_i - x_l))} \quad (1.2)$$

is the Lax matrix of the trigonometric Ruijsenaars-Schneider system. In particular,

$$H_1 = \sum_i e^{\eta p_i} \prod_{l \neq i} \frac{\sinh(\gamma(x_i - x_l + \eta))}{\sinh(\gamma(x_i - x_l))} \quad (1.3)$$

is the standard first Hamiltonian of the Ruijsenaars-Schneider system. In a similar way, the evolution of the x_i 's with respect to the time \bar{t}_m is governed by the Hamiltonian

$$\bar{H}_m = -\frac{\sinh(m\gamma\eta)}{m\gamma\eta} \text{tr } L^{-m}. \quad (1.4)$$

The paper is organized as follows. In section 2 we remind the reader the main facts about the 2DTL hierarchy. Section 3 is devoted to solutions which are trigonometric functions of $x = t_0$. We derive equations of motion for their poles as functions of the time t_1 . In section 4 we consider the dynamics of poles with respect to the higher times and derive the corresponding Hamiltonian equations. In section 5 we derive the self-dual form of equations of motion and show that it encodes all higher equations of motion in the generating form. In section 6 the determinant formula for the tau-function of trigonometric solutions is proved.

2 The 2D Toda latttice hierarchy

Here we very briefly review the 2DTL hierarchy (see [16]). Let us consider the pseudo-difference operators

$$\mathcal{L} = e^{\eta\partial_x} + \sum_{k \geq 0} U_k(x) e^{-k\eta\partial_x}, \quad \bar{\mathcal{L}} = c(x) e^{-\eta\partial_x} + \sum_{k \geq 0} \bar{U}_k(x) e^{k\eta\partial_x}, \quad (2.1)$$

where $e^{\eta\partial_x}$ is the shift operator ($e^{\pm\eta\partial_x} f(x) = f(x \pm \eta)$) and the coefficient functions U_k, \bar{U}_k are functions of x, \mathbf{t} and $\bar{\mathbf{t}}$. They are the Lax operators of the 2DTL hierarchy. The equations of the hierarchy are differential-difference equations for the functions U_k, \bar{U}_k . They are encoded in the Lax equations

$$\partial_{t_m} \mathcal{L} = [\mathcal{A}_m, \mathcal{L}], \quad \partial_{\bar{t}_m} \bar{\mathcal{L}} = [\bar{\mathcal{A}}_m, \bar{\mathcal{L}}] \quad \mathcal{A}_m = (\mathcal{L}^m)_{\geq 0}, \quad (2.2)$$

$$\partial_{\bar{t}_m} \mathcal{L} = [\bar{\mathcal{A}}_m, \mathcal{L}], \quad \partial_{t_m} \bar{\mathcal{L}} = [\bar{\mathcal{A}}_m, \bar{\mathcal{L}}] \quad \bar{\mathcal{A}}_m = (\bar{\mathcal{L}}^m)_{< 0}, \quad (2.3)$$

where $(\sum_{\mathbb{Z}} U_k e^{k\eta\partial_x})_{\geq 0} = \sum_{k \geq 0} U_k e^{k\eta\partial_x}$, $(\sum_{k \in \mathbb{Z}} U_k e^{k\eta\partial_x})_{< 0} = \sum_{k < 0} U_k e^{k\eta\partial_x}$. For example, $\mathcal{A}_1 = e^{\eta\partial_x} + U_0(x)$, $\bar{\mathcal{A}}_1 = c(x)e^{-\eta\partial_x}$.

An equivalent formulation is through the zero curvature (Zakharov-Shabat) equations

$$\partial_{t_n} \mathcal{A}_m - \partial_{t_m} \mathcal{A}_n + [\mathcal{A}_m, \mathcal{A}_n] = 0, \quad (2.4)$$

$$\partial_{\bar{t}_n} \mathcal{A}_m - \partial_{t_m} \bar{\mathcal{A}}_n + [\mathcal{A}_m, \bar{\mathcal{A}}_n] = 0, \quad (2.5)$$

$$\partial_{\bar{t}_n} \bar{\mathcal{A}}_m - \partial_{\bar{t}_m} \bar{\mathcal{A}}_n + [\bar{\mathcal{A}}_m, \bar{\mathcal{A}}_n] = 0. \quad (2.6)$$

In particular, at $n = 1, m = 2$ we obtain from (2.4)

$$\begin{cases} \partial_{t_1} (U_0(x) + U_0(x - \eta)) = U_1(x + \eta) - U_1(x - \eta) \\ \partial_{t_2} U_0(x) = \partial_{t_1} (U_0^2(x) + U_1(x + \eta) + U_1(x)). \end{cases} \quad (2.7)$$

Excluding U_1 from this system, one gets the mKP equation for $v(x) = U_0(x)$:

$$\partial_{t_2} (v(x + \eta) - v(x)) = \partial_{t_1}^2 (v(x + \eta) + v(x)) + \partial_{t_1} (v^2(x + \eta) - v^2(x)). \quad (2.8)$$

From (2.5) at $m = n = 1$ we have

$$\begin{cases} \partial_{t_1} \log c(x) = v(x) - v(x - \eta) \\ \partial_{\bar{t}_1} v(x) = c(x) - c(x + \eta). \end{cases}$$

Excluding $v(x)$, we get the second order differential-difference equation for $c(x)$:

$$\partial_{t_1} \partial_{\bar{t}_1} \log c(x) = 2c(x) - c(x + \eta) - c(x - \eta)$$

which is one of the forms of the 2D Toda equation. After the change of variables $c(x) = e^{\varphi(x) - \varphi(x - \eta)}$ it acquires the most familiar form

$$\partial_{t_1} \partial_{\bar{t}_1} \varphi(x) = e^{\varphi(x) - \varphi(x - \eta)} - e^{\varphi(x + \eta) - \varphi(x)}. \quad (2.9)$$

The zero curvature equations are compatibility conditions for the auxiliary linear problems

$$\partial_{t_m} \psi = \mathcal{A}_m(x) \psi, \quad \partial_{\bar{t}_m} \psi = \bar{\mathcal{A}}_m(x) \psi, \quad (2.10)$$

where the wave function ψ depends on a spectral parameter z : $\psi = \psi(z; \mathbf{t})$. The wave function has the following expansion in powers of z :

$$\psi = z^{x/\eta} e^{\xi(\mathbf{t}, z)} \left(1 + \frac{\xi_1(x, \mathbf{t}, \bar{\mathbf{t}})}{z} + \frac{\xi_2(x, \mathbf{t}, \bar{\mathbf{t}})}{z^2} + \dots \right), \quad (2.11)$$

where

$$\xi(\mathbf{t}, z) = \sum_{k \geq 1} t_k z^k. \quad (2.12)$$

The wave operator is the pseudo-difference operator of the form

$$\mathcal{W}(x) = 1 + \xi_1(x) e^{-\eta \partial_x} + \xi_2(x) e^{-2\eta \partial_x} + \dots \quad (2.13)$$

with the same coefficient functions ξ_k as in (2.11), then the wave function can be written as

$$\psi = \mathcal{W}(x) z^{x/\eta} e^{\xi(\mathbf{t}, z)}. \quad (2.14)$$

The adjoint wave function ψ^\dagger is defined by the formula

$$\psi^\dagger = (\mathcal{W}^\dagger(x - \eta))^{-1} z^{-x/\eta} e^{-\xi(\mathbf{t}, z)} \quad (2.15)$$

(see, e.g., [17]), where the adjoint difference operator is defined according to the rule $(f(x) \circ e^{n\eta \partial_x})^\dagger = e^{-n\eta \partial_x} \circ f(x)$. The auxiliary linear problems for the adjoint wave function have the form

$$-\partial_{t_m} \psi^\dagger = \mathcal{A}_m^\dagger(x - \eta) \psi^\dagger. \quad (2.16)$$

In particular, we have:

$$\partial_{t_1} \psi(x) = \psi(x + \eta) + v(x) \psi(x), \quad (2.17)$$

$$-\partial_{t_1} \psi^\dagger(x) = \psi^\dagger(x - \eta) + v(x - \eta) \psi^\dagger(x),$$

$$\partial_{\bar{t}_1} \psi(x) = c(x) \psi(x - \eta). \quad (2.18)$$

A common solution to the 2DTL hierarchy is provided by the tau-function $\tau = \tau(x, \mathbf{t}, \bar{\mathbf{t}})$ [18, 19]. The hierarchy is encoded in the bilinear relation

$$\begin{aligned} & \oint_{\infty} z^{\frac{x-x'}{\eta}-1} e^{\xi(\mathbf{t}, z) - \xi(\mathbf{t}', z)} \tau(x, \mathbf{t} - [z^{-1}], \bar{\mathbf{t}}) \tau(x' + \eta, \mathbf{t}' + [z^{-1}], \bar{\mathbf{t}}') dz \\ & = \oint_0 z^{\frac{x-x'}{\eta}-1} e^{\xi(\bar{\mathbf{t}}, z^{-1}) - \xi(\bar{\mathbf{t}}', z^{-1})} \tau(x + \eta, \mathbf{t}, \bar{\mathbf{t}} - [z]) \tau(x', \mathbf{t}', \bar{\mathbf{t}}' + [z]) dz \end{aligned} \quad (2.19)$$

valid for all $x, x', \mathbf{t}, \mathbf{t}', \bar{\mathbf{t}}, \bar{\mathbf{t}}'$, where

$$\mathbf{t} \pm [z] = \left\{ t_1 \pm z, t_2 \pm \frac{1}{2} z^2, t_3 \pm \frac{1}{3} z^3, \dots \right\}. \quad (2.20)$$

The integration contour in the left hand side is a big circle around infinity separating the singularities coming from the exponential factor from those coming from the tau-functions. The integration contour in the right hand side is a small circle around zero separating the singularities coming from the exponential factor from those coming from the tau-functions. In particular, setting $x = x', \bar{\mathbf{t}} = \bar{\mathbf{t}}'$, one obtains from (2.19) the bilinear relation for the mKP hierarchy

$$\frac{1}{2\pi i} \oint_{\infty} z^{-1} e^{\xi(\mathbf{t}, z) - \xi(\mathbf{t}', z)} \tau(x, \mathbf{t} - [z^{-1}]) \tau(x + \eta, \mathbf{t}' + [z^{-1}]) dz = \tau(x + \eta, \mathbf{t}) \tau(x, \mathbf{t}'). \quad (2.21)$$

Consequences of the bilinear relations (which are in fact equivalent to the whole hierarchy, see [20]) are the equations

$$\begin{aligned} & \mu\tau(x + \eta, \mathbf{t} + [\lambda^{-1}] - [\mu^{-1}], \bar{\mathbf{t}})\tau(x, \mathbf{t}, \bar{\mathbf{t}}) - \lambda\tau(x + \eta, \mathbf{t}, \bar{\mathbf{t}})\tau(x, \mathbf{t} + [\lambda^{-1}] - [\mu^{-1}], \bar{\mathbf{t}}) \\ & + (\lambda - \mu)\tau(x + \eta, \mathbf{t} + [\lambda^{-1}], \bar{\mathbf{t}})\tau(x, \mathbf{t} - [\mu^{-1}], \bar{\mathbf{t}}) = 0, \end{aligned} \quad (2.22)$$

$$\begin{aligned} & \tau(x, \mathbf{t} - [\lambda^{-1}], \bar{\mathbf{t}})\tau(x, \mathbf{t}, \bar{\mathbf{t}} - [\nu]) - \tau(x, \mathbf{t}, \bar{\mathbf{t}})\tau(x, \mathbf{t} - [\lambda^{-1}], \bar{\mathbf{t}} - [\nu]) \\ & = \nu\lambda^{-1}\tau(x + \eta, \mathbf{t}, \bar{\mathbf{t}} - [\nu])\tau(x - \eta, \mathbf{t} - [\lambda^{-1}], \bar{\mathbf{t}}). \end{aligned} \quad (2.23)$$

There is also an equation similar to (2.22) with shifts of the negative times. Together with the tau-function τ it is convenient to introduce another tau-function, τ' , which differs from τ by a simple factor:

$$\tau'(x, \mathbf{t}, \bar{\mathbf{t}}) = \exp\left(\sum_{k \geq 1} kt_k \bar{t}_k\right) \tau(x, \mathbf{t}, \bar{\mathbf{t}}). \quad (2.24)$$

The coefficient functions of the Lax operators can be expressed through the tau-function. In particular,

$$U_0(x) = v(x) = \partial_{t_1} \log \frac{\tau(x + \eta)}{\tau(x)}, \quad c(x) = \frac{\tau(x + \eta)\tau(x - \eta)}{\tau^2(x)}. \quad (2.25)$$

After this substitution the mKP equation (2.8) becomes

$$\partial_{t_2} \log \frac{\tau(x + \eta)}{\tau(x)} = \partial_{t_1}^2 \log(\tau(x + \eta)\tau(x)) + \left(\partial_{t_1} \log \frac{\tau(x + \eta)}{\tau(x)}\right)^2, \quad (2.26)$$

which can be also represented in the bilinear form

$$\tau(x)\partial_{t_2}\tau(x + \eta) - \tau(x + \eta)\partial_{t_2}\tau(x) = \tau(x + \eta)\partial_{t_1}^2\tau(x) - 2\partial_{t_1}\tau(x + \eta)\partial_{t_1}\tau(x) + \tau(x)\partial_{t_1}^2\tau(x + \eta).$$

The Toda equation (2.9) becomes

$$\partial_{t_1} \partial_{\bar{t}_1} \log \tau(x) = 1 - \frac{\tau(x + \eta)\tau(x - \eta)}{\tau^2(x)}. \quad (2.27)$$

The wave function and its adjoint are expressed through the tau-function according to the formulas

$$\psi = z^{x/\eta} e^{\xi(\mathbf{t}, z)} \frac{\tau(x, \mathbf{t} - [z^{-1}], \bar{\mathbf{t}})}{\tau(x, \mathbf{t}, \bar{\mathbf{t}})}, \quad (2.28)$$

$$\psi^\dagger = z^{-x/\eta} e^{-\xi(\mathbf{t}, z)} \frac{\tau(x, \mathbf{t} + [z^{-1}], \bar{\mathbf{t}})}{\tau(x, \mathbf{t}, \bar{\mathbf{t}})}. \quad (2.29)$$

One may also introduce the complimentary wave functions $\bar{\psi}$, $\bar{\psi}^\dagger$ by the formulas

$$\bar{\psi} = z^{x/\eta} e^{\xi(\bar{\mathbf{t}}, z^{-1})} \frac{\tau(x + \eta, \mathbf{t}, \bar{\mathbf{t}} - [z])}{\tau(x, \mathbf{t}, \bar{\mathbf{t}})}, \quad (2.30)$$

$$\bar{\psi}^\dagger = z^{-x/\eta} e^{-\xi(\bar{\mathbf{t}}, z^{-1})} \frac{\tau(x - \eta, \mathbf{t}, \bar{\mathbf{t}} + [z])}{\tau(x, \mathbf{t}, \bar{\mathbf{t}})}. \quad (2.31)$$

They satisfy the same auxiliary linear problems as the wave functions ψ , ψ^\dagger . It will be more convenient for us to work with the renormalized wave functions

$$\phi(x) = \frac{\tau(x)}{\tau(x + \eta)} \bar{\psi}(x) = z^{x/\eta} e^{\xi(\bar{\mathbf{t}}, z^{-1})} \frac{\tau(x + \eta, \mathbf{t}, \bar{\mathbf{t}} - [z])}{\tau(x + \eta, \mathbf{t}, \bar{\mathbf{t}})}, \quad (2.32)$$

$$\phi^\dagger(x) = \frac{\tau(x)}{\tau(x - \eta)} \bar{\psi}^\dagger(x) = z^{-x/\eta} e^{-\xi(\bar{\mathbf{t}}, z^{-1})} \frac{\tau(x - \eta, \mathbf{t}, \bar{\mathbf{t}} + [z])}{\tau(x - \eta, \mathbf{t}, \bar{\mathbf{t}})}. \quad (2.33)$$

It is easy to check that they satisfy the linear equations

$$\partial_{\bar{t}_1} \phi(x) = \phi(x - \eta) - \bar{v}(x) \phi(x), \quad -\partial_{\bar{t}_1} \phi^\dagger(x) = \phi^\dagger(x + \eta) - \bar{v}(x - \eta) \phi^\dagger(x), \quad (2.34)$$

where $\bar{v}(x) = \partial_{\bar{t}_1} \log \frac{\tau(x + \eta)}{\tau(x)}$.

Finally, let us point out useful corollaries of the bilinear relation (2.21). Differentiating it with respect to t_m and putting $\mathbf{t} = \mathbf{t}'$ after that, we obtain:

$$\begin{aligned} & \frac{1}{2\pi i} \oint_{\infty} z^{m-1} \tau(x, \mathbf{t} - [z^{-1}]) \tau(x + \eta, \mathbf{t} + [z^{-1}]) dz \\ &= \partial_{t_m} \tau(x + \eta, \mathbf{t}) \tau(x, \mathbf{t}) - \partial_{t_m} \tau(x, \mathbf{t}) \tau(x + \eta, \mathbf{t}) \end{aligned} \quad (2.35)$$

or

$$\operatorname{res}_{\infty} \left(z^m \psi(x) \psi^\dagger(x + \eta) \right) = \partial_{t_m} \log \frac{\tau(x + \eta)}{\tau(x)}. \quad (2.36)$$

In a similar way, differentiating the bilinear relation (2.19) with respect to \bar{t}_m and putting $x = x'$, $\mathbf{t} = \mathbf{t}'$, $\bar{\mathbf{t}} = \bar{\mathbf{t}'}$ after that, we obtain the relation

$$\operatorname{res}_0 \left(z^{-m} \phi(x) \phi^\dagger(x + \eta) \right) = -\partial_{\bar{t}_m} \log \frac{\tau(x + \eta)}{\tau(x)}. \quad (2.37)$$

Here $\operatorname{res}_{\infty}$, res_0 are defined according to the convention $\operatorname{res}_{\infty}(z^{-n}) = \delta_{n1}$, $\operatorname{res}_0(z^{-n}) = \delta_{n1}$.

3 Trigonometric solutions to the mKP equation

We are going to consider solutions which are trigonometric (i.e. single-periodic) functions of the variable x . For trigonometric solutions the tau-function has the form

$$\tau(x, \mathbf{t}) = \prod_{i=1}^N \left(e^{2\gamma x} - e^{2\gamma x_i(\mathbf{t})} \right). \quad (3.1)$$

(In this section we ignore the dependence on the negative times keeping them fixed to zero.) This function has a single period $\pi i/\gamma$ in the complex plane. As in [11], we pass to the exponentiated variables

$$w = e^{2\gamma x}, \quad w_i = e^{2\gamma x_i}. \quad (3.2)$$

In these variables, the tau-function becomes a polynomial of degree N with roots w_i which are supposed to be distinct: $\tau = \prod_i (w - w_i)$. The function $v(x) = \partial_{t_1} \log(\tau(x+\eta)/\tau(x))$ is

$$v(x) = \sum_i \left(\frac{\dot{w}_i}{w - w_i} - \frac{\dot{w}_i}{qw - w_i} \right), \quad (3.3)$$

where

$$q = e^{2\gamma\eta} \quad (3.4)$$

and here and below dot means the t_1 -derivative.

We begin with the investigation of the t_1 -dynamics of the poles. The ansatz for the ψ -function depending on the spectral parameter z suggested by equation (2.28) is

$$\psi = z^{x/\eta} e^{t_1 z} \left(1 + \sum_i \frac{2\gamma c_i}{w - w_i} \right), \quad (3.5)$$

where we have put $t_k = 0$ for $k \geq 2$. The coefficients c_i depend on \mathbf{t} and on z . Substituting ψ and v into the first auxiliary linear problem in (2.17) $-\partial_{t_1} \psi(x) + \psi(x+\eta) + v(x)\psi(x) = 0$, we get:

$$\begin{aligned} & -z \sum_i \frac{c_i}{w - w_i} - \sum_i \frac{\dot{c}_i}{w - w_i} - \sum_i \frac{\dot{w}_i c_i}{(w - w_i)^2} + \sum_i \frac{q^{-1} c_i}{w - q^{-1} w_i} \\ & + \frac{1}{2\gamma} \sum_i \left(\frac{\dot{w}_i}{w - w_i} - \frac{\dot{w}_i q^{-1}}{w - q^{-1} w_i} \right) + \sum_i \left(\frac{\dot{w}_i}{w - w_i} - \frac{\dot{w}_i q^{-1}}{w - q^{-1} w_i} \right) \sum_k \frac{c_k}{w - w_k} = 0. \end{aligned}$$

The left hand side is a rational function of w vanishing at infinity with simple poles at $w = w_i$ and $w = q^{-1} w_i$ (the second order poles cancel identically). We should equate residues at the poles to zero. This gives the following system of linear equations for the coefficients c_i :

$$\begin{cases} z c_i - q \sum_k \frac{\dot{w}_i c_k}{w_i - q w_k} = \frac{1}{2\gamma} \dot{w}_i \\ \dot{c}_i = c_i \left(\sum_{k \neq i} \frac{\dot{w}_k}{w_i - w_k} - \sum_k \frac{\dot{w}_k}{q w_i - w_k} \right) + \sum_{k \neq i} \frac{\dot{w}_i c_k}{w_i - w_k} - q \sum_k \frac{\dot{w}_i c_k}{w_i - q w_k}. \end{cases} \quad (3.6)$$

In a similar way, the adjoint linear problem $\partial_{t_1} \psi^\dagger(x) + \psi^\dagger(x - \eta) + v(x - \eta)\psi^\dagger(x) = 0$ with the ansatz for the ψ^\dagger -function

$$\psi^\dagger = z^{-x/\eta} e^{-t_1 z} \left(1 + \sum_i \frac{2\gamma c_i^*}{w - w_i} \right) \quad (3.7)$$

leads to the linear equations for the coefficients c_i^* :

$$\begin{cases} z c_i^* - \sum_k \frac{\dot{w}_i c_k^*}{w_k - q w_i} = -\frac{1}{2\gamma} \dot{w}_i \\ \dot{c}_i^* = c_i^* \left(\sum_{k \neq i} \frac{\dot{w}_k}{w_i - w_k} + \sum_k \frac{q \dot{w}_k}{w_i - q w_k} \right) + \sum_{k \neq i} \frac{\dot{w}_i c_k^*}{w_i - w_k} - \sum_k \frac{\dot{w}_i c_k^*}{q w_i - w_k}. \end{cases} \quad (3.8)$$

After the gauge transformation $\tilde{c}_i = c_i w_i^{-1/2}$, $\tilde{c}_i^* = c_i^* w_i^{-1/2}$ the above conditions can be written in the matrix form

$$(zI - q^{1/2}L)\tilde{\mathbf{c}} = \dot{X}W^{1/2}\mathbf{e}, \quad \partial_{t_1}\tilde{\mathbf{c}} = M\tilde{\mathbf{c}}, \quad (3.9)$$

$$\tilde{\mathbf{c}}^* \dot{X}^{-1}(zI - q^{-1/2}L) = -\mathbf{e}^T W^{1/2}, \quad \partial_{t_1}\tilde{\mathbf{c}}^* = -\tilde{\mathbf{c}}^* \tilde{M}, \quad (3.10)$$

where $\tilde{\mathbf{c}} = (\tilde{c}_1, \dots, \tilde{c}_N)^T$ is a column vector, $\tilde{\mathbf{c}}^* = (\tilde{c}_1^*, \dots, \tilde{c}_N^*)$ is a row vector, $\mathbf{e} = (1, 1, \dots, 1)^T$, I is the identity matrix and the matrices X , W , L , M , \tilde{M} are

$$X = \text{diag}(x_1, x_2, \dots, x_N), \quad W = \text{diag}(w_1, w_2, \dots, w_N), \quad (3.11)$$

$$L_{ij} = 2\gamma q^{1/2} \frac{\dot{x}_i w_i^{1/2} w_j^{1/2}}{w_i - q w_j}, \quad (3.12)$$

$$M_{ij} = \gamma \delta_{ij} \left(\sum_{k \neq i} \frac{w_i + w_k}{w_i - w_k} \dot{x}_k - \sum_k \frac{q w_i + w_k}{q w_i - w_k} \dot{x}_k \right) + 2\gamma \frac{\dot{x}_i w_i^{1/2} w_j^{1/2}}{w_i - w_j} (1 - \delta_{ij}) - 2\gamma q \frac{\dot{x}_i w_i^{1/2} w_j^{1/2}}{w_i - q w_j}, \quad (3.13)$$

$$\tilde{M}_{ji} = -\gamma \delta_{ij} \left(\sum_{k \neq i} \frac{w_i + w_k}{w_i - w_k} \dot{x}_k - \sum_k \frac{w_i + q w_k}{w_i - q w_k} \dot{x}_k \right) + 2\gamma \frac{\dot{x}_i w_i^{1/2} w_j^{1/2}}{w_j - w_i} (1 - \delta_{ij}) - 2\gamma \frac{\dot{x}_i w_i^{1/2} w_j^{1/2}}{w_j - q w_i}. \quad (3.14)$$

The following commutation relation can be checked directly:

$$q^{-1/2}WL - q^{1/2}LW = W^{-1/2}\dot{W}EW^{1/2}. \quad (3.15)$$

Here $E = \mathbf{e} \otimes \mathbf{e}^T$ is the rank 1 matrix with matrix elements $E_{ij} = 1$. This commutation relation will be important in what follows.

The system of linear equations (3.9) is overdetermined. Taking the t_1 -derivative of the first equation in (3.9) and substituting the second equation, one obtains the compatibility condition of the system in the form

$$\left(\dot{L} + [L, M] \right) \tilde{\mathbf{c}} + q^{-1/2} \left(\ddot{X} + \gamma \dot{X}^2 - M \dot{X} \right) W^{1/2} \mathbf{e} = 0. \quad (3.16)$$

A straightforward calculation shows that

$$\dot{L} + [L, M] = RL,$$

$$\left(\ddot{X} + \gamma \dot{X}^2 - M \dot{X} \right) W^{1/2} \mathbf{e} = R \dot{X} W^{1/2} \mathbf{e},$$

where

$$R = \ddot{X} \dot{X}^{-1} + D^+ + D^- - 2D^0$$

and the diagonal matrices D^\pm , D_0 are

$$D_{ij}^\pm = \delta_{ij} \gamma \sum_{k \neq i} \frac{q^{\pm 1} w_i + w_k}{q^{\pm 1} w_i - w_k} \dot{x}_k, \quad D_{ij}^0 = \delta_{ij} \gamma \sum_{k \neq i} \frac{w_i + w_k}{w_i - w_k} \dot{x}_k.$$

Therefore, the compatibility condition takes the form $R\check{c} = 0$ which means that $R_{ii} = 0$ for all i . This leads to the equations of motion of the trigonometric Ruijsenaars-Schneider model

$$\begin{aligned}\ddot{x}_i &= -\gamma \sum_{k \neq i} \dot{x}_i \dot{x}_k \left(\coth(\gamma(x_{ik} + \eta)) + \coth(\gamma(x_{ik} - \eta)) - 2 \coth(\gamma x_{ik}) \right) \\ &= \sum_{k \neq i} \dot{x}_i \dot{x}_k \frac{2\gamma \sinh^2(\gamma\eta) \cosh(\gamma x_{ik})}{\sinh(\gamma x_{ik}) \sinh(\gamma(x_{ik} + \eta)) \sinh(\gamma(x_{ik} - \eta))},\end{aligned}\tag{3.17}$$

where $x_{ik} = x_i - x_k$. The matrix equation $\dot{L} + [L, M'] = 0$ with

$$L_{ij} = \frac{\gamma \dot{x}_i}{\sinh(\gamma(x_{ij} - \eta))},\tag{3.18}$$

$$M'_{ij} = \gamma \delta_{ij} \left(\sum_{k \neq i} \dot{x}_k \coth(\gamma x_{ik}) - \sum_k \dot{x}_k \coth(\gamma(x_{ik} + \eta)) \right) + (1 - \delta_{ij}) \frac{\gamma \dot{x}_i}{\sinh(\gamma x_{ij})}\tag{3.19}$$

provides the Lax representation for them.

Equations (3.17) are Hamiltonian with the Hamiltonian

$$H_1 = \sum_i e^{\eta p_i} \prod_{k \neq i} \frac{\sinh(\gamma(x_{ik} + \eta))}{\sinh(\gamma x_{ik})}\tag{3.20}$$

and the canonical Poisson brackets between p_i and x_i . The velocity is given by

$$\dot{x}_i = \frac{\partial H_1}{\partial p_i} = \eta e^{\eta p_i} \prod_{k \neq i} \frac{\sinh(\gamma(x_{ik} + \eta))}{\sinh(\gamma x_{ik})}.$$

The Lax representation implies that the higher conserved quantities are $\text{tr } L^m$. It is proved in [21] that they are in involution, i.e., the system is integrable.

Let us consider the transformation of the phase space coordinates $(p_i, x_i) \rightarrow (u_i, x'_i)$, where $x'_i = x_i$ and

$$u_i = \log \dot{x}_i = \eta p_i + \sum_{k \neq i} \log \frac{\sinh(\gamma(x_{ik} + \eta))}{\sinh(\gamma x_{ik})} + \log \eta.\tag{3.21}$$

Then the derivatives transform as follows:

$$\frac{\partial f}{\partial p_i} = \sum_k \frac{\partial u_k}{\partial p_i} \frac{\partial f}{\partial u_k} + \sum_k \frac{\partial x'_k}{\partial p_i} \frac{\partial f}{\partial x'_k} = \eta \frac{\partial f}{\partial u_i},\tag{3.22}$$

$$\begin{aligned}\frac{\partial f}{\partial x_i} &= \sum_k \frac{\partial u_k}{\partial x_i} \frac{\partial f}{\partial u_k} + \sum_k \frac{\partial x'_k}{\partial x_i} \frac{\partial f}{\partial x'_k} \\ &= \frac{\partial f}{\partial x'_i} + \gamma \frac{\partial f}{\partial u_i} \sum_{l \neq i} (\coth(\gamma(x_{il} + \eta)) - \coth(\gamma x_{il})) \\ &\quad + \gamma \sum_{k \neq i} \frac{\partial f}{\partial u_k} (\coth(\gamma(x_{ik} + \eta)) - \coth(\gamma x_{ik})).\end{aligned}\tag{3.23}$$

At this point we finish the discussion of the t_1 -dynamics of poles and pass to the higher times in the next section.

4 The higher Hamiltonian equations

4.1 Positive times

In order to study the dynamics of poles in the higher positive times \mathbf{t} , we use the relation (2.36), which, after the substitution of the wave functions for the trigonometric solutions, takes the form

$$\frac{1}{2\pi i} \oint_{\infty} z^{m-1} \left(1 + \sum_i \frac{2\gamma c_i}{w - w_i}\right) \left(1 + \sum_k \frac{2\gamma c_k^*}{qw - w_k}\right) dz = \sum_i \left(\frac{\partial_{t_m} w_i}{w - w_i} - \frac{\partial_{t_m} w_i}{qw - w_i}\right).$$

The both sides are rational functions of w with simple poles at $w = w_i$ and $w = q^{-1}w_i$ vanishing at infinity. Identifying the residues at the poles at $w = w_i$ in the both sides, we obtain:

$$\partial_{t_m} x_i = -2\gamma \operatorname{res}_{\infty} \left(z^m \tilde{c}_i^* \dot{w}_i^{-1} \tilde{c}_i\right). \quad (4.1)$$

From (3.9), (3.10) we have:

$$\tilde{\mathbf{c}} = \frac{1}{2\gamma} (zI - q^{1/2}L)^{-1} \dot{W} W^{-1/2} \mathbf{e}, \quad \tilde{\mathbf{c}}^* = -\frac{1}{2\gamma} \mathbf{e}^T W^{1/2} (zI - q^{-1/2}L)^{-1} \dot{W} W^{-1}.$$

Substituting this into (4.1), we get:

$$\begin{aligned} \partial_{t_m} x_i &= \frac{1}{2\gamma} \operatorname{res}_{\infty} \sum_{k,k'} \left[z^m w_k^{1/2} \left(\frac{1}{zI - q^{-1/2}L}\right)_{ki} w_i^{-1} \left(\frac{1}{zI - q^{1/2}L}\right)_{ik'} \dot{w}_{k'} w_{k'}^{-1/2} \right] \\ &= \frac{1}{2\gamma} \operatorname{res}_{\infty} \operatorname{tr} \left(z^m \dot{W} W^{-1/2} E W^{1/2} \frac{1}{zI - q^{-1/2}L} E_i W^{-1} \frac{1}{zI - q^{1/2}L} \right), \end{aligned}$$

where E_i is the diagonal matrix with the matrix elements $(E_i)_{jk} = \delta_{ij} \delta_{ik}$. Using the commutation relation (3.15), we have:

$$\begin{aligned} \partial_{t_m} x_i &= \frac{1}{2\gamma} \operatorname{res}_{\infty} \operatorname{tr} \left(z^m (q^{-1/2}WL - q^{1/2}LW) \frac{1}{zI - q^{-1/2}L} E_i W^{-1} \frac{1}{zI - q^{1/2}L} \right) \\ &= \frac{1}{2\gamma} \operatorname{res}_{\infty} \operatorname{tr} \left(z^m \left(E_i \frac{1}{zI - q^{-1/2}L} - E_i \frac{1}{zI - q^{1/2}L} \right) \right). \end{aligned}$$

Next, we use the easily proved identity

$$E_i L = \dot{x}_i \frac{\partial L}{\partial \dot{x}_i} = \frac{\partial L}{\partial u_i} = \eta^{-1} \frac{\partial L}{\partial p_i}$$

(see (3.22)) to continue the chain of equalities:

$$\begin{aligned} \partial_{t_m} x_i &= \frac{1}{2\gamma\eta} \operatorname{res}_{\infty} \operatorname{tr} \left(z^m \left(\frac{\partial L}{\partial p_i} \frac{L^{-1}}{zI - q^{-1/2}L} - \frac{\partial L}{\partial p_i} \frac{L^{-1}}{zI - q^{1/2}L} \right) \right) \\ &= \frac{1}{2\gamma\eta} (q^{-m/2} - q^{m/2}) \operatorname{tr} \left(\frac{\partial L}{\partial p_i} L^{m-1} \right) = -\frac{\sinh(m\gamma\eta)}{m\gamma\eta} \frac{\partial}{\partial p_i} \operatorname{tr} L^m. \end{aligned} \quad (4.2)$$

In this way we have obtained one half of the Hamiltonian equations for the higher flows

$$\partial_{t_m} x_i = \frac{\partial H_m}{\partial p_i}, \quad H_m = -\frac{\sinh(m\gamma\eta)}{m\gamma\eta} \operatorname{tr} L^m, \quad (4.3)$$

where the Lax matrix L is given by (1.2). In particular, the Hamiltonian H_1 coincides with (3.20).

The derivation of the second half of the Hamiltonian equations is more involved. The idea of the derivation is the same as in [14]. First of all, we note that (4.3) can be written in the form

$$\partial_{t_m} x_i = -m\eta\kappa_m \operatorname{tr}(E_i L^m), \quad \kappa_m = \frac{\sinh(m\gamma\eta)}{m\gamma\eta}.$$

Differentiating this equality with respect to t_1 and using the Lax equation, we get:

$$\partial_{t_m} \dot{x}_i = -m\eta\kappa_m \operatorname{tr}(E_i[M', L^m]) = -m\eta\kappa_m \operatorname{tr}(L^m[E_i, M']).$$

Now we apply ∂_{t_m} to equation (3.21):

$$\begin{aligned} \partial_{t_m} p_i &= \eta^{-1} \partial_{t_m} \log \dot{x}_i - \eta^{-1} \sum_j \sum_{l \neq i} \frac{\partial}{\partial x_j} \log \frac{\sinh(\gamma(x_{il} + \eta))}{\sinh(\gamma x_{il})} \partial_{t_m} x_j \\ &= -m\kappa_m \dot{x}_i^{-1} \operatorname{tr}(L^m[E_i, M']) + m\kappa_m \sum_j \sum_{l \neq i} \frac{\partial}{\partial x_j} \log \frac{\sinh(\gamma(x_{il} + \eta))}{\sinh(\gamma x_{il})} \operatorname{tr}(E_j L^m) \\ &= -m\kappa_m \operatorname{tr}(A^{(i)} L^{m-1}), \end{aligned}$$

where the matrix $A^{(i)}$ is

$$A^{(i)} = \dot{x}_i^{-1} (L E_i M' - M' E_i L) - \sum_j \sum_{l \neq i} \frac{\partial}{\partial x_j} \log \frac{\sinh(\gamma(x_{il} + \eta))}{\sinh(\gamma x_{il})} E_j L. \quad (4.4)$$

Note that the diagonal part of the matrix M' (3.19) does not contribute, so instead of the matrix M' here we can substitute its off-diagonal part

$$A_{ij} = 2\gamma(1 - \delta_{ij}) \frac{\dot{x}_i w_i^{1/2} w_j^{1/2}}{w_i - w_j}.$$

Let us calculate the matrix elements:

$$\begin{aligned} (L E_i A)_{jk} &= \gamma \dot{x}_i L_{jk} \left(\frac{w_i + w_k}{w_i - w_k} - \frac{q w_i + w_k}{q w_i - w_k} \right) (1 - \delta_{ik}), \\ (A E_i L)_{jk} &= -\gamma \dot{x}_i L_{jk} \left(\frac{w_i + w_j}{w_i - w_j} - \frac{w_i + q w_k}{w_i - q w_k} \right) (1 - \delta_{ij}), \\ &\quad \sum_l \sum_{r \neq i} \frac{\partial}{\partial x_l} \log \frac{\sinh(\gamma(x_{lr} + \eta))}{\sinh(\gamma x_{lr})} (E_l L)_{jk} \\ &= \gamma \delta_{ij} L_{jk} \sum_{r \neq i} \left(\frac{q w_i + w_r}{q w_i - w_r} - \frac{w_i + w_r}{w_i - w_r} \right) - \gamma (1 - \delta_{ij}) L_{jk} \left(\frac{q w_i + w_j}{q w_i - w_j} - \frac{w_i + w_j}{w_i - w_j} \right). \end{aligned}$$

Combining everything together, we obtain the matrix elements of the matrix $A^{(i)}$:

$$A_{jk}^{(i)} = \gamma L_{jk} \left(\frac{w_i + w_k}{w_i - w_k} (1 - \delta_{ik}) - \frac{w_i + qw_k}{w_i - qw_k} (1 - \delta_{ij}) + \frac{qw_i + w_j}{qw_i - w_j} (\delta_{ik} - \delta_{ij}) - \delta_{ij} \sum_{r \neq i} \left(\frac{qw_i + w_r}{qw_i - w_r} - \frac{w_i + w_r}{w_i - w_r} \right) \right). \quad (4.5)$$

Our next goal is to prove that

$$A^{(i)} = -\frac{\partial L}{\partial x_i} - [C^{(i)}, L], \quad (4.6)$$

where the matrix $C^{(i)}$ is given by

$$C^{(i)} = \gamma \sum_l \frac{qw_l + w_i}{qw_l - w_i} E_l - \gamma \sum_{l \neq i} \frac{w_l + w_i}{w_l - w_i} E_l. \quad (4.7)$$

From this one concludes that

$$\partial_{t_m} p_i = -m\kappa_m \operatorname{tr} \left(A^{(i)} L^{m-1} \right) = m\kappa_m \operatorname{tr} \left(\frac{\partial L}{\partial x_i} L^{m-1} \right) = \kappa_m \frac{\partial}{\partial x_i} \operatorname{tr} L^m.$$

This yields the second half of the Hamiltonian equations for the higher flows:

$$\partial_{t_m} p_i = -\frac{\partial H_m}{\partial x_i}. \quad (4.8)$$

In order to prove the identity (4.6), we calculate matrix elements of the right hand side and compare them with (4.5). Indeed, we have:

$$\begin{aligned} \frac{\partial L_{jk}}{\partial x_i} &= \gamma L_{jk} \left(\frac{w_j + qw_k}{w_j - qw_k} (\delta_{ik} - \delta_{ij}) + \frac{w_i + qw_j}{w_i - qw_j} (1 - \delta_{ij}) - \frac{w_i + w_j}{w_i - w_j} (1 - \delta_{ij}) \right. \\ &\quad \left. + \delta_{ij} \sum_{r \neq i} \left(\frac{qw_i + w_r}{qw_i - w_r} - \frac{w_i + w_r}{w_i - w_r} \right) \right), \\ [C^{(i)}, L]_{jk} &= \gamma L_{jk} \left(\frac{qw_j + w_i}{qw_j - w_i} - \frac{qw_k + w_i}{qw_k - w_i} - \frac{w_j + w_i}{w_j - w_i} (1 - \delta_{ij}) + \frac{w_k + w_i}{w_k - w_i} (1 - \delta_{ik}) \right), \end{aligned}$$

and one can check that $A^{(i)} + \partial L / \partial x_i + [C^{(i)}, L] = 0$.

4.2 Negative times

In order to investigate the dynamics of zeros of the tau-function in the negative times, we first consider the \bar{t}_1 -evolution. We will work with the complimentary wave functions ϕ, ϕ^\dagger given by (2.32), (2.33) for which we use the ansatz

$$\phi(x) = z^{x/\eta} e^{\bar{t}_1 z^{-1}} \left(1 + \sum_i \frac{2\gamma b_i}{qw - w_i} \right), \quad (4.9)$$

$$\phi^\dagger(x) = z^{-x/\eta} e^{-\bar{t}_1 z^{-1}} \left(1 + \sum_i \frac{2\gamma b_i^*}{q^{-1}w - w_i} \right), \quad (4.10)$$

where b_i, b_i^* are some unknown coefficients depending on the times and on z but not on x . Substituting them into the linear equations (2.34), we can write down the conditions of cancellation of the poles in the way similar to that of section 3. In fact the equations for b_i are the same as for c_i^* up to changing z to $-z^{-1}$, w to qw and ∂_{t_1} to $\partial_{\bar{t}_1}$. The equations for b_i^* and c_i are connected in a similar way. Passing to $\tilde{b}_i = w_i^{-1/2} b_i$, $\tilde{b}_i^* = w_i^{-1/2} b_i^*$, we have, after some algebra, in the notation of section 3:

$$\tilde{\mathbf{b}}^T (\partial_{\bar{t}_1} X)^{-1} (z^{-1} I + q^{-1/2} \bar{L}) = \mathbf{e}^T W^{1/2}, \quad (4.11)$$

$$(z^{-1} I + q^{1/2} \bar{L}) \tilde{\mathbf{b}}^* = -\partial_{\bar{t}_1} X W^{1/2} \mathbf{e}, \quad (4.12)$$

where $\tilde{\mathbf{b}}^T = (\tilde{b}_1, \dots, \tilde{b}_N)$, $\tilde{\mathbf{b}}^* = (\tilde{b}_1^*, \dots, \tilde{b}_N^*)$ and the matrix \bar{L} reads

$$\bar{L}_{ij} = 2\gamma q^{1/2} \frac{\partial_{\bar{t}_1} x_i w_i^{1/2} w_j^{1/2}}{w_i - qw_j}. \quad (4.13)$$

This matrix satisfies the commutation relation (3.15) with $\partial_{\bar{t}_1} W$ instead of $\dot{W} = \partial_{t_1} W$:

$$q^{-1/2} W \bar{L} - q^{1/2} \bar{L} W = W^{-1/2} \partial_{\bar{t}_1} W E W^{1/2}. \quad (4.14)$$

Using the relation (2.37), we find, similarly to (4.1):

$$\partial_{\bar{t}_m} x_i = -2\gamma \operatorname{res}_0 \left(z^{-m-2} \tilde{b}_i^* (\partial_{\bar{t}_1} w_i)^{-1} \tilde{b}_i \right). \quad (4.15)$$

Substituting here the solutions of linear systems (4.11), (4.12) and using (4.14), one can repeat the calculation from section 4.1 with the result

$$\partial_{\bar{t}_m} x_i = (-1)^m \frac{\sinh(m\gamma\eta)}{\gamma} \operatorname{tr} (E_i \bar{L}^m). \quad (4.16)$$

Our next goal is to derive a relation between the Lax matrices L and \bar{L} . For this, we need a relation between the velocities $\dot{x}_i = \partial_{t_1} x_i$ and $\partial_{\bar{t}_1} x_i$. The latter can be derived from the Toda equation (2.27). Substituting the tau-function in the form $\tau = \prod_i (w - w_i)$, we get

$$-\sum_i \frac{\partial_{t_1} \partial_{\bar{t}_1} w_i}{w - w_i} - \sum_i \frac{\partial_{t_1} w_i \partial_{\bar{t}_1} w_i}{(w - w_i)^2} = 1 - \prod_k \frac{(qw - w_k)(q^{-1}w - w_k)}{(w - w_k)^2}.$$

Identifying the second order poles in the both sides, we obtain the relation

$$\partial_{t_1} w_i \partial_{\bar{t}_1} w_i = \frac{\prod_k (qw_i - w_k)(q^{-1}w_i - w_k)}{\prod_{l \neq i} (w_i - w_l)^2} \quad (4.17)$$

or

$$\partial_{t_1} X \partial_{\bar{t}_1} X = \frac{1}{4\gamma^2} W^{-2} U_+ U_-, \quad (4.18)$$

where the diagonal matrices U_\pm are

$$(U_\pm)_{ij} = \delta_{ij} \frac{\prod_k (w_i - q^{\pm 1} w_k)}{\prod_{l \neq i} (w_i - w_l)}. \quad (4.19)$$

Next, we need the formula for the inverse of the Cauchy matrix

$$C_{ij} = \frac{1}{w_i - qw_j}. \quad (4.20)$$

We have:

$$C_{ij}^{-1} = \frac{1}{qw_i - w_j} \frac{\prod_k (qw_i - w_k)(w_j - qw_k)}{q^{N-1} \prod_{l \neq j} (w_j - w_l) \prod_{l' \neq i} (w_i - w_{l'})} \quad (4.21)$$

or

$$C^{-1} = -qU_- C^T U_+. \quad (4.22)$$

Now we write $L = 2\gamma q^{1/2} \partial_{t_1} X W^{1/2} C W^{1/2}$ and find, using (4.22), (4.18):

$$\begin{aligned} L^{-1} &= \frac{q^{-1/2}}{2\gamma} W^{-1/2} C^{-1} W^{-1/2} (\partial_{t_1} X)^{-1} \\ &= -2\gamma q^{1/2} W^{-1/2} U_- C^T W^{-1/2} \partial_{t_1} X W^2 U_-^{-1} \\ &= -2\gamma q^{1/2} W^{-1} U_- (\partial_{t_1} X W^{1/2} C W^{1/2})^T (W^{-1} U_-)^{-1} \\ &= -W^{-1} U_- \bar{L}^T (W^{-1} U_-)^{-1}. \end{aligned}$$

We see that the matrix $-\bar{L}^T$ is connected with L^{-1} by a similarity transformation with a diagonal matrix. Using the fact that $E_i \bar{L} = -\eta^{-1} \partial \bar{L} / \partial p_i$, we can therefore rewrite equation (4.16) as

$$\partial_{\bar{t}_m} x_i = -\frac{\sinh(m\gamma\eta)}{m\gamma\eta} \frac{\partial}{\partial p_i} \text{tr} L^{-m} = \frac{\partial \bar{H}_m}{\partial p_i} \quad (4.23)$$

which is one half of the Hamiltonian equations for the negative time flows.

The derivation of the second half is straightforward. We note that

$$\partial_{\bar{t}_m} x_i = m\eta\kappa_m \text{tr} (E_i L^{-m}),$$

where we use the notation of section 4.1. In the complete analogy with the calculation in the previous subsection, we have

$$\partial_{\bar{t}_m} p_i = m\kappa_m \text{tr} (A^{(i)} L^{-m-1})$$

with the same matrix $A^{(i)}$ (4.4). By virtue of (4.6) we obtain:

$$\partial_{\bar{t}_m} p_i = -m\kappa_m \text{tr} \left(\frac{\partial L}{\partial x_i} L^{-m-1} \right) = m\kappa_m \text{tr} \left(\frac{\partial L^{-1}}{\partial x_i} (L^{-1})^{m-1} \right) = \kappa_m \frac{\partial}{\partial x_i} \text{tr} L^{-m},$$

which are the Hamiltonian equations

$$\partial_{\bar{t}_m} p_i = -\frac{\partial \bar{H}_m}{\partial x_i} \quad (4.24)$$

with \bar{H}_m given by (1.4). In particular,

$$\bar{H}_1 = \frac{\sinh^2(\gamma\eta)}{\gamma^2\eta^2} \sum_i e^{-\eta p_i} \prod_{k \neq i} \frac{\sinh(\gamma(x_{ik} - \eta))}{\sinh(\gamma x_{ik})}. \quad (4.25)$$

5 The generating form of equations of motion in higher times

In the above analysis we parametrized the wave function by residues at its poles. Another possible parametrization is by zeros and poles. It leads to the so-called self-dual form of equations of motion. In this section we derive these equations and show that they provide a generating form of equations of motion for the Ruijsenaars-Schneider model in the higher times.

In this section we keep the negative times $\bar{\mathbf{t}}$ fixed and consider only the dependence on \mathbf{t} . In accordance with (2.28) we have $\psi(\mu, x, \mathbf{t}) = \mu^{x/\eta} e^{\xi(\mathbf{t}, \mu)} \hat{\tau}(x, \mathbf{t}) / \tau(x, \mathbf{t})$ (here $\hat{\tau}(x, \mathbf{t}) = \tau(x, \mathbf{t} - [\mu^{-1}])$), then the auxiliary linear problem (2.17) acquires the form

$$\partial_{t_1} \log \frac{\hat{\tau}(x)}{\tau(x + \eta)} = \mu \frac{\hat{\tau}(x + \eta) \tau(x)}{\tau(x + \eta) \hat{\tau}(x)} - \mu. \quad (5.1)$$

For trigonometric solutions τ is of the form (3.1) and for $\hat{\tau}$ we write

$$\hat{\tau} = \prod_i (e^{2\gamma x} - e^{2\gamma y_i}) = \prod_i (w - v_i), \quad v_i = e^{2\gamma y_i}, \quad (5.2)$$

parametrizing it by its zeros y_i . Substituting this into (5.1), we have:

$$\sum_i \frac{\dot{w}_i}{qw - w_i} - \sum_i \frac{\dot{v}_i}{w - v_i} = \mu \prod_k \frac{(w - w_k)(qw - v_k)}{(w - v_k)(qw - w_k)} - \mu.$$

Identifying residues at the simple poles at $w = q^{-1}w_i$ and $w = v_i$, we get the system of equations

$$\begin{cases} 2\gamma \dot{x}_i = \mu(1 - q) \prod_{j \neq i} \frac{w_i - qw_j}{w_i - w_j} \prod_k \frac{w_i - v_k}{w_i - qv_k} \\ 2\gamma \dot{y}_i = \mu(1 - q) \prod_{j \neq i} \frac{qv_i - v_j}{v_i - v_j} \prod_k \frac{v_i - w_k}{qv_i - w_k} \end{cases} \quad (5.3)$$

or

$$\begin{cases} \gamma \dot{x}_i = -\mu \sinh(\gamma\eta) \prod_{j \neq i} \frac{\sinh(\gamma(x_i - x_j - \eta))}{\sinh(\gamma(x_i - x_j))} \prod_k \frac{\sinh(\gamma(x_i - y_k))}{\sinh(\gamma(x_i - y_k - \eta))} \\ \gamma \dot{y}_i = -\mu \sinh(\gamma\eta) \prod_{j \neq i} \frac{\sinh(\gamma(y_i - y_j + \eta))}{\sinh(\gamma(y_i - y_j))} \prod_k \frac{\sinh(\gamma(y_i - x_k))}{\sinh(\gamma(y_i - x_k + \eta))} \end{cases} \quad (5.4)$$

This is the Ruijsenaars-Schneider analog of the Bäcklund transformation for the Calogero-Moser system [22, 23]. These equations appeared in [24] in the context of the integrable time discretization of the Ruijsenaars-Schneider model (see also [25, 26]). One can show that the equations of motion of the Ruijsenaars-Schneider model for x_i 's follow from (5.4) and y_i 's obey the same equations (for the proof see [25]).

At the same time these equations contain all the higher equations of motion in an encoded form. To see this, we introduce the differential operator

$$D(\mu) = \sum_{k \geq 1} \frac{\mu^{-k}}{k} \partial_{t_k}, \quad (5.5)$$

then $\hat{\tau} = e^{-D(\mu)}\tau$ and $y_i = e^{-D(\mu)}x_i$. Performing an overall time shift in the second equation in (5.4), we can rewrite them in the form

$$\begin{cases} \gamma\dot{x}_i = -\mu \sinh(\gamma\eta) \prod_{j \neq i} \frac{\sinh(\gamma(x_i - x_j - \eta))}{\sinh(\gamma(x_i - x_j))} \prod_k \frac{\sinh(\gamma(x_i - e^{-D(\mu)}x_k))}{\sinh(\gamma(x_i - e^{-D(\mu)}x_k - \eta))} \\ \gamma\dot{x}_i = -\mu \sinh(\gamma\eta) \prod_{j \neq i} \frac{\sinh(\gamma(x_i - x_j + \eta))}{\sinh(\gamma(x_i - x_j))} \prod_k \frac{\sinh(\gamma(x_i - e^{D(\mu)}x_k))}{\sinh(\gamma(x_i - e^{D(\mu)}x_k + \eta))}. \end{cases} \quad (5.6)$$

Dividing one equation by the other, we obtain the equations

$$\prod_{k=1}^N \frac{\sinh(\gamma(x_i - e^{D(\mu)}x_k))}{\sinh(\gamma(x_i - e^{D(\mu)}x_k + \eta))} \frac{\sinh(\gamma(x_i - x_k + \eta))}{\sinh(\gamma(x_i - x_k - \eta))} \frac{\sinh(\gamma(x_i - e^{-D(\mu)}x_k - \eta))}{\sinh(\gamma(x_i - e^{-D(\mu)}x_k))} = -1 \quad (5.7)$$

which are, on one hand, equations of motion for the Ruijsenaars-Schneider system in discrete time (see [27]) and, on the other, provide the generating form of the higher equations of motion in continuous hierarchical times. Indeed, expanding (5.7) in (inverse) powers of μ , one gets the set of the higher equations of motion. In particular, equations (3.17) are obtained by expansion of (5.7) up to μ^{-1} .

6 The tau-function for trigonometric solutions

In this section we prove the determinant formula for the tau-function of trigonometric solutions

$$\tau'(x, \mathbf{t}, \bar{\mathbf{t}}) = \det_{N \times N} \left(wI - \exp \left(\sum_{k \geq 1} (q^{-k/2} - q^{k/2})(t_k L_0^k - \bar{t}_k L_0^{-k}) \right) W_0 \right), \quad (6.1)$$

where $L_0 = L(0)$, $W_0 = W(0)$. We recall that the tau-function τ' is connected with τ by formula (2.24).

The matrix $\exp \left(\sum_{k \geq 1} (q^{-k/2} - q^{k/2})(t_k L_0^k - \bar{t}_k L_0^{-k}) \right) W_0$ can be diagonalized with the help of a diagonalizing matrix V :

$$V \exp \left(\sum_{k \geq 1} (q^{-k/2} - q^{k/2})(t_k L_0^k - \bar{t}_k L_0^{-k}) \right) W_0 V^{-1} = W.$$

There is a freedom in the definition of V : it can be multiplied by a diagonal matrix from the left. We fix this freedom by the condition

$$\mathbf{e}^T W_0^{1/2} = \mathbf{e}^T W^{1/2} V. \quad (6.2)$$

The matrices W_0 , L_0 satisfy the commutation relation (3.15) which we write here in the form

$$q^{-1/2} W_0^{1/2} L_0 W_0^{-1/2} - q^{1/2} W_0^{-1/2} L_0 W_0^{1/2} = W_0^{-1} \dot{W}_0 \mathbf{e} \otimes \mathbf{e}^T. \quad (6.3)$$

Let us prove, following [24], that the matrices W and $L = V L_0 V^{-1}$ satisfy the same commutation relation. We have:

$$q^{-1/2} W^{1/2} L W^{-1/2} - q^{1/2} W^{-1/2} L W^{1/2} = W^{1/2} (q^{-1/2} L - q^{1/2} W^{-1} L W) W^{-1/2}$$

$$\begin{aligned}
&= W^{1/2} \left(q^{-1/2} V L_0 V^{-1} - q^{1/2} V W_0^{-1} L_0 W_0 V^{-1} \right) W^{-1/2} \\
&= W^{1/2} V W_0^{-1/2} \left(q^{-1/2} W_0^{1/2} L_0 W_0^{-1/2} - q^{1/2} W_0^{-1/2} L_0 W_0^{1/2} \right) W_0^{1/2} V^{-1} W^{-1/2} \\
&= W^{1/2} V W_0^{-3/2} \dot{W}_0 \mathbf{e} \otimes \mathbf{e}^T W_0^{1/2} V^{-1} W^{-1/2} \\
&= W^{1/2} V W_0^{-3/2} \dot{W}_0 \mathbf{e} \otimes \mathbf{e}^T.
\end{aligned}$$

(The last equality follows from the condition (6.2).) Denoting $W^{3/2} V W_0^{-3/2} \dot{W}_0 \mathbf{e} = \dot{W} \mathbf{e}$, we arrive at the desired commutation relation.

We are going to prove that the function (6.1) satisfies the bilinear equations (2.22), (2.23) of the 2DTL hierarchy. We begin with equation (2.22):

$$\begin{aligned}
&\mu \frac{\tau(x + \eta, \mathbf{t} + [\lambda^{-1}] - [\mu^{-1}])}{\tau(x + \eta, \mathbf{t})} - \lambda \frac{\tau(x, \mathbf{t} + [\lambda^{-1}] - [\mu^{-1}])}{\tau(x, \mathbf{t})} \\
&+ (\lambda - \mu) \frac{\tau(x + \eta, \mathbf{t} + [\lambda^{-1}])}{\tau(x + \eta, \mathbf{t})} \frac{\tau(x, \mathbf{t} - [\mu^{-1}])}{\tau(x, \mathbf{t})} = 0.
\end{aligned} \tag{6.4}$$

(Here and below in the proof we put $\bar{\mathbf{t}} = 0$ and identify τ and τ' .) The similarity transformation with the matrix V under the determinant in (6.1) allows one to write the following formulas:

$$\begin{aligned}
&\tau(x, \mathbf{t}) = \det(wI - W), \tag{6.5} \\
\tau(x, \mathbf{t} + [\lambda^{-1}]) &= \det \left(wI - \frac{\lambda I - q^{1/2} L}{\lambda I - q^{-1/2} L} W \right) = \frac{\det(w(\lambda I - q^{-1/2} L) - (\lambda I - q^{1/2} L)W)}{\det(\lambda I - q^{-1/2} L)} \\
&= \frac{\det((wI - W)(\lambda I - q^{-1/2} L) - \tilde{E})}{\det(\lambda I - q^{-1/2} L)} = \tau(x, \mathbf{t}) \left(1 - \text{tr} \left(\frac{1}{\lambda I - q^{-1/2} L} \frac{1}{wI - W} \tilde{E} \right) \right),
\end{aligned}$$

where the matrix $\tilde{E} = W^{-1/2} \dot{W} E W^{1/2}$ has rank 1 and we have used the commutation relation (3.15) and the formula $\det(I + A) = 1 + \text{tr} A$ valid for any rank 1 matrix A . Similar calculations yield

$$\begin{aligned}
&\tau(x, \mathbf{t} - [\mu^{-1}]) = \tau(x, \mathbf{t}) \left(1 + \text{tr} \left(\frac{1}{wI - W} \frac{1}{\mu I - q^{1/2} L} \tilde{E} \right) \right), \\
\tau(x, \mathbf{t} + [\lambda^{-1}] - [\mu^{-1}]) &= \det \left(wI - \frac{\lambda I - q^{1/2} L}{\lambda I - q^{-1/2} L} \frac{\mu I - q^{-1/2} L}{\mu I - q^{1/2} L} W \right) \\
&= \det \left(wI - \frac{\lambda I - q^{1/2} L}{\lambda I - q^{-1/2} L} W \frac{\mu I - q^{-1/2} L}{\mu I - q^{1/2} L} \right) \\
&= \frac{\det(w(\lambda I - q^{-1/2} L)(\mu I - q^{1/2} L) - (\lambda I - q^{1/2} L)W(\mu I - q^{-1/2} L))}{\det(\lambda I - q^{-1/2} L) \det(\mu I - q^{1/2} L)} \\
&= \frac{\det((\mu I - q^{1/2} L)(wI - W)(\lambda I - q^{-1/2} L) + (\lambda - \mu)\tilde{E})}{\det(\lambda I - q^{-1/2} L) \det(\mu I - q^{1/2} L)} \\
&= \tau(x, \mathbf{t}) \left[1 + (\lambda - \mu) \text{tr} \left(\frac{1}{\lambda I - q^{-1/2} L} \frac{1}{wI - W} \frac{1}{\mu I - q^{1/2} L} \tilde{E} \right) \right].
\end{aligned}$$

Substituting everything into the left hand side of (6.4), we obtain:

$$\begin{aligned}
& \text{LHS of (6.4)} \propto q^{-1} \mu \operatorname{tr} \left[\frac{1}{\lambda I - q^{-1/2} L} \frac{1}{wI - q^{-1} W} \frac{1}{\mu I - q^{1/2} L} \tilde{E} \right] \\
& \quad - \lambda \operatorname{tr} \left[\frac{1}{\lambda I - q^{-1/2} L} \frac{1}{wI - W} \frac{1}{\mu I - q^{1/2} L} \tilde{E} \right] \\
& + \operatorname{tr} \left[\frac{1}{wI - W} \frac{1}{\mu I - q^{1/2} L} \tilde{E} \right] - q^{-1} \operatorname{tr} \left[\frac{1}{\lambda I - q^{-1/2} L} \frac{1}{wI - q^{-1} W} \tilde{E} \right] \\
& - q^{-1} \operatorname{tr} \left[\frac{1}{wI - W} \frac{1}{\mu I - q^{1/2} L} \tilde{E} \right] \operatorname{tr} \left[\frac{1}{\lambda I - q^{-1/2} L} \frac{1}{wI - q^{-1} W} \tilde{E} \right].
\end{aligned}$$

This expression is a rational function of w with simple poles at $w = w_i$ and $w = q^{-1}w_i$ vanishing at ∞ . To prove that it actually vanishes identically it is enough to prove that the residues at the poles are zero. The residue at the pole at $w = w_i$ is equal to

$$\begin{aligned}
& -\lambda \sum_{j,k} \left(\frac{1}{\lambda I - q^{-1/2} L} \right)_{ji} \left(\frac{1}{\mu I - q^{1/2} L} \right)_{ik} w_k^{-1/2} \dot{w}_k w_j^{1/2} + \sum_j \left(\frac{1}{\mu I - q^{1/2} L} \right)_{ij} w_j^{-1/2} \dot{w}_j w_i^{1/2} \\
& - \sum_{j,k,k'} \left(\frac{1}{\mu I - q^{1/2} L} \right)_{ij} w_j^{-1/2} \dot{w}_j w_i^{1/2} \left(\frac{1}{\lambda I - q^{-1/2} L} \right)_{kk'} \frac{w_{k'}^{-1/2} \dot{w}_{k'} w_k^{1/2}}{q w_i - w_{k'}}.
\end{aligned}$$

Recalling that $L_{ij} = q^{1/2} \frac{\dot{w}_i w_i^{-1/2} w_j^{1/2}}{w_i - q w_j}$, we can rewrite the last line (the triple sum) in the form

$$\sum_{j,k} \left(\frac{1}{\mu I - q^{1/2} L} \right)_{ij} w_j^{-1/2} \dot{w}_j w_k^{1/2} \left(\frac{q^{-1/2} L}{\lambda I - q^{-1/2} L} \right)_{ki}$$

from which it is seen that the residue is zero. The calculation for the residue at $w = q^{-1}w_i$ is similar.

The fact that the function (6.1) is a KP tau-function with respect to the times \mathbf{t} follows also from the result of Kasman and Gekhtman [28]: for any matrices X, Y, Z such that the matrix $XZ - YX$ has rank 1 the function

$$\tau = \det \left(X \exp \left(\sum_{k \geq 1} t_k Z^k \right) + \exp \left(\sum_{k \geq 1} t_k Y^k \right) \right) \quad (6.6)$$

is a tau-function of the KP hierarchy. In our case $X = -W_0$, $Z = q^{-1/2} L_0$, $Y = q^{1/2} L_0$ and the condition that $XZ - YX$ has rank 1 is equivalent to the commutation relation (3.15).

Let us pass to the proof of equation (2.23) which we write here in the equivalent form

$$\begin{aligned}
& \frac{\tau'(x, \mathbf{t} + [\lambda^{-1}], \bar{\mathbf{t}} - [\nu])}{\tau'(x - \eta, \mathbf{t}, \bar{\mathbf{t}})} - \frac{\nu}{\lambda} \frac{\tau'(x + \eta, \mathbf{t} + [\lambda^{-1}], \bar{\mathbf{t}} - [\nu])}{\tau'(x, \mathbf{t}, \bar{\mathbf{t}})} \\
& - \left(1 - \frac{\nu}{\lambda} \right) \frac{\tau'(x, \mathbf{t}, \bar{\mathbf{t}} - [\nu])}{\tau'(x - \eta, \mathbf{t}, \bar{\mathbf{t}})} \frac{\tau'(x, \mathbf{t} + [\lambda^{-1}])}{\tau'(x, \mathbf{t}, \bar{\mathbf{t}})} = 0.
\end{aligned} \quad (6.7)$$

The calculations similar to the ones done above yield:

$$\begin{aligned}\tau'(x, \mathbf{t} + [\lambda^{-1}], \bar{\mathbf{t}}) &= \tau'(x, \mathbf{t}, \bar{\mathbf{t}}) \left(1 - \text{tr} \left(\frac{1}{\lambda I - q^{-1/2}L} \frac{1}{wI - W} \tilde{E} \right) \right), \\ \tau'(x, \mathbf{t}, \bar{\mathbf{t}} - [\nu]) &= q^N \tau'(x - \eta, \mathbf{t}, \bar{\mathbf{t}}) \left(1 + \text{tr} \left(\frac{q}{wI - qW} \frac{1}{\nu I - q^{1/2}L} \tilde{E} \right) \right), \\ \tau'(x, \mathbf{t} + [\lambda^{-1}], \bar{\mathbf{t}} - [\nu]) &= q^N \tau'(x - \eta, \mathbf{t}, \bar{\mathbf{t}}) \\ &\quad \times \left(1 + (\lambda - \nu) \text{tr} \left(\frac{1}{\lambda I - q^{-1/2}L} \frac{q}{wI - qW} \frac{1}{\nu I - q^{1/2}L} \tilde{E} \right) \right).\end{aligned}$$

Using the results of the above calculation, it is not difficult to see that the substitution into (6.7) gives the identity, so the equation (2.23) is proved.

7 Conclusion

The main result of this paper is establishing the precise correspondence between trigonometric solutions of the 2D Toda lattice hierarchy and the hierarchy of the Hamiltonian equations for the integrable Ruijsenaars-Schneider model with higher Hamiltonians. The zeros of the tau-function move as particles of the Ruijsenaars-Schneider model. We have shown that the m th time flow t_m of the 2DTL hierarchy gives rise to the flow with the Hamiltonian H_m of the Ruijsenaars-Schneider model proportional to $\text{tr} L^m$, where L is the Lax matrix, while the time flow \bar{t}_m gives rise to the Hamiltonian flow with the Hamiltonian \bar{H}_m proportional to $\text{tr} L^{-m}$. In some sense this correspondence is simpler and more natural than a similar correspondence between the KP hierarchy and trigonometric Calogero-Moser hierarchy [11], which in principle can be obtained from our results in the limit $\eta \rightarrow 0$.

Acknowledgments

The work of V.P. was supported in part by RFBR grant 18-01-00273. The research of A.Z. was carried out within the HSE University Basic Research Program and funded (jointly) by the Russian Academic Excellence Project '5-100'. The work of A.Z. was also supported in part by RFBR grant 18-01-00461.

References

- [1] H. Airault, H.P. McKean, and J. Moser, *Rational and elliptic solutions of the Korteweg-De Vries equation and a related many-body problem*, Commun. Pure Appl. Math., **30** (1977) 95-148.
- [2] F. Calogero, *Solution of the one-dimensional N -body problems with quadratic and/or inversely quadratic pair potentials*, J. Math. Phys. **12** (1971) 419-436.

- [3] F. Calogero, *Exactly solvable one-dimensional many-body systems*, Lett. Nuovo Cimento **13** (1975) 411-415.
- [4] J. Moser, *Three integrable Hamiltonian systems connected with isospectral deformations*, Adv. Math. **16** (1975) 197-220.
- [5] M.A. Olshanetsky and A.M. Perelomov, *Classical integrable finite-dimensional systems related to Lie algebras*, Phys. Rep. **71** (1981) 313-400.
- [6] I.M. Krichever, *Rational solutions of the Kadomtsev-Petviashvili equation and integrable systems of N particles on a line*, Funct. Anal. Appl. **12:1** (1978) 59-61.
- [7] D.V. Chudnovsky, G.V. Chudnovsky, *Pole expansions of non-linear partial differential equations*, Nuovo Cimento **40B** (1977) 339-350.
- [8] I.M. Krichever, *Elliptic solutions of the Kadomtsev-Petviashvili equation and integrable systems of particles*, Funk. Anal. i Ego Pril. **14:4** (1980) 45-54 (in Russian); English translation: Functional Analysis and Its Applications **14:4** (1980) 282-290.
- [9] T. Shiota, *Calogero-Moser hierarchy and KP hierarchy*, J. Math. Phys. **35** (1994) 5844-5849.
- [10] L. Haine, *KP trigonometric solitons and an adelic flag manifold*, SIGMA **3** (2007) 015.
- [11] A. Zabrodin, *KP hierarchy and trigonometric Calogero-Moser hierarchy*, arXiv:1906.09846.
- [12] I. Krichever, A. Zabrodin, *Spin generalization of the Ruijsenaars-Schneider model, non-abelian 2D Toda chain and representations of Sklyanin algebra*, Uspekhi Math. Nauk, **50** (1995) 3-56.
- [13] S. N. M. Ruijsenaars and H. Schneider, *A new class of integrable systems and its relation to solitons*, Ann. Phys. **170** (1986) 370-405.
- [14] P. Iliev, *Rational Ruijsenaars-Schneider hierarchy and bispectral difference operators*, Physica D **229** (2007), no. 2, 184-190, arXiv:math-ph/0609011.
- [15] A. Zabrodin, *The master T -operator for inhomogeneous XXX spin chain and mKP hierarchy*, SIGMA **10** (2014), 006.
- [16] K. Ueno and K. Takasaki, *Toda lattice hierarchy*, Adv. Studies in Pure Math. **4** (1984) 1-95.
- [17] A. Zabrodin, *On matrix modified Kadomtsev-Petviashvili hierarchy*, Teor. Mat. Fys. **199** (2019) 343-356 (English translation: Matrix modified Kadomtsev-Petviashvili hierarchy, Theor. Math. Phys. **199** (2019) 771-783, arXiv:1802.02797).
- [18] E. Date, M. Jimbo, M. Kashiwara and T. Miwa, *Transformation groups for soliton equations: Nonlinear integrable systems – classical theory and quantum theory* (Kyoto, 1981). Singapore: World Scientific, 1983, 39-119.

- [19] M. Jimbo and T. Miwa, *Solitons and infinite dimensional Lie algebras*, Publ. Res. Inst. Math. Sci. Kyoto **19** (1983) 943-1001.
- [20] K. Takasaki and T. Takebe, *Integrable hierarchies and dispersionless limit*, Rev. Math. Phys. **7** (1995) 743-808.
- [21] S.N.M. Ruijsenaars, *Complete integrability of relativistic Calogero-Moser systems and elliptic function identities*, Commun. Math. Phys. **110** (1987) 191-213.
- [22] S. Wojciechowski, *The analogue of the Bäcklund transformation for integrable many-body systems*, J. Phys. A: Math. Gen. **15** (1982) L653-L657.
- [23] A. Abanov, E. Bettelheim and P. Wiegmann, *Integrable hydrodynamics of Calogero-Sutherland model: Bidirectional Benjamin-Ono equation*, J. Phys. A **42** (2009) 135201.
- [24] Yu. Suris, *The Problem of Integrable Discretization: Hamiltonian Approach*, Springer Basel AG, 2003.
- [25] A. Zabrodin and A. Zotov, *Self-dual form of Ruijsenaars-schneider models and ILW equation with discrete Laplacian*, Nuclear Physics B **927** (2018) 550-565.
- [26] A. Zabrodin, *Elliptic solutions to integrable nonlinear equations and many-body systems*, arXiv:1905.11383.
- [27] F.W. Nijhoff, O. Ragnisco and V. Kuznetsov, *Integrable time-discretization of the Ruijsenaars-Schneider model*, Commun. Math. Phys. **176** (1996) 681-700.
- [28] A. Kasman and M. Gekhtman, *Solitons and almost-intertwining matrices*, J. Math. Phys. **42** (2001) 3540-3551.