

# On the discretization of Darboux Integrable Systems admitting the second-order integrals.

Kostyantyn Zheltukhin<sup>1</sup>

Department of Mathematics, Middle East Technical University, Ankara, Turkey

Natalya Zheltukhina<sup>2</sup>

Department of Mathematics, Faculty of Science, Bilkent University, Ankara, Turkey

**Abstract** *We study discretization of Darboux integrable systems. The discretization is done by using  $x$ - or  $y$ -integrals of the considered systems. New examples of semi-discrete Darboux integrable systems are obtained.*

*Keywords:* semi-discrete system, Darboux integrability,  $x$ -integral,  $n$ -integral, discretization.

## 1 Introduction

In the present paper we study the problem of discretization of integrable equations so that the property of integrability is preserved. In particular, we consider hyperbolic type systems

$$p_{xy}^i = f^i(x, y, p, p_x, p_y) \quad i = 1, \dots, m, \quad (1)$$

where  $p = (p^1, \dots, p^m)$ ,  $p_x = (p_x^1, \dots, p_x^m)$  and  $p_y = (p_y^1, \dots, p_y^m)$ .

For such hyperbolic systems it is convenient to use Darboux integrability [1]. The above system is said to be integrable if it admits  $m$  functionally independent non-trivial  $x$ -integrals and  $m$  functionally independent non-trivial  $y$ -integrals. A function  $I(x, y, p, p_y, p_{yy}, \dots)$  is called an  $x$ -integral of the system (1) if

$$D_x I(x, y, p, p_y, p_{yy}, \dots) = 0 \quad \text{on all solutions of (1),} \quad (2)$$

where  $D_x$  is the total derivative with respect to  $x$ . One can define  $y$ -integrals in a similar way. The Darboux integrable systems are extensively studied, see [2]-[11] and a review paper [12].

The extension of the notion of Darboux integrability to discrete and semi-discrete Darboux integrable systems was developed by Habibullin and Pekcan [13], see also [14]. In recent years there is an interest in studying such systems, see [15]-[25]. A semi-discrete system

$$q_{nx}^i = f^i(x, n, q, q_x, q_1) \quad i = 1, \dots, m, \quad (3)$$

---

<sup>1</sup>e-mail: zheltukh@metu.edu.tr

<sup>2</sup>e-mail: natalya@fen.bilkent.edu.tr

where  $q = (q^1, \dots, q^m)$ ,  $q_x = (q_x^1, \dots, q_x^m)$  and  $q_1 = (q^1(x, n+1), \dots, q^m(x, n+1))$ , is called Darboux integrable if it admits  $m$  functionally independent non-trivial  $x$ -integrals and  $m$  functionally independent non-trivial  $n$ -integrals. A function  $J(x, n, q, q_x, q_{xx}, \dots)$  is called an  $n$ -integral of the system (3) if

$$DJ(x, y, q, q_x, q_{xx}, \dots) = J(x, n, q, q_x, q_{xx}, \dots) \quad \text{on all solutions of (3),} \quad (4)$$

where  $D$  is the shift operator, that is  $Dq = q_1$ . Note that  $Dq_k = q_{k+1}$ ,  $k = 1, 2, 3, \dots$ . The  $x$ -integrals  $I(x, n, q, q_1, q_2, \dots)$  for the system (3) are defined in the same way as for continuous system.

A hypothesis states that any continuous Darboux integrable system can be discretized with respect to one of the independent variables such that the resulting semi-discrete system is Darboux integrable and admits the set of  $x$ - or  $y$ -integrals of the original system as  $n$ -integrals [25]. The results of our work support the above hypothesis. We complete the discretization of continuous Darboux integrable equations derived by Zhiber and Kostrogina in [8]. In their paper Zhiber and Kostrogina considered the classification problem for continuous Darboux integrable systems admitting  $x$ - and  $y$ -integrals of the first and second orders. They found all such systems together with their  $x$ - and  $y$ -integrals. Following [8] we have two types of systems. The first system is

$$\begin{cases} u_{xy} = \frac{u_x u_y}{u+v} + \left( \frac{1}{u+v} + \frac{\alpha}{u+\alpha^2 v} \right) u_x v_y, \\ v_{xy} = \frac{\alpha^2 v_x v_y}{u+\alpha^2 v} + \left( \frac{1}{\alpha(u+v)} + \frac{\alpha}{u+\alpha^2 v} \right) u_x v_y. \end{cases} \quad (5)$$

For  $\alpha = 1$  it has  $y$ -integrals

$$I = 2v - \frac{u+v+c}{u_x} + 2c \ln \frac{u_x}{u+v+c}, \quad (6)$$

$$J = \frac{u_{xx}}{u_x} - \frac{2u_x + v_x}{(u+v+c)} \quad (7)$$

and the  $x$ -integrals have the same form in  $u, u_y, u_{yy}$  and  $v, v_y, v_{yy}$  variables.

For  $\alpha \neq 1$  it has  $y$ -integrals

$$I_1 = \left( 1 + \frac{1}{\alpha} \right) v \left( \frac{u_x}{u+v} \right)^{1-\alpha} - v_x \left( \frac{u_x}{u+v} \right)^{-\alpha}, \quad (8)$$

$$J_1 = \frac{u_{xx}}{u_x} - \frac{(\alpha+1)u_x + \alpha v_x}{\alpha(u+v)} \quad (9)$$

and the  $x$ -integrals have the same form in  $u, u_y, u_{yy}$  and  $v, v_y, v_{yy}$  variables.

The second system is

$$\begin{cases} u_{xy} = \frac{v u_x u_y}{uv+d} + \left( \frac{1}{uv+d} + \frac{1}{\alpha(uv+c)} \right) u u_x v_y, \\ v_{xy} = \frac{u v_x v_y}{uv+c} + \left( \frac{\alpha}{uv+d} + \frac{1}{uv+c} \right) v u_x v_y. \end{cases} \quad (10)$$

For  $\alpha = 1$  it has  $y$ -integrals

$$I_2 = \frac{(d-c)v^2u_x^2}{2(uv+d)^2} - \frac{cu_xv_x}{uv+d} \quad (11)$$

and

$$J_2 = \frac{u_{xx}}{u_x} + \frac{(d-c)vu_x - cuv_x}{c(uv+d)}, \quad (12)$$

where  $c$  and  $d$  are non-zero constants and the  $x$ -integrals have the same form in  $u, u_y, u_{yy}$  and  $v, v_y, v_{yy}$  variables.

For  $\alpha \neq 1$  it has  $y$ -integrals

$$I_3 = \frac{u_x^\beta v_x}{(uv+d)^\beta} + \frac{\beta v^2 u_x^{\beta+1}}{(uv+d)^{\beta+1}} \quad (13)$$

and

$$J_3 = -\frac{u_{xx}}{u_x} + \frac{2vu_x + uv_x}{uv+d}, \quad (14)$$

where  $d$  and  $\beta \neq 1$  are non-zero constants, and the  $x$ -integrals have the same form in  $u, u_y, u_{yy}$  and  $v, v_y, v_{yy}$  variables.

To discretize the systems (5) and (10) we employ a method introduced by Habibullin et. all [21], (see also [24]-[26]). In this approach one takes  $x$ - or  $y$ -integrals of a system and looks for a semi-discrete system admitting such integrals as  $n$ -integrals. In general one gets a set of semi-discrete systems admitting these  $n$ -integrals. For all sets of  $y$ -integrals of systems (5) and (10) we obtained corresponding semi-discrete systems. In all cases we were able to choose a semi-discrete system that gives the original system in the continuum limit. Also in examples where we can write a semi-discrete system explicitly we have shown that the system is Darboux integrable.

The following theorems are formulated for a hyperbolic type semi-discrete system

$$\begin{cases} u_{xn} = f(x, n, u, v, u_x, v_x, u_n, v_n), \\ v_{xn} = g(x, n, u, v, u_x, v_x, u_n, v_n), \end{cases} \quad (15)$$

where variables  $u, v$  depend on a continuous variable  $x \in \mathbb{R}$  and a discrete variable  $n \in \mathbb{N}$ . Note that the system (5) in the case  $\alpha = 1$  was discretized in [25].

**Theorem 1** *Let  $\alpha \neq 1$ . A system (15) admits  $n$ -integrals (8) and (9) if and only if it has the form*

$$\begin{aligned} u_{1x} &= \frac{u_1+v_1}{u+v} \mathcal{D}_1^{\alpha-1} u_x, \\ v_{1x} &= \frac{\alpha+1}{\alpha} \frac{v_1 \mathcal{D}_1^{\alpha-1} - v \mathcal{D}_1}{u+v} u_x + \mathcal{D}_1 v_x. \end{aligned} \quad (16)$$

The function  $\mathcal{D}_1$  is equal to 1 or given implicitly by  $H(K_1, L_1) = 0$ , where  $H$  is any smooth function and

$$K_1 = \frac{\alpha v_1 \mathcal{D}_1^{\alpha-1} - \alpha v \mathcal{D}_1^{1+\alpha-1} + (1 - \mathcal{D}_1^{\alpha-1}) u_1}{(\mathcal{D}_1^{\alpha-1} - 1)^{\alpha+1}}, \quad (17)$$

$$L_1 = \frac{(u_1 - \mathcal{D}_1^{1+\alpha^{-1}} u) e^{\mathcal{D}_1^{\alpha^{-1}}} + \frac{(-1)^\alpha e^{\mathcal{D}_1^{\alpha^{-1}}} (\alpha v_1 \mathcal{D}_1^{\alpha^{-1}} - \alpha v \mathcal{D}_1^{1+\alpha^{-1}} + (1 - \mathcal{D}_1^{\alpha^{-1}}) u_1)}{(\mathcal{D}_1^{\alpha^{-1}} - 1)^{\alpha+1}}. \quad (18)$$

Let us construct some examples.

**Example 1** In the case  $\mathcal{D}_1 = 1$  the system (16) becomes

$$u_{1x} = \frac{u_1 + v_1}{u + v} u_x, \quad (19)$$

$$v_{1x} = \left(1 + \frac{1}{\alpha}\right) \frac{v_1 - v}{u + v} u_x + v_x.$$

This system is Darboux integrable. Indeed, it has two independent non-trivial  $n$ -integrals (8), (9) and two independent non-trivial  $x$ -integrals

$$\mathcal{F}_1 = \frac{v - v_1}{v_1 - v_2} \quad \text{and} \quad \mathcal{F}_2 = \frac{u_1 - u}{(v_1 - v)^{\frac{\alpha}{1+\alpha}}} - \alpha(v_1 - v)^{\frac{1}{1+\alpha}}. \quad (20)$$

The  $x$ -integrals can be found by considering the  $x$ -algebra corresponding to the system.

**Example 2** Considering  $K_1 = 0$  and  $\alpha = -1$  we get  $\mathcal{D}_1 = \frac{u_1 + v_1}{u_1 + v}$ . Using (16) we get the system

$$u_{1x} = \frac{u_1 + v}{u + v} u_x, \quad (21)$$

$$v_{1x} = \frac{u_1 + v_1}{u_1 + v} v_x.$$

This system is Darboux integrable. Indeed, it has two independent non-trivial  $n$ -integrals (8), (9) and two independent non-trivial  $x$ -integrals

$$\mathcal{F}_1 = \frac{(u_2 + v_1)(v - v_1)}{(u_1 + v_1)(v_1 - v_2)} \quad \text{and} \quad \mathcal{F}_2 = \frac{(u - u_1)(u_1 + v_1)}{(-u_1 + u_2)(u_1 + v)}. \quad (22)$$

**Example 3** Considering  $K_1 = 0$  and  $\alpha = \frac{-1}{2}$  we get  $\mathcal{D}_1 = \frac{4u_1 + 2v_1}{v + \sqrt{v^2 + 16u_1^2 + 8u_1v_1}}$ . Using (16) we get the system

$$\begin{aligned} u_{1x} &= \frac{u_1 + v_1}{u + v} \left( \frac{v + \sqrt{v^2 + 16u_1^2 + 8u_1v_1}}{4u_1 + 2v_1} \right)^2 u_x, \\ v_{1x} &= - \left( \frac{v_1}{u + v} \left( \frac{v + \sqrt{v^2 + 16u_1^2 + 8u_1v_1}}{4u_1 + 2v_1} \right)^2 - \frac{v(4u_1 + 2v_1)}{(u + v)(v + \sqrt{v^2 + 16u_1^2 + 8u_1v_1})} \right) u_x \\ &\quad + \frac{4u_1 + 2v_1}{v + \sqrt{v^2 + 16u_1^2 + 8u_1v_1}} v_x \end{aligned} \quad (23)$$

This system has two independent non-trivial  $n$ -integrals (8) and (9).

**Example 4** Considering  $L_1 = 0$  and  $\alpha = \frac{-1}{2}$  we get  $\mathcal{D}_1 = \frac{v_1 + \sqrt{v_1^2 + 16u^2 + 8uv}}{2v + 4u}$ . Using (16) we get the system

$$\begin{aligned} u_{1x} &= \frac{u_1 + v_1}{u + v} \left( \frac{2v + 4u}{v_1 + \sqrt{v_1^2 + 16u^2 + 8uv}} \right)^2 u_x, \\ v_{1x} &= - \left( \frac{v_1}{u + v} \left( \frac{2v + 4u}{v_1 + \sqrt{v_1^2 + 16u^2 + 8uv}} \right)^2 - \frac{v(v_1 + \sqrt{v_1^2 + 16u^2 + 8uv})}{(u + v)(2v + 4u)} \right) u_x \\ &\quad + \frac{v_1 + \sqrt{v_1^2 + 16u^2 + 8uv}}{2v + 4u} v_x \end{aligned} \quad (24)$$

This system has two independent non-trivial  $n$ - integrals (8) and (9).

**Remark 1** In both previous examples let us consider the corresponding  $x$ -rings. Denote by  $X = D_x$ ,  $Y_1 = \frac{\partial}{\partial u_x}$ ,  $Y_2 = \frac{\partial}{\partial v_x}$ ,  $E_1 = [Y_1, X]$ ,  $E_2 = [Y_2, X]$ ,  $E_3 = [E_1, E_2]$ . Note that  $X = u_x E_1 + v_x E_2 + Y_1 + Y_2$ . The following multiplication table

$[E_i, E_j]$	$E_1$	$E_2$	$E_3$
$E_1$	0	$E_3$	$-2(u + v)^{-1} E_3$
$E_2$	$-E_3$	0	$-2(u + v)^{-1} E_3$
$E_3$	$2(u + v)^{-1} E_3$	$2(u + v)^{-1} E_3$	0

shows that  $x$ -rings are finite-dimensional. Therefore systems (23) and (24) are Darboux integrable.

**Remark 2** Expansion of the function  $D_1^{\alpha-1}$  given implicitly by  $H(K_1, L_1) = L_1 = 0$ , that is by

$$\alpha v_1 D_1^{\alpha-1} - \alpha v D_1^{1+\alpha-1} + (1 - D_1^{\alpha-1}) u_1 = 0,$$

into a series of the form  $D_1^{\alpha-1}(u_1, v, v_1) = \sum_{n=0}^{\infty} a_n (v_1 - v)^n$ , where coefficients  $a_n$  depend on variables  $u_1$  and  $v$  only, yields

$$D_1^{\alpha-1}(u_1, v, v_1) = 1 + \frac{\alpha}{u_1 + \alpha^2 v} (v_1 - v) + \sum_{n=2}^{\infty} a_n (v_1 - v)^n$$

and

$$D_1(u_1, v, v_1) = 1 + \frac{\alpha^2}{u_1 + \alpha^2 v} (v_1 - v) + \sum_{n=2}^{\infty} a_n (v_1 - v)^n.$$

By letting  $u_1 = u + \varepsilon u_y$ ,  $v_1 = v + \varepsilon v_y$  and taking  $\varepsilon \rightarrow 0$  one can see that the system (16) becomes (5).

**Theorem 2** A system (15) admits  $n$ -integrals (11) and (12) if and only if it has the form

$$\begin{aligned} u_{1x} &= \frac{v(u_1v_1 + d)\mathcal{D}_2}{v_1(uv + d)}u_x, \\ v_{1x} &= \frac{(d - c)vv_1(\mathcal{D}_2^2 - 1)}{2c(uv + d)\mathcal{D}_2}u_x + \frac{v_1}{v\mathcal{D}_2}v_x. \end{aligned} \quad (25)$$

The function  $\mathcal{D}_2$  is given implicitly by  $H(K_2, L_2) = 0$ , where  $H$  is any smooth function and

$$K_2 = \frac{v_1(\mathcal{D}_2 - 1)M^{-\frac{2d}{c+d}}}{v\mathcal{D}_2} (-2cdu_1v_1 + uv\mathcal{D}_2M), \quad L_2 = \frac{v\mathcal{D}_2M^{\frac{2d}{c+d}}}{v_1}, \quad (26)$$

where

$$M = 2cd + \frac{(c + d)(\mathcal{D}_2 - 1)u_1v_1}{\mathcal{D}_2}.$$

**Example 5** Considering  $K_2 = 0$  we can get  $\mathcal{D}_2 = \frac{(2cd + (c + d)uv)u_1v_1}{(2cd + (c + d)u_1v_1)uv}$ . Using (25) we get the system

$$\begin{aligned} u_{1x} &= \frac{u_1(u_1v_1 + d)(2cd + (c + d)uv)}{u(uv + d)(2cd + (c + d)u_1v_1)}u_x, \\ v_{1x} &= \frac{(d - c)}{2c(uv + d)} \left\{ \frac{u_1v_1^2(2cd + (c + d)uv)}{u(2cd + (c + d)u_1v_1)} - \frac{uv^2(2cd + (c + d)u_1v_1)}{u_1(2cd + (c + d)uv)} \right\} u_x \\ &\quad + \frac{u(2cd + (c + d)u_1v_1)}{u_1(2cd + (c + d)uv)}v_x. \end{aligned} \quad (27)$$

This system has two independent non-trivial  $n$ -integrals (11) and (12). One can check that this system also has the following two  $n$ -integrals

$$I_2^* = \frac{(2cd + (c + d)uv)u_x}{u(uv + d)},$$

$$J_2^* = \frac{(c - d)uv^2u_x}{2c(uv + d)(2cd + (c + d)uv)} + \frac{uv_x}{2cd + (c + d)uv}.$$

Considering the corresponding  $x$ -algebra we can also find  $x$ -integrals given by

$$\mathcal{F}_1 = \frac{u_1}{u} \left( \frac{2cd + (c + d)uv}{2cd + (c + d)u_1v_1} \right)^{\frac{c-d}{c+d}}, \quad \mathcal{F}_2 = \frac{u_1v_1 - uv}{u_2v_2 - uv}. \quad (28)$$

**Example 6** Considering  $K_2 = 0$  we can also get  $\mathcal{D}_2 = \frac{(c + d)u_1v_1}{2cd + (c + d)u_1v_1}$ . Using (25) we get the system

$$\begin{aligned} u_{1x} &= \frac{(c + d)u_1v(u_1v_1 + d)}{(uv + d)(2cd + (c + d)u_1v_1)}u_x, \\ v_{1x} &= \frac{(d - c)v}{2c(uv + d)} \left\{ \frac{(c + d)u_1v_1^2}{2cd + (c + d)u_1v_1} - \frac{2cd + (c + d)u_1v_1}{(c + d)u_1} \right\} u_x + \frac{2cd + (c + d)u_1v_1}{(c + d)u_1}v_x. \end{aligned} \quad (29)$$

This system has two independent non-trivial  $n$ - integrals (11) and (12) and two independent  $x$ -integrals

$$\mathcal{F}_1 = \frac{1}{c+d} \left( \frac{2cd + (c+d)u_1v_1}{vu_1} \right)^{\frac{c+d}{2d}} + \frac{u}{u_1} \left( \frac{2cd + (c+d)u_1v_1}{vu_1} \right)^{\frac{c-d}{2d}}$$

and

$$\mathcal{F}_2 = \frac{v_1u_1^{\frac{d-c}{2d}} (2cd + (c+d)u_1v_1)^{\frac{c+d}{2d}}}{v^{\frac{c+d}{2d}} (2cd + (c+d)(u_1v_1 + u_2v_2))}.$$

**Remark 3** The expansion of the function  $D_2$  given implicitly by  $H(K_2, L_2) = L_2 - (2cd)^{2d/(c+d)} = 0$  into a series of the form  $D_2(u_1, v, v_1) = \sum_{n=0}^{\infty} a_n(v_1 - v)^n$ , where coefficients  $a_n$  depend on variables  $u_1$  and  $v$  only, yields  $D_2(u_1, v, v_1) = 1 + \frac{c}{v(uv + c)}(v_1 - v) + \sum_{n=2}^{\infty} a_n(v_1 - v)^n$ . By letting  $u_1 = u + \varepsilon u_y$ ,  $v_1 = v + \varepsilon v_y$  and taking  $\varepsilon \rightarrow 0$  one can see that the system (25) becomes (10) with  $\alpha = -1$ .

**Theorem 3** A system (15) admits  $n$ -integrals (13) and (14) if and only if it has form

$$u_{1x} = \frac{u_1v_1 + d_1}{\mathcal{D}_3(uv + d)} u_x, \tag{30}$$

$$v_{1x} = \left( \frac{-\beta v_1^2}{\mathcal{D}_3(uv + d)} + \frac{\beta v^2 \mathcal{D}_3^\beta}{uv + d} \right) u_x + \mathcal{D}_3^\beta v_x.$$

The function  $\mathcal{D}_3$  is given implicitly by  $H(K_3, L_3) = 0$ , where  $H$  is any smooth function and

$$K_3 = \frac{(v_1 - v\mathcal{D}_3^\beta)^{\beta-1} (d_1u - du_1\mathcal{D}_3)}{\mathcal{D}_3}, \tag{31}$$

$$L_3 = (v_1 - v\mathcal{D}_3^\beta)^{(1-\beta)\beta-1} (d_1\mathcal{D}_3^{\beta-1} - d_1 + (\beta - 1)u_1(v_1 - v\mathcal{D}_3^\beta)). \tag{32}$$

**Example 7** Considering  $K_3 = 0$  we can get  $\mathcal{D}_3 = \frac{v_1^{1/\beta}}{v^{1/\beta}}$ . Using (30) we get the system

$$u_{1x} = \frac{(u_1v_1 + d_1)v^{1/\beta}}{(uv + d)v_1^{1/\beta}} u_x, \tag{33}$$

$$v_{1x} = \left\{ -\frac{\beta v_1^2 v^{1/\beta}}{v_1^{1/\beta} (uv + d)} + \frac{\beta v^2 v_1}{v(uv + d)} \right\} u_x + \frac{v_1}{v} v_x.$$

This system has two independent non-trivial  $n$ - integrals (13) and (14) and two independent  $x$ -integrals

$$\mathcal{F}_1 = \left( 1 - \left( \frac{v_1}{v} \right)^{\frac{1-\beta}{\beta}} \right) \left( -d_1u + du_1 \left( \frac{v_1}{v} \right)^{\frac{1}{\beta}} \right)^{\beta-1}$$

and

$$\mathcal{F}_2 = \frac{v^{\frac{1-\beta}{\beta}} - v_2^{\frac{1-\beta}{\beta}}}{v^{\frac{1-\beta}{\beta}} - v_1^{\frac{1-\beta}{\beta}}}.$$

One can check that this system also has the following two  $n$ -integrals

$$I_3^* = \frac{v^{1/\beta} u_x}{uv + d}, \quad J_3^* = \frac{v_x}{v} + \frac{\beta v u_x}{uv + d}.$$

**Example 8** Considering  $K_3 = 0$  we can also get  $\mathcal{D}_3 = \frac{d_1 u}{du_1}$ . Using (30) we get the system

$$\begin{aligned} u_{1x} &= \frac{(u_1 v_1 + d_1) du_1}{(uv + d) d_1 u} u_x, \\ v_{1x} &= \left\{ -\frac{\beta d v_1^2 u_1}{d_1 u (uv + d)} + \frac{\beta d_1^\beta v^2 u^\beta}{d^\beta u_1^\beta (uv + d)} \right\} u_x + \frac{d_1^\beta u^\beta}{d^\beta u_1^\beta} v_x. \end{aligned} \tag{34}$$

This system has two independent non-trivial  $n$ - integrals (13) and (14) and two independent  $x$ -integrals

$$\mathcal{F}_1 = \frac{d_1^\beta u^\beta v - d^\beta u_1^\beta v_1}{d_2^\beta u_1^\beta v_1 - d_1^\beta u_2^\beta v_2}$$

and

$$\mathcal{F}_2 = \frac{(d_1^\beta u^\beta v - d^\beta u_1^\beta v_1)(d d_1^\beta u^\beta u - d_1 d^\beta u_1^\beta u + (1 - \beta) u u_1)}{d d_1 u u_1}.$$

One can check that this system also has the following two  $n$ -integrals

$$I_3^{**} = \frac{du_x}{u(uv + d)}, \quad J_3^{**} = \frac{u^\beta v_x}{d^\beta} + \frac{\beta v^2 u^\beta u_x}{d^\beta (uv + d)}.$$

**Example 9** Considering  $L_3 = 0$  with  $\beta = 2$  we get  $\mathcal{D}_3 = \frac{d_1 + R}{2u_1 v}$ , where

$$R = \sqrt{d_1^2 + 4u_1 v (u_1 v_1 - d_1)}.$$

Using (30) we get the system

$$\begin{aligned} u_{1x} &= \frac{(u_1 v_1 + d_1)(d_1 - R)}{2(uv + d)(d_1 - u_1 v_1)} u_x, \\ v_{1x} &= \left\{ \frac{v_1^2 (R - d_1)}{d_1 - u_1 v_1} + \frac{d_1^2 + 2u_1 v (u_1 v_1 - d_1) + d_1 R}{u_1^2} \right\} \frac{u_x}{uv + d} + \frac{d_1^2 + 2u_1 v (u_1 v_1 - d_1) + d_1 R}{2u_1^2 v^2} v_x. \end{aligned} \tag{35}$$

This system has two independent non-trivial  $n$ - integrals (13) and (14).

**Example 10** Considering  $L_3 = 0$  with  $\beta = 1/2$  we get  $\mathcal{D}_3^{1/2} = \frac{2d_1 + u_1 v_1 + R}{2u_1 v}$ , where

$$R = \sqrt{(2d_1 + u_1 v_1)^2 - 8d_1 u_1 v}.$$



Using (30) we get the system

$$\begin{aligned} u_{1x} &= \frac{(u_1v_1 + d_1)(2d_1 + u_1v_1 - R)^2}{16d_1^2(uv + d)} u_x, \\ v_{1x} &= \left\{ \frac{-v_1^2(2d_1 + u_1v_1 - R)^2}{32d_1^2} + \frac{v(2d_1 + u_1v_1 + R)}{4u_1} \right\} \frac{u_x}{uv + d} + \frac{2d_1 + u_1v_1 + R}{2u_1v} v_x. \end{aligned} \quad (36)$$

This system has two independent non-trivial  $n$ - integrals (13) and (14).

**Remark 4** In both previous examples the corresponding  $x$ -rings have the following multiplication table

$[E_i, E_j]$	$E_1$	$E_2$	$E_3$
$E_1$	0	$E_3$	$\frac{-2v}{d+uv} E_3$
$E_2$	$-E_3$	0	$\frac{-2u}{d+uv} E_3$
$E_3$	$\frac{2v}{d+uv} E_3$	$\frac{2u}{d+uv} E_3$	0

where fields  $X, Y_1, Y_2, E_1, E_2$  and  $E_3$  are introduced in the same way as in Remark 1. It shows that the  $x$ -rings are finite-dimensional and the corresponding systems are Darboux integrable.

**Remark 5** The expansion of the function  $D_3$  given implicitly by  $H(K_3, L_3) = L_3 = 0$  into a series of the form  $D_3(u_1, v, v_1) = \sum_{n=0}^{\infty} a_n (v_1 - v)^n$ , where coefficients  $a_n$  depend on variables  $u_1$  and  $v$  only, yields

$$D_3(u_1, v, v_1) = 1 + \frac{u_1}{\beta u_1 v - d_1} (v_1 - v) + \sum_{n=2}^{\infty} a_n (v_1 - v)^n.$$

By letting  $u_1 = u + \varepsilon u_y$ ,  $v_1 = v + \varepsilon v_y$  and taking  $\varepsilon \rightarrow 0$  one can see that the system (30) becomes (10). Note that  $\beta = -\alpha$ .

## 2 Proof of Theorem 1

It follows from the equality  $DJ_1 = J_1$  that

$$\frac{u_{1xx}}{u_{1x}} - \left(1 + \frac{1}{\alpha}\right) \frac{u_{1x}}{u_1 + v_1} - \frac{v_{1x}}{u_1 + v_1} = \frac{u_{xx}}{u_x} - \frac{(\alpha + 1)u_x + \alpha v_x}{\alpha(u + v)}, \quad (37)$$

that is

$$\frac{f_x + f_u u_x + f_v v_x + f_{u_1} f + f_{v_1} g + f_{u_x} u_{xx} + f_{v_x} v_{xx}}{f} - \left(1 + \frac{1}{\alpha}\right) \frac{f}{u_1 + v_1} - \frac{g}{u_1 + v_1} = \frac{u_{xx}}{u_x} - \frac{(\alpha + 1)u_x + \alpha v_x}{\alpha(u + v)}. \quad (38)$$

By comparing the coefficients by  $v_{xx}$  and  $u_{xx}$ , we get  $f_{v_x} = 0$  and  $\frac{f_{u_x}}{f} = \frac{1}{u_x}$ . Hence

$$f(x, n, u, v, u_1, v_1, u_x, v_x) = A(x, n, u, v, u_1, v_1)u_x. \quad (39)$$

It follows from  $DI_1 = I_1$  that

$$\left(1 + \frac{1}{\alpha}\right) v_1 \left(\frac{Au_x}{u_1 + v_1}\right)^{1-\alpha} - g \left(\frac{Au_x}{u_1 + v_1}\right)^{-\alpha} = \left(1 + \frac{1}{\alpha}\right) v \left(\frac{u_x}{u + v}\right)^{1-\alpha} - v_x \left(\frac{u_x}{u + v}\right)^{-\alpha}, \quad (40)$$

that is

$$g = \left(1 + \frac{1}{\alpha}\right) \left(\frac{Av_1}{u_1 + v_1} - \frac{vA^\alpha}{u + v} \left(\frac{u + v}{u_1 + v_1}\right)^\alpha\right) u_x + \left(A \frac{u + v}{u_1 + v_1}\right)^\alpha v_x. \quad (41)$$

By substituting the expressions for  $f$  and  $g$  into (38) and comparing the coefficients by  $v_x$ ,  $u_x$  and the free term we get

$$\frac{A_x}{A} = 0, \quad (42)$$

$$\frac{A_u}{A} + A_{u_1} + \left(1 + \frac{1}{\alpha}\right) \left[ A_{v_1} \frac{v_1}{u_1 + v_1} - \frac{vA^\alpha A_{v_1}}{A(u + v)} \left(\frac{u + v}{u_1 + v_1}\right)^\alpha - \frac{A}{u_1 + v_1} - \frac{Av_1}{(u_1 + v_1)^2} + \frac{vA^\alpha}{(u + v)(u_1 + v_1)} \left(\frac{u + v}{u_1 + v_1}\right)^\alpha + \frac{1}{u + v} \right] = 0, \quad (43)$$

$$\frac{A_v}{A} + \frac{A_{v_1} A^\alpha}{A} \left(\frac{u + v}{u_1 + v_1}\right)^\alpha - \frac{A^\alpha}{u_1 + v_1} \left(\frac{u + v}{u_1 + v_1}\right)^\alpha + \frac{1}{u + v} = 0. \quad (44)$$

Let

$$\mathcal{D}_1 = \left(\frac{u + v}{u_1 + v_1}\right)^\alpha A^\alpha. \quad (45)$$

In terms of the function  $\mathcal{D}_1$  the equations (43) and (44) become

$$(u + v)\mathcal{D}_{1u} + (u_1 + v_1)\mathcal{D}_1^{\alpha-1}\mathcal{D}_{1u_1} + \frac{\alpha + 1}{\alpha}(v_1\mathcal{D}_1^{\alpha-1} - v\mathcal{D}_1)\mathcal{D}_{1v_1} - \mathcal{D}_1(\mathcal{D}_1^{\alpha-1} - 1) = 0, \quad (46)$$

$$\frac{\mathcal{D}_{1v}}{\mathcal{D}_1} + \mathcal{D}_{1v_1} = 0. \quad (47)$$

The set of solutions of the above system is not empty. For example,  $\mathcal{D}_1 = 1$  is one singular solution that leads to the Darboux integrable system (19). Let  $\mathcal{D}_1 \neq 1$ . For function  $W = W(u, v, u_1, v_1, \mathcal{D}_1)$  equations (46) and (47) become

$$(u + v)W_u + (u_1 + v_1)\mathcal{D}_1^{\alpha-1}W_{u_1} + \frac{\alpha + 1}{\alpha}(v_1\mathcal{D}_1^{\alpha-1} - v\mathcal{D}_1)W_{v_1} + \mathcal{D}_1(\mathcal{D}_1^{\alpha-1} - 1)W_{\mathcal{D}_1} = 0, \quad (48)$$

$$\frac{W_v}{\mathcal{D}_1} + W_{v_1} = 0. \quad (49)$$

After the change of variables  $\tilde{v} = v$ ,  $\tilde{v}_1 = v_1 - v\mathcal{D}_1$ ,  $\tilde{u} = u$ ,  $\tilde{u}_1 = u_1$ ,  $\tilde{\mathcal{D}}_1 = \mathcal{D}_1$  equations above become

$$(\tilde{u} + \tilde{v})W_{\tilde{u}} + (\tilde{u}_1 + \tilde{v}_1 + \tilde{v}\tilde{\mathcal{D}}_1)\tilde{\mathcal{D}}_1^{\alpha-1}W_{\tilde{u}_1} + \left(\left(1 + \frac{1}{\alpha}\right)\tilde{v}_1\tilde{\mathcal{D}}_1^{\alpha-1} + \frac{1}{\alpha}\tilde{v}(\tilde{\mathcal{D}}_1^{1+\alpha-1} - \tilde{\mathcal{D}}_1)\right)W_{\tilde{v}_1}$$

$$+ (\tilde{\mathcal{D}}_1^{1+\alpha-1} - \tilde{\mathcal{D}}_1)W_{\tilde{\mathcal{D}}_1} = 0,$$

$$W_{\tilde{v}} = 0.$$

We differentiate the first equation with respect to  $\tilde{v}$ , use  $W_{\tilde{v}} = 0$ , and get two new equations

$$W_{\tilde{u}} + \tilde{\mathcal{D}}_1^{1+\alpha^{-1}} W_{\tilde{u}_1} + \frac{1}{\alpha} (\tilde{\mathcal{D}}_1^{1+\alpha^{-1}} - \tilde{\mathcal{D}}_1) W_{\tilde{v}_1} = 0, \quad (50)$$

$$\tilde{u} W_{\tilde{u}} + (\tilde{u}_1 + \tilde{v}_1) \tilde{\mathcal{D}}_1^{\alpha^{-1}} W_{\tilde{u}_1} + \frac{\alpha + 1}{\alpha} \tilde{v}_1 \tilde{\mathcal{D}}_1^{\alpha^{-1}} W_{\tilde{v}_1} + (\tilde{\mathcal{D}}_1^{1+\alpha^{-1}} - \tilde{\mathcal{D}}_1) W_{\tilde{\mathcal{D}}_1} = 0. \quad (51)$$

After the change of variables  $u_1^* = \tilde{u}_1 - \tilde{\mathcal{D}}_1^{1+\alpha^{-1}} \tilde{u}$ ,  $v_1^* = \alpha \tilde{\mathcal{D}}_1^{\alpha^{-1}} \tilde{v}_1 + (1 - \tilde{\mathcal{D}}_1^{\alpha^{-1}}) \tilde{u}_1$ ,  $u^* = \tilde{u}$ ,  $v^* = \tilde{v}$  and  $\mathcal{D}_1^* = \tilde{\mathcal{D}}_1$  the last system becomes

$$\begin{aligned} W_{u^*} &= 0, \\ \left( (\mathcal{D}_1^{*\alpha^{-1}} + \alpha^{-1}(1 - \mathcal{D}_1^{*\alpha^{-1}})) u_1^* + \alpha^{-1} v_1^* \mathcal{D}_1^{*\alpha^{-1}} \right) W_{u_1^*} &+ \frac{\alpha+1}{\alpha} v_1^* \mathcal{D}_1^{*\alpha^{-1}} W_{v^*} \\ &+ \mathcal{D}_1^* (\mathcal{D}_1^{*\alpha^{-1}} - 1) W_{\mathcal{D}_1^*} = 0. \end{aligned}$$

The last equation has a general solution  $H(K_1, L_1) = 0$ , where  $K_1, L_1$  (rewritten in old variables) are given by (17), (18) and  $H$  is any smooth function. Now, using the equalities (45), (39) and (41) we obtain the system (16).  $\square$

### 3 Proof of Theorem 2

The equality  $DJ_2 = J_2$  implies

$$\begin{aligned} \frac{f_x + f_u u_x + f_v v_x + f_{u_1} f + f_{v_1} g + f_{u_x} u_{xx} + f_{v_x} v_{xx}}{f} &+ \frac{(d_1 - c_1) v_1 f - c_1 u_1 g}{c_1 (u_1 v_1 + d_1)} \\ &= \frac{u_{xx}}{u_x} + \frac{(d - c) v u_x - c u v_x}{c (uv + d)}. \end{aligned} \quad (52)$$

By comparing the coefficients by  $u_{xx}$  and  $v_{xx}$  in the above equality we get  $f_{v_x} = 0$  and  $\frac{f_{u_x}}{f} = \frac{1}{u_x}$ .

Hence

$$f = A(x, n, u, v, u_1, v_1) u_x. \quad (53)$$

Equality  $DI_2 = I_2$  implies

$$\frac{(d_1 - c_1) v_1^2 A^2 u_x}{2(u_1 v_1 + d_1)^2} - \frac{c A g}{u_1 v_1 + d_1} = \frac{(d - c) v^2 u_x}{2(uv + d)^2} - \frac{c v_x}{uv + d}. \quad (54)$$

It follows from (54) that

$$g = \left( \frac{(d_1 - c_1) v_1^2 A}{2c_1 (u_1 v_1 + d_1)} - \frac{(d - c) v_1^2 (u_1 v_1 + d_1)}{2c_1 A (uv + d)^2} \right) u_x + \frac{c (u_1 v_1 + d_1)}{c_1 A (uv + d)} v_x. \quad (55)$$

By substituting the expressions for  $f$  and  $g$  into (52) and comparing the coefficients by  $u_x$ ,  $v_x$  and free term we get

$$\begin{aligned} \frac{A_x}{A} &= 0, \\ \frac{A_u}{A} + A_{u_1} + \left( \frac{A_{v_1}}{A} - \frac{u_1}{u_1 v_1 + d_1} \right) &\left( \frac{(d_1 - c_1)v_1^2 A}{2c_1(u_1 v_1 + d_1)} - \frac{(d - c)v^2(u_1 v_1 + d_1)}{2c_1 A(uv + d)^2} \right) \\ &+ \frac{(d_1 - c_1)v_1 A}{c_1(u_1 v_1 + d_1)} - \frac{(d - c)v}{c(uv + d)} = 0, \\ \frac{A_v}{A} + \frac{c(u_1 v_1 + d_1)}{c_1 A(uv + d)} &\left( \frac{A_{v_1}}{A} - \frac{u_1}{u_1 v_1 + d_1} \right) + \frac{u}{uv + d} = 0. \end{aligned} \quad (56)$$

One can check that  $A = \frac{v(u_1 v_1 + d)}{v_1(uv + d)}$  is a particular solution provided  $d_1 = d$  and  $c_1 = c$ . Now assuming that  $A \neq \frac{v(u_1 v_1 + d)}{v_1(uv + d)}$  we introduce new function

$$\mathcal{D}_2 = \frac{v_1(uv + d)}{v(u_1 v_1 + d_1)} A. \quad (57)$$

In terms of  $\mathcal{D}_2$  the system (56) becomes

$$\begin{aligned} \mathcal{D}_{2x} &= 0, \\ (uv + d)\mathcal{D}_{2u} + \frac{v(u_1 v_1 + d_1)\mathcal{D}_2}{v_1} \mathcal{D}_{2u_1} + \frac{vv_1}{2c_1} &((d_1 - c_1)\mathcal{D}_2 - (d - c)\mathcal{D}_2^{-1}) \mathcal{D}_{2v_1} \\ - \frac{dv}{c}\mathcal{D}_2 + \frac{(d_1 + c_1)v}{2c_1} \mathcal{D}_2^2 + \frac{v(d - c)}{2c_1} &= 0, \\ c_1 v \mathcal{D}_2 \mathcal{D}_{2v} + c v_1 \mathcal{D}_{2v_1} + (-c\mathcal{D}_2 + c_1 \mathcal{D}_2^2) &= 0. \end{aligned}$$

For function  $W = W(u, v, u_1, v_1, \mathcal{D}_2)$  the last two equations become

$$\begin{aligned} (uv + d)W_u + \frac{v(u_1 v_1 + d_1)}{v_1} \mathcal{D}_2 W_{u_1} + \frac{vv_1}{2c_1} &((d_1 - c_1)\mathcal{D}_2 - (d - c)\mathcal{D}_2^{-1}) W_{v_1} \\ + \left( \frac{dv}{c}\mathcal{D}_2 - \frac{(d_1 + c_1)v}{2c_1} \mathcal{D}_2^2 - \frac{v(d - c)}{2c_1} \right) &W_{\mathcal{D}_2} = 0, \\ c_1 v \mathcal{D}_2 W_v + c v_1 W_{v_1} + (c\mathcal{D}_2 - c_1 \mathcal{D}_2^2) W_{\mathcal{D}_2} &= 0. \end{aligned}$$

In new variables  $\tilde{u} = u$ ,  $\tilde{u}_1 = u_1$ ,  $\tilde{v} = v(c_1 \mathcal{D}_2 - c)$ ,  $\tilde{v}_1 = v_1(c_1 \mathcal{D}_2 - c)\mathcal{D}_2^{-1}$ ,  $\tilde{\mathcal{D}}_2 = \mathcal{D}_2$  the last system can be rewritten as

$$\begin{aligned} \left( (c_1 \tilde{\mathcal{D}}_2 - c)\tilde{u}\tilde{v} + d(c_1 \tilde{\mathcal{D}}_2 - c)^2 \right) W_{\tilde{u}} + \frac{\tilde{v}}{\tilde{v}_1} &\left( \tilde{u}_1 \tilde{v}_1 \tilde{\mathcal{D}}_2 (c_1 \tilde{\mathcal{D}}_2 - c) + d_1 (c_1 \tilde{\mathcal{D}}_2 - c)^2 \right) W_{\tilde{u}_1} \\ + \tilde{v}^2 \left( \frac{c_1 d \tilde{\mathcal{D}}_2}{c} - \frac{(d_1 + c_1)\tilde{\mathcal{D}}_2^2}{2} + \frac{c - d}{2} \right) &W_{\tilde{v}} + \tilde{v}\tilde{v}_1 \left( \frac{(d_1 - c_1)\tilde{\mathcal{D}}_2^2}{2} - \frac{cd_1 \tilde{\mathcal{D}}_2}{c_1} + \frac{c + d}{2} \right) W_{\tilde{v}_1} = 0, \\ W_{\tilde{\mathcal{D}}_2} &= 0. \end{aligned} \quad (58)$$

Special solutions of (58) may occur only when  $\tilde{\mathcal{D}}_2 = c_1/c$ . We differentiate equation (58) with respect to  $\tilde{\mathcal{D}}_2$  three times and get the following system of three equations

$$(dc^2 - c\tilde{u}\tilde{v})W_{\tilde{u}} + c^2d_1\frac{\tilde{v}}{\tilde{v}_1}W_{\tilde{u}_1} + \frac{(c-d)\tilde{v}^2}{2}W_{\tilde{v}} + \frac{(c+d)\tilde{v}\tilde{v}_1}{2}W_{\tilde{v}_1} = 0, \quad (59)$$

$$(c_1\tilde{u}\tilde{v} - 2dc_1c)W_{\tilde{u}} - (2d_1c_1c\frac{\tilde{v}}{\tilde{v}_1} + c\tilde{u}_1\tilde{v})W_{\tilde{u}_1} + \frac{c_1d\tilde{v}^2}{c}W_{\tilde{v}} - \frac{cd_1\tilde{v}\tilde{v}_1}{c_1}W_{\tilde{v}_1} = 0, \quad (60)$$

$$dc_1^2W_{\tilde{u}} + \left(\frac{d_1c_1^2\tilde{v}}{\tilde{v}_1} + c_1\tilde{u}_1\tilde{v}\right)W_{\tilde{u}_1} - \frac{(d_1+c_1)\tilde{v}^2}{2}W_{\tilde{v}} + \frac{(d_1-c_1)\tilde{v}\tilde{v}_1}{2}W_{\tilde{v}_1} = 0, \quad (61)$$

that has no solutions if  $c_1 \neq c$  or  $d_1 \neq d$ . In case of  $c_1 = c$  and  $d_1 = d$  the system becomes

$$W_{\tilde{u}} - \frac{\tilde{v}^2(2c^2d + (c-d)\tilde{u}_1\tilde{v}_1)}{2c(\tilde{u}\tilde{u}_1\tilde{v}\tilde{v}_1 + cd(\tilde{u}\tilde{v} - \tilde{u}_1\tilde{v}_1))}W_{\tilde{v}} - \frac{\tilde{v}\tilde{v}_1(2c^2d + (c+d)\tilde{u}_1\tilde{v}_1)}{2c(\tilde{u}\tilde{u}_1\tilde{v}\tilde{v}_1 + cd(\tilde{u}\tilde{v} - \tilde{u}_1\tilde{v}_1))}W_{\tilde{v}_1} = 0, \quad (62)$$

$$W_{\tilde{u}_1} - \frac{\tilde{v}\tilde{v}_1(-2c^2d + (c+d)\tilde{u}\tilde{v})}{2c(\tilde{u}\tilde{u}_1\tilde{v}\tilde{v}_1 + cd(\tilde{u}\tilde{v} - \tilde{u}_1\tilde{v}_1))}W_{\tilde{v}} + \frac{\tilde{v}_1^2(2c^2d + (-c+d)\tilde{u}\tilde{v})}{2c(\tilde{u}\tilde{u}_1\tilde{v}\tilde{v}_1 + cd(\tilde{u}\tilde{v} - \tilde{u}_1\tilde{v}_1))}W_{\tilde{v}_1} = 0. \quad (63)$$

After the change of variables  $u_1^* = \tilde{u}_1$ ,  $v_1^* = \tilde{v}_1$ ,  $v^* = \frac{\tilde{v}}{\tilde{v}_1}(2c^2d + (c+d)\tilde{u}_1\tilde{v}_1)^{\frac{2d}{c+d}}$ ,  $u^* = \tilde{u}\tilde{v}_1(2c^2d + (c+d)\tilde{u}_1\tilde{v}_1)^{\frac{c-d}{c+d}} - 2c^2d\tilde{u}_1\tilde{v}_1^2\tilde{v}^{-1}(2c^2d + (c+d)\tilde{u}_1\tilde{v}_1)^{-\frac{2d}{c+d}}$  equations (62) and (63) become  $W_{v_1^*} = 0$  and  $W_{u_1^*} = 0$  respectively. We rewrite these first integrals in old variables and get that the general solution is given implicitly by  $H(K_2, L_2) = 0$ , where  $H$  is any smooth function and  $K_2, L_2$  are given by (26). The form of system (25) follows from (53), (55) and (57).  $\square$

## 4 Proof of Theorem 3

**Proof.** Equality  $DJ_3 = J_3$  implies

$$-\frac{f_x + f_u u_x + f_v v_x + f_{u_1} f + f_{v_1} g + f_{u_x} u_{xx} + f_{v_x} v_{xx}}{f} + \frac{2v_1 f + u_1 g}{u_1 v_1 + d_1} = -\frac{u_{xx}}{u_x} + \frac{2v u_x + u v_x}{uv + d}. \quad (64)$$

By comparing the coefficients by  $u_{xx}$  and  $v_{xx}$  in the above equality we get  $f_{v_x} = 0$  and  $\frac{f_{u_x}}{f} = \frac{1}{u_x}$ .

Hence

$$f = A(x, n, u, v, u_1, v_1)u_x. \quad (65)$$

Equality  $DI_3 = I_3$  implies

$$\frac{f^\beta g}{(u_1 v_1 + d_1)^\beta} + \frac{\beta v_1^2 f^{\beta+1}}{(u_1 v_1 + d_1)^{\beta+1}} = \frac{u_x^\beta v_x}{(uv + d)^\beta} + \frac{\beta v^2 u_x^{\beta+1}}{(uv + d)^{\beta+1}}. \quad (66)$$

Let

$$\mathcal{D}_3 = \frac{u_1 v_1 + d_1}{A(uv + d)}. \quad (67)$$

Then from (66) we get

$$g = \left( -\frac{\beta v_1^2}{\mathcal{D}_3(uv+d)} + \frac{\beta v^2 \mathcal{D}_3^\beta}{(uv+d)} \right) u_x + \mathcal{D}_3^\beta v_x. \quad (68)$$

The equality (64) in terms of  $\mathcal{D}_3$  takes the form

$$\begin{aligned} \frac{\mathcal{D}_{3x}}{\mathcal{D}_3} + \left( \frac{\mathcal{D}_{3u}}{\mathcal{D}_3} + \frac{u_1 v_1 + d_1}{\mathcal{D}_3^2(uv+d)} \mathcal{D}_{3u_1} + \frac{\beta(v^2 \mathcal{D}_3^\beta - v_1^2 \mathcal{D}_3^{-1})}{\mathcal{D}_3(uv+d)} \mathcal{D}_{3v_1} + \frac{v_1}{\mathcal{D}_3(uv+d)} - \frac{v}{(uv+d)} \right) u_x \\ + \left( \frac{\mathcal{D}_{3v}}{\mathcal{D}_3} + \mathcal{D}_3^{\beta-1} \mathcal{D}_{3v_1} \right) v_x = 0. \end{aligned} \quad (69)$$

By comparing the coefficients by  $u_x$ ,  $v_x$  and free term we get

$$\mathcal{D}_{3x} = 0, \quad (70)$$

$$\frac{uv+d}{\mathcal{D}_3} \mathcal{D}_{3u} + \frac{u_1 v_1 + d_1}{\mathcal{D}_3^2} \mathcal{D}_{3u_1} + \frac{\beta v^2 \mathcal{D}_3^\beta - \beta v_1^2 \mathcal{D}_3^{-1}}{\mathcal{D}_3} \mathcal{D}_{3v_1} + \frac{v_1}{\mathcal{D}_3} - v = 0, \quad (71)$$

$$\mathcal{D}_{3v} + \mathcal{D}_3^\beta \mathcal{D}_{3v_1} = 0. \quad (72)$$

In new variables  $\tilde{v}_1 = v_1 - v \mathcal{D}_3^\beta$ ,  $\tilde{v} = v$ ,  $\tilde{u} = u$ ,  $\tilde{u}_1 = u_1$ ,  $\tilde{\mathcal{D}}_3 = \mathcal{D}_3$  equations (72) and (71) can be rewritten for function  $W = W(\tilde{u}, \tilde{v}, \tilde{u}_1, \tilde{v}_1, \tilde{\mathcal{D}}_3)$  as follows

$$W_{\tilde{v}} = 0,$$

$$\tilde{\mathcal{D}}_3(\tilde{u}\tilde{v} + d)W_{\tilde{u}} + (\tilde{u}_1(\tilde{v}_1 + \tilde{v}\tilde{\mathcal{D}}_3^\beta) + d_1)W_{\tilde{u}_1} + \tilde{\mathcal{D}}_3(\tilde{v}(\tilde{\mathcal{D}}_3 - \tilde{\mathcal{D}}_3^\beta) - \tilde{v}_1)W_{\tilde{\mathcal{D}}_3} - \beta\tilde{v}_1(\tilde{v}_1 + \tilde{v}\tilde{\mathcal{D}}_3^\beta)W_{\tilde{v}_1} = 0.$$

We differentiate the last equation with respect to  $\tilde{v}$ , use the fact that  $W_{\tilde{v}} = 0$  and get the new system of equations

$$\begin{aligned} \tilde{u}\tilde{\mathcal{D}}_3 W_{\tilde{u}} + \tilde{u}_1 \tilde{\mathcal{D}}_3^\beta W_{\tilde{u}_1} + (\tilde{\mathcal{D}}_3^2 - \tilde{\mathcal{D}}_3^{\beta+1})W_{\tilde{\mathcal{D}}_3} - \beta\tilde{v}_1 \tilde{\mathcal{D}}_3^\beta W_{\tilde{v}_1} = 0, \\ d\tilde{\mathcal{D}}_3 W_{\tilde{u}} + (\tilde{u}_1 \tilde{v}_1 + d_1)W_{\tilde{u}_1} - \tilde{\mathcal{D}}_3 \tilde{v}_1 W_{\tilde{\mathcal{D}}_3} - \beta\tilde{v}_1^2 W_{\tilde{v}_1} = 0, \end{aligned}$$

that can be rewritten as

$$\begin{aligned} W_{\tilde{u}} + \frac{d_1 \tilde{\mathcal{D}}_3 - d_1 \tilde{\mathcal{D}}_3^\beta + \tilde{\mathcal{D}}_3 \tilde{u}_1 \tilde{v}_1}{d_1 \tilde{u} - d \tilde{\mathcal{D}}_3^\beta \tilde{u}_1 + \tilde{u} \tilde{u}_1 \tilde{v}_1} W_{\tilde{\mathcal{D}}_3} - \frac{\beta d_1 \tilde{v}_1 \tilde{\mathcal{D}}_3^{\beta-1}}{d_1 \tilde{u} - d \tilde{\mathcal{D}}_3^\beta \tilde{u}_1 + \tilde{u} \tilde{u}_1 \tilde{v}_1} W_{\tilde{v}_1} = 0, \\ W_{\tilde{u}_1} - \frac{\tilde{\mathcal{D}}_3(d \tilde{\mathcal{D}}_3 - d \tilde{\mathcal{D}}_3^\beta + \tilde{u} \tilde{v}_1)}{d_1 \tilde{u} - d \tilde{\mathcal{D}}_3^\beta \tilde{u}_1 + \tilde{u} \tilde{u}_1 \tilde{v}_1} W_{\tilde{\mathcal{D}}_3} + \frac{\beta \tilde{v}_1 (d \tilde{\mathcal{D}}_3^\beta - \tilde{u} \tilde{v}_1)}{d_1 \tilde{u} - d \tilde{\mathcal{D}}_3^\beta \tilde{u}_1 + \tilde{u} \tilde{u}_1 \tilde{v}_1} W_{\tilde{v}_1} = 0. \end{aligned}$$

After the change of variables  $u^* = \tilde{u} \tilde{v}_1^{1/\beta} d_1^{1/(1-\beta)} \tilde{\mathcal{D}}_3^{-1} - d d_1^{\beta/(1-\beta)} \tilde{u}_1 \tilde{v}_1^{1/\beta}$ ,  $\mathcal{D}_3^* = \tilde{v}_1^{(1-\beta)/\beta} \tilde{\mathcal{D}}_3^{\beta-1} - \tilde{v}_1^{(1-\beta)/\beta} + (\beta-1) d_1^{-1} \tilde{u}_1 \tilde{v}_1^{1/\beta}$ ,  $u_1^* = \tilde{u}_1$ ,  $v^* = \tilde{v}$ ,  $v_1^* = \tilde{v}_1$  the last two equations become respectively  $W_{v_1^*} = 0$  and  $W_{u_1^*} = 0$ . We rewrite these first integrals in old variables and get that general solution is given implicitly by  $H(K_3, L_3) = 0$ , where  $H$  is any smooth function and  $K_3, L_3$  are given by (31), (32). The form of system (30) follows from (65), (68) and (67).  $\square$

## References

- [1] Darboux G. *Leconsur la theory generale des surface et les applicationgeometriques du calculus infinitesimal* vol. **2** (Paris: Gautier Villas) (1915)
- [2] Shabat A. B., Yamilov R. I. *Exponential systems of type I and Cartan matrices* (Russian) *Preprint BBAS USSR Ufa* (1981)
- [3] Leznov A.N., Smirnov V.G. and Shabat A.B. *Internal symmetry group and integrability conditions for two-dimensional dynamical systems* (Russian) *Teoret. Mat. Fiz.* **51**, 10-21 (1982)
- [4] Sokolov V.V., Zhiber A.V. *On the Darboux integrable hyperbolic equations* *Phys. Lett. A* **208**, 303-308 (1995)
- [5] Zhiber A.V., Sokolov V.V. and Startsev S.Ya. *On nonlinear Darboux-integrable hyperbolic equations*, (Russian) *Dokl. Akad. Nauk* **343**, 746-748 (1995)
- [6] Zhiber A. V., Sokolov V. V. *Exactly integrable hyperbolic equations of Liouville type*, *Russian Math. Surveys* **56**, 61-101 (2001)
- [7] Zhiber A.V., Murtazina R.D. *On the characteristic Lie algebras for the equations  $u_{xy} = f(u, u_x)$* , *J. Math. Sci. (N. Y.)* **151**, 3112-3122 (2008)
- [8] Kostrigina O.S., Zhiber A.V. *Darboux-integrable two-component nonlinear hyperbolic systems of equations*, *J. Math. Phys.* **52**, 033503 (2011)
- [9] Murtazina R. D. *Nonlinear hyperbolic equations with characteristic ring of dimension 3*, (Russian) *Ufa Math. J.* **3**, 113-118 (2011)
- [10] Anderson I. M., Fels M. E. *The Cauchy problem for Darboux integrable systems and nonlinear d'Alembert formulas*, *SIGMA* **9**, Paper 017, (2013)
- [11] Anderson, I. M., Fels, M. E. and Vassiliou P. J. *On Darboux integrability*, *SPT 2007Symmetry and perturbation theory*, 1320, World Sci. Publ., Hackensack, NJ, (2008)
- [12] Zhiber A.B., Murtazina R.D., Habibullin I.T. and Shabat A.B. *Characteristic Lie rings and integrable models in mathematical physics*, *Ufa Math. J.* **4**, 17-85 (2012)

- [13] Habibullin I.T., Pekcan A. *Characteristic Lie algebra and the classification of semi-discrete models*, Theoret. and Math. Phys. **151**, 781-790 (2007)
- [14] Adler V. E., Startsev S.Ya. *On discrete analogues of the Liouville equation*, Theoret. and Math. Phys. **121**, 1484-1495 (1999)
- [15] Habibullin I.T. *Characteristic algebras of fully discrete hyperbolic type equations*, SIGMA Symmetry Integrability Geom.: Methods Appl. **1**, 9 (2005)
- [16] Habibullin I.T., Zheltukhin K. and Yangubaeva M. *Cartan matrices and integrable lattice Toda field equations* J. Phys. A **44**, no. 46, 465202 (2011)
- [17] Habibullin I.T., Zheltukhina N. and Pekcan A. *On some algebraic properties of semi-discrete hyperbolic type equations*, Turkish J. Math. **32**, 277-292 (2008)
- [18] Habibullin I.T., Zheltukhina N. and Pekcan A. *On the classification of Darboux integrable chains*, J. Math. Phys. **49**, 102702 (2008)
- [19] Habibullin I.T., Zheltukhina N. and Pekcan A. *Complete list of Darboux integrable chains of the form  $t_{1x} = t_x + d(t, t_1)$* , J. Math. Phys. **50**, 102710 (2009)
- [20] Habibullin I.T., Zheltukhina N. and Sakieva A. *On Darboux-integrable semi-discrete chain*, J. Phys. A **43**, 434017 (2010)
- [21] Habibullin I., Zheltukhina N. and Sakieva A. *Discretization of hyperbolic type Darboux integrable equations preserving integrability*, J. Math. Phys. **52**, 093507( 2011).
- [22] Habibullin I.T. and Gudkova E.V. *Classification of integrable discrete Klein-Gordon models*, Physica Scripta bf 81, 045003 (2011)
- [23] Smirnov S V. *Semidiscrete Toda lattices*, Theoret. and Math. Phys. **172**, no. 3, 12171231 (2012)
- [24] Habibullin I.T. and Zheltukhina N. *Discretization of Liouville type nonautonomous equations*, J. Nonlinear Math. Phys. **23**, 620-642 (2016).
- [25] Zheltukhin K. and Zheltukhina N. *On the discretization of Laine equations*, J. Nonlinear Math. Phys. **25**, 166177 (2018).
- [26] Zheltukhin K. and Zheltukhina N. *On the discretization of Darboux Integrable Systems*, J. Nonlinear Math. Phys. (to appear).