RESEARCH ARTICLES

Parameter estimation for fractional autoregressive process with seasonal structure

Chunhao Cai^a and Yiwu Shang^b

^aSchool of mathematics(Zhuhai),Sun Yat-sen University,Zhuhai,People's Republic of China; ^bSchool of mathematical sciences,Nankai University,Tianjin,People's Republic of China

ARTICLE HISTORY

Compiled April 1, 2025

ABSTRACT

This paper introduces a new kind of seasonal fractional autoregressive process (SFAR) driven by fractional Gaussian noise (fGn). The new model includes a standard seasonal AR model and fGn. The estimation of the parameters of this new model has to solve two problems: nonstationarity from the seasonal structure and long memory from fGn. We innovatively solve these by getting a stationary subsequence, making a stationary additive sequence, and then obtaining their spectral density. Then, we use one-step procedure for Generalized Least Squares Estimator (GLSE) and the Geweke Porter-Hudak (GPH) method to get better results. We prove that both the initial and one-step estimators are consistent and asymptotically normal. Finally, we use Monte Carlo simulations with finite-sized samples to demonstrate the performance of these estimators. Moreover, through empirical analysis, it is shown that the SFAR model can simulate some real world phenomena better than general models.

KEYWORDS

Seasonal autoregressive process; fractional Gaussian noise; one-step procedure

1. INTRODUCTION

The long memory phenomenon and seasonal phenomenon play important roles in economics, geography, and other fields. One classic type of seasonal model with long memory is the $ARFISMA(p, d, q) \times (P, D, Q)_s$ process, which has been extensively researched by Hosking (1984), Franco & Reisen (2007), Chan & Terrin (1995). As demonstrated below, these models are equivalent to the ARUMA model, which can be expressed as

$$G(\mathcal{B})X_n = \epsilon_n,\tag{1}$$

where \mathcal{B} is the lag operator, ϵ_n is a short memory process, and $G(\cdot)$ satisfy the recurrence relation

$$G(z) = (1-z)^{d_0} \left\{ \prod_{j=1}^{r-1} (1-2z\cos\lambda_j + z^2)^{d_j} \right\} (1+z)^{d_r},$$
(2)

CONTACT Yiwu Shang. Email: shangyiwu@mail.nankai.edu.cn

where $|d_j| \leq \frac{1}{2}$, and for j = 0, 1, 2, ..., r, denoting that r is a positive integer, the frequencies satisfy $0 \leq \lambda_j \leq \pi$. Additionally, $\lambda_0 = 0$ and $\lambda_r = \pi$.

In the present paper, we conduct a comprehensive study on a *p*-order seasonal fractional autoregressive process (SFAR), denoted as X_{nT+u} . Here, the nonnegative integer *T* signifies the number of seasons, suggesting that the time series data exhibits seasonal fluctuations with a period of *T*. For example, when T = 4, it represents a quarterly seasonal pattern, and when T = 12, it corresponds to a monthly seasonal pattern. For any $n \in \mathbb{N}$ (where *n* denotes the count of complete seasonal cycles), the model adheres to the following recursive relation:

$$X_{nT+u} = \sum_{i=1}^{p} \phi_i (nT+u) X_{(n-i)T+u} + \epsilon_{nT+u}^H, \quad u = 1, 2, ...T,$$
(3)

where u denotes the specific time points within each seasonal cycle, thus taking values from 1 to T, p represents the order of the autoregressive part of the model. The $\phi_i(nT+u)$ are autoregressive seasonal coefficients, which may change with time and satisfy $\phi_i(u) = \phi_i(u+T)$. ϵ_{nT+u}^H represents fractional Gaussian noise, which explains the nonseasonal fluctuations. Fractional Gaussian noise exhabits long memory when $\frac{1}{2} < H < 1$. The long memory phenomenon indicates strong autocorrelation or dependence in time series data. We typically say that X_t has long memory if its covariance satisfies

$$\gamma_j \sim Q j^{2H-2}, \quad j \to \infty,$$
 (4)

the spectral density is defined by the scheme

$$f(\lambda) \sim V \lambda^{1-2H}, \quad \lambda \to 0^+,$$
 (5)

where $\frac{1}{2} < H < 1$, Q and V are constants greater than 0. Robinson (2010), Bisognin & Lopes (2009), Beran et al. (2013) did a great deal of detailed and excellent work in fractional Gaussian noise (fGn), especially in the estimation of H.

The Seasonal Fractional Autoregressive (SFAR) model represents a natural expansion of the fractional autoregressive process (FAR). The FAR, recognized as a long memory model is formulated as

$$X_n = \sum_{i=1}^p a_i X_{n-1-i} + \epsilon_n^H, \quad n \in \mathbb{N}.$$
 (6)

where $a_i \in \mathbb{R}$. It is composed of fractional Gaussian noise, and its long range dependence characteristics are determined by the value of H.

In this paper, we focus on the estimation and asymptotic properties of parameters in the SFAR model. Geweke & Porter-Hudak (1983) and Carlin & Dempster (1989) conducted some research on such models in the early stage. We aim to extend related research and will use a one-step procedure to optimize our approach.

For the parameter estimation of SFAR model, two key problems need to be addressed: the nonstationarity resulting from the seasonal structure and the dependence within the fractional Gaussian noise.

Seasonality is a distinctive feature of time series data where patterns repeat at regular intervals, typically defined by a specific period T. Seasonal time series models are often nonstationary, which presents certain challenges for our research. A common solution is to perform seasonal differencing on the time series. Seasonal autoregressive process is a classical model was proposed by Harrison (1965) and Chatfield & Prothero (1973). Tsay (2013) has explored SAR model with white noise in detail, however, there still remain many interesting variations worthy of research. For instance, the study in Kong & Lund (2023) employed particle filtering likelihood methods to estimate seasonal count time series. The other category is the research on the SAR model driven by fGn.

Previous studies by Brouste et al. (2014) and Soltane (2024) have laid a foundation for the estimation of the parameters $\phi_i(u)$ in FAR models. In this paper, we use the modified Generalized Least Squares Estimation (GLSE) proposed by Esstafa (2019) and Hariz et al. (2024) to obtain a consistent estimator of $\phi_i(u)$. Additionally, we will prove that this estimator is asymptotically normal.

Time series models with long memory show long range dependencies between distant observations, posing challenges to traditional statistical analysis and forecasting. In the SFAR model, long memory comes from fractional Gaussian noise, where the parameter H determines this characteristic. Thus, estimating H is crucial. The first method for estimating H was the rescaled range analysis by Hurst (1951), but its lack of a limiting distribution complicates statistical inference. Now, popular estimation techniques are the GPH estimation by Geweke & Porter-Hudak (1983) and the local Whittle estimation by Robinson (1995).

For the estimation of the Hurst index H, we will adopt the Geweke Porter-Hudak (GPH) method, which exhibits a smaller bias, for an additive stationary time series derived from the samples. It is worth noting that it would be more straightforward to estimate $\hat{H}_n(u)$ by $(X_{nT+u})_{n\in\mathbb{N}}$. However, this approach is not fundamentally different from the method in Hariz et al. (2024) and each $\hat{H}_n(u)$ cannot contain information about all the data. Meanwhile, considering that sequence $(X_{nT+u})_{n\in\mathbb{N},u=1,\dots,T}$ represents data of the same nature, we assume that the long memory parameter is the same for each season and is independent of the season u, and the differences between different seasons are only determined by the seasonal parameters. To obtain a unique \hat{H}_n , we sum up the data in each cycle to obtain a new sequence $(Y_n)_{n\in\mathbb{N}}$, then we prove the stationarity of $(Y_n)_{n\in\mathbb{N}}$, calculate its spectral density, and finally use the GPH method to get $\hat{H}_n(u)$. This improvement enables us to address the issue of parameter estimation for H in nonstationary time series with seasonality.

After obtaining the initial estimators of $\phi_i(u)$ and H, we modify our approach using a faster and asymptotically efficient method known as the one-step estimator. This method, first proposed by Le Cam (1956), has been widely applied in ergodic Markov chains (Kutoyants & Motrunich, 2016), diffusion processes (Gloter & Yoshida, 2021), and fractional autoregressive processes (Hariz et al., 2024). The primary challenge lies in calculating the Fisher information matrix, as discussed in Cohen et al. (2011). To tackle this issue, We extract the data from each season to form a new series, proving the stationarity of this new series and deriving its spectral density. Subsequently, we can utilize the results from Cohen et al. (2011) and Hariz et al. (2024) to obtain related findings.

This paper is organized as follows. Sections 2 and 3 present the main results. Section 2 introduces the initial estimator of the Hurst index, $\phi_i(u)$ and discusses its asymptotic properties. Section 3 derives the one-step estimator and its asymptotic properties. Section 4 provides numerical illustrations to demonstrate the performance of both the initial and one-step estimators. Section 5 concludes the paper and considers the prospects and significance of our research. Section 6 illustrates that the SFAR model is superior to the traditional seasonal autoregressive model through a practical application. All technical proofs are gathered in Section 7, while Section 8 presents auxiliary results.

2. Initial estimator of SFAR(1) models

2.1. Problem statements and assumptions

Without loss of generality, based on the representation of the SFAR model in (3), we can consider the first order model in this paper and denote $\phi_1(u) = \phi(u)$.

 X_{nT+u} is said to be a SFAR(1) model if it admits the representation

$$X_{nT+u} = \phi(nT+u)X_{(n-1)T+u} + \epsilon_{nT+u}^{H}, \quad u = 1, 2, 3...T, \quad n \in \mathbb{N},$$
(7)

where $\phi(u) = \phi(u+nT)$, T represents the season length and u denotes the u-th season of the n-th cycle. The term ϵ_{nT+u}^{H} represents a stationary fractional Gaussian noise with a Hurst index H. It is defined as the increment of the fractional Brownian motion, specifically $\epsilon_{nT+u}^{H} = B_{nT+u+1}^{H} - B_{nT+u}^{H}$, where B_{nT+u}^{H} is the fractional Brownian motion. The autocovariance of sequence $(\epsilon_{n}^{H})_{n \in \mathbb{N}}$ takes the form of

$$\rho(k) = \frac{1}{2}(|k+1|^{2H} - 2|k|^{2H} + |k-1|^{2H}), \tag{8}$$

the spectral density of $(\epsilon_n^H)_{n \in \mathbb{N}}$ defined by

$$f_{\epsilon_n^H}(\lambda) = C_H(1 - \cos(\lambda)) \sum_{j \in \mathbb{Z}} \frac{1}{|\lambda + 2j\pi|^{2H+1}},\tag{9}$$

where $C_H = \frac{1}{2\pi} \Gamma(2H+1) \sin(\pi H)$ and $\lambda \in [-\pi,\pi]$, $\Gamma(\cdot)$ is Gamma function.

Here are some assumptions and notations bellow.

 A_0 : Denote $\Theta_u^{l^{\star}}$ as a compact set with the following expression,

 $\Theta_u^{l^\star} = \{\phi(u) \in \mathbb{R}; \text{ the roots of } 1 - \phi(u)z = 0 \text{ have modulus } \ge 1 + l\}.$

We define the set Θ_u^l as the Cartesian product $\Theta_u^{l^*} \times [d_1, d_2]$, where l is a positive constant and $[d_1, d_2] \in (0, 1)$.

 $A_1: \phi(u) \in (-1, 1) \text{ and } H \in (0, 1).$

Notation: By $\xrightarrow{\mathcal{L}}$ and $\xrightarrow{\mathbb{P}}$, respectively, we denote convergence in law and convergence in probability. Let $\phi = (\phi(1), \phi(2), \dots, \phi(T))$. Denote the parameters $\theta(u) = (\phi(u), H)$, where $\theta(u) \in \overset{\circ}{\Theta}_{u}^{l}$, and $\overset{\circ}{\Theta}_{u}^{l}$ represents the interior of Θ_{u}^{l} . Define the parameter space $\Theta^{l} = \Theta_{1}^{l^{\star}} \times \Theta_{2}^{l^{\star}} \times \cdots \times \Theta_{T}^{l^{\star}} \times [d_{1}, d_{2}]$, which encompasses

Define the parameter space $\Theta^l = \Theta_1^{l^*} \times \Theta_2^{l^*} \times \cdots \times \Theta_T^{l^*} \times [d_1, d_2]$, which encompasses all the required parameters. Given samples of size n, we obtain the estimators $\hat{\theta}_n = (\hat{\phi}_n(1), \hat{\phi}_n(2), \dots, \hat{\phi}_n(T), \hat{H}_n)$ and $\hat{\theta}_n(u) = (\hat{\phi}_n(u), \hat{H}_n)$.

In this paper, we will present both the initial estimator and the one-step estimator for the parameters of the SFAR(1) model. The following sections will delve into the asymptotic properties and characteristics of these estimators in detail.

2.2. The GPH estimator for the hurst index

Due to the nonstationarity of X_n , obtaining an estimator for H using standard semiparametric methods is not feasible. To address this, we can extract stationarity from the data by splitting the time series $(X_n)_{n \in \mathbb{N}}$ into seasonal components, resulting in Tstationary subsequences $\underline{X}(u) = (X_u, X_{T+u}, ..., X_{nT+u})$ and we construct a stationary additive series defined as $Y_n = \sum_{u=1}^T X_{nT+u}$. In this subsection, we will estimate H using the log-periodogram method, specifically

In this subsection, we will estimate H using the log-periodogram method, specifically the GPH estimator, applied to the additive series $(Y_n)_{n \in \mathbb{N}}$. The spectral density and stationarity properties of $(Y_n)_{n \in \mathbb{N}}$ and $(X_{nT+u})_{u \in \mathbb{Z}}$ are outlined in the following three propositions.

Proposition 2.1. For each u = 1, 2, ...T and any $n \in \mathbb{N}$, Under conditions (A_0) and (A_1) , the process

$$X_{nT+u} = \sum_{j=0}^{\infty} \phi^j(u) \epsilon^H_{(n-j)T+u}, \quad a.s,$$
(10)

$$Y_n = \sum_{u=1}^T X_{nT+u}, \quad a.s,$$
 (11)

are stationary process.

According to the above formula and Theorem 4.4.1 in Brockwell & Davis (1991), we deduce the spectral density of Y_n from the spectral density of ϵ_t^H . The proof will be presented in detail in Section 6.

Remark 1. The stationary process (Y_n) encompasses all the information of ϵ_n^H . Therefore, we will utilize (Y_n) to obtain the estimation of H and the one-step estimator.

Proposition 2.2. Let $f_{H,\phi(u)}(\lambda)$ be the spectral density of $(X_{nT+u})_{n\in\mathbb{N}}$, then it can be rewritten as

$$f_{H,\phi(u)}(\lambda) = (1 - 2\phi(u)\cos\lambda T + \phi^2(u))^{-1} f_{\epsilon_n^H}(\lambda).$$
(12)

Proposition 2.3. Let $g_{H,\underline{\phi}}(\lambda)$ be the spectral density of $(Y_n)_{n\in\mathbb{N}}$, then it can be rewritten as

$$g_{H,\underline{\phi}}(\lambda) = |\sum_{p=0}^{T-1} \Phi_{\phi(T-p)}(\lambda)|^2 f_{\epsilon_n^H}(\lambda), \qquad (13)$$

where $\Phi_{\phi(T-p)}(\lambda) = \frac{e^{-ip\lambda}}{1-\phi(T-p)e^{-i\lambda T}}, \ p = 0, 1, ..., T-1.$

Because the GPH estimator is a type of semi-parametric estimation as discussed in Geweke & Porter-Hudak (1983), the explicit expression of $|\sum_{p=0}^{T-1} \Phi_{\phi(T-p)}(\lambda)|^2$ does not affect the estimation of H. Thus, the equation $\hat{H}_n = \hat{d}_n + \frac{1}{2}$ remains valid. We can then apply the GPH method directly to the stationary process Y_n .

Let new series $(Y_n)_{n \in \mathbb{N}}$ be an observation sample generated via the equation (11) and

choose a suitable integer m which can decrease the mean square error of estimation, where m < n. we get the periodogram of Y_n given by

$$I(\lambda) = \frac{1}{2\pi n} \left| \sum_{t=0}^{n} Y_t exp(it\lambda) \right|^2,$$
(14)

$$\lambda_j = \frac{2\pi j}{n}, \quad j \in \{1, 2, ...m\},$$
(15)

$$a_j = \log(2\sin\frac{\lambda_j}{2}), \quad \overline{a}_m = \frac{1}{m}\sum_{j=1}^m a_j, \quad S_m = \sum_{j=1}^m (a_j - \overline{a}_m)^2.$$
 (16)

We estimate d by regressing $\log I(\lambda_i)$ with respect to a_i , such that

$$\hat{d}_n = -\frac{1}{2S_m} \sum_{j=1}^m (a_j - \overline{a}_m) \log I(\lambda_j).$$
(17)

The estimator \hat{H}_n is defined by

$$\hat{H}_n = \hat{d}_n + \frac{1}{2}.$$
 (18)

Remark 2. There are several semi-parametric methods for estimating the long memory parameter d and H, such as whittle estimation and R/S estimation method proposed by Robinson (1995) and Marinucci & Robinson (1998). These models rely on the log-periodogram approach. However, these methods tend to exhibit greater bias compared to the GPH estimator.

2.3. Generalized least squares estimation of SFAR(1) models

We now focus on estimating $\phi(u)$ given that the parameter H has been estimated. When the noise in the seasonal autoregressive model is white noise, we can easily obtain the estimator of the parameters of these models using Least Squares Estimation (LSE). However, when the noise is fractional Gaussian noise (fGn), the covariance matrix of fGn is no longer diagonal, making LSE inappropriate. Therefore, we consider using Generalized Least Squares Estimation (GLSE).

To address the effect of seasonal structure on parameter estimation, we apply GLSE to the subsequences $(X_u, X_{T+u}, ..., X_{nT+u})$, where u = 1, 2, ..., T. This allows us to estimate the parameters $\phi(1), \phi(2), ..., \phi(T)$ sequentially, assuming the Hurst index is known.

We deduce the time series can be written in the form

$$\Phi_i^j(u) = (X_{u+iT}, X_{u+(i+1)T}, \dots X_{u+jT})^*, \quad i \le j,$$
(19)

and the autocovariance matrix is given by

$$\Gamma_{nT,u}(H) = \rho(|i-j|T)_{1 \le i,j \le n} = \begin{pmatrix} \gamma_{0,u} & \gamma_{T,u} & \gamma_{2T,u} & \cdots & \gamma_{(n-1)T,u} \\ \gamma_{T,u} & \gamma_{0,u} & \gamma_{3T,u} & \cdots & \gamma_{(n-2)T,u} \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ \gamma_{(n-1)T,u} & \gamma_{(n-2)T,u} & \gamma_{(n-3)T,u} & \cdots & \gamma_{0,u} \end{pmatrix},$$
(20)

where $\gamma_{nT,u} = cov(X_{nT+u}, X_u)$, $n \in \mathbb{N}$. We can easily show that $\Gamma_{nT,u}(H)$ depends only on n and not on u. Hence, we will denote $\Gamma_{nT,u}$ simply as Γ_{nT} from now on, without distinguishing between them.

The estimators $\left\{\hat{\phi}_n(u)\right\}_{u\geq 0}$ are defined by

$$\hat{\phi}_n(u) = \frac{\Phi_2^n(u)^* \Gamma_{(n-1)T}^{-1}(\hat{H}_n) \Phi_1^{n-1}(u)}{\Phi_1^{n-1}(u)^* \Gamma_{(n-1)T}^{-1}(\hat{H}_n) \Phi_1^{n-1}(u)}.$$
(21)

Now, due to the seasonal structure, we need to examine whether the elements of $\Gamma_{nT}^{-1}(\hat{H}_n)$ are finite to assess the feasibility of this method. Thanks to Fox & Taqqu (1986), Esstafa (2019). We know that the elements of

Thanks to Fox & Taqqu (1986), Esstafa (2019). We know that the elements of $\Gamma_{nT}^{-1}(\hat{H}_n)$ can be expressed as a function of the spectral density of fGn. The spectral representation of $(\Gamma_{nT}^{-1})_{j,k}$ implies that

$$(\Gamma_{nT}^{-1})_{j,k} = \frac{1}{(2\pi)^2} \int_{-\pi}^{\pi} \frac{1}{f_{\epsilon_n^H}(\lambda)} e^{i(k-j)T\lambda} d\lambda.$$
 (22)

As $\lambda \to 0$, according to the definition of fractional Gaussian noise, we have

$$f_{\epsilon_n^H}(\lambda) \sim \frac{C_H}{2} |\lambda|^{1-2H},\tag{23}$$

where C_H is a constant. We can categorize the elements of the matrix into two types: diagonal elements and off-diagonal elements.

When j = k, we have

$$(\Gamma_{nT}^{-1})_{j,j} = \frac{1}{(2\pi)^2} \int_{-\pi}^{\pi} \frac{1}{f_{\epsilon_n^H}(\lambda)} \, d\lambda = \frac{1}{2\pi^2} \int_0^{\pi} \frac{1}{f_{\epsilon_n^H}(\lambda)} \, d\lambda.$$
(24)

One has when $\lambda \to 0$ that

$$\frac{1}{f_{\epsilon_n^H}(\lambda)} = \frac{2}{C_H} |\lambda|^{2H-1} + o\left(\frac{2}{C_H} |\lambda|^{2H-1}\right).$$
(25)

This implies that for l > 0 there exists $\delta_l > 0$ such that for any $\lambda \in (-\delta_l, \delta_l)$, we have

$$(1-l)\frac{2}{C_H}|\lambda|^{2H-1} \le \frac{1}{f_{\epsilon_n^H}(\lambda)} \le (1+l)\frac{2}{C_H}|\lambda|^{2H-1}.$$
(26)

Thus, equation (24) have an upper bound when $\lambda \in (-\delta_l, \delta_l)$:

$$\begin{aligned} |(\Gamma_{nT}^{-1})_{j,j}| &\leq \frac{1+l}{C_{H}\pi^{2}} \int_{0}^{\delta_{l}} \lambda^{2H-1} d\lambda + \frac{1}{2\pi^{2}} \int_{\delta_{l}}^{\pi} \frac{1}{f_{\epsilon_{n}^{H}}(\lambda)} d\lambda \\ &\leq \frac{\delta_{l}^{2H}(1+l)}{2HC_{H}\pi^{2}} + \frac{\pi - \delta_{l}}{2\pi^{2}} \sup_{\lambda \in (\delta_{l},\pi]} \frac{1}{f_{\epsilon_{n}^{H}}(\lambda)} \\ &\leq K_{1}, \end{aligned}$$
(27)

where K_1 is a constant.

When $j \neq k$, according to Esstafa (2019), there exists a positive constant K_2 such that for any j, k = 1, 2, ...

$$\left| (\Gamma_{nT}^{-1})_{j,k} \right| \le K_2 \left| \frac{1}{(k-j)T} \right|^{2H}.$$
 (28)

Therefore, we have shown that the elements of $\Gamma_{(n-1)T}^{-1}(\hat{H}_n)$ are finite, which implies that $\hat{\phi}_n(u)$ is bounded. From these points we use the notations $H, \phi(u)$ and estimator $\hat{H}_n(u), \hat{\phi}_n(u)$ to present our results concerning the asymptotic properties of the initial estimator.

Theorem 2.4. Letting $m = [n^{\delta}]$ for some $0 < \delta < 1$, $(X_{nT+u})_{n\geq 0}$ satisfy the equation (7). Under conditions (A_0) and (A_1) , we have

$$\begin{pmatrix} \hat{H}_n\\ \hat{\phi}_n(u) \end{pmatrix} \xrightarrow[n \to \infty]{\mathbb{P}} \begin{pmatrix} H\\ \phi(u) \end{pmatrix},$$

for every u = 1, 2, ..., T, as $n \to \infty$. Where \hat{H}_n and $\hat{\phi}_n(u)$ are initial estimators defined in equation (18) and equation (21). [·] denotes the integer part function.

Remark 3. In this proof, we demonstrate that the estimators for each pair of parameters are individually consistent. Consequently, it follows that the estimators for all parameters together are also consistent.

Theorem 2.5. Let $m = [n^{\delta}]$ for some $\frac{1}{2} < \delta < \frac{2}{3}$. Under conditions (A_0) and (A_1) , $\hat{\theta}_n$ has a (T+1) dimension limiting normal distribution given by

$$\sqrt{m} \begin{pmatrix} \hat{H}_n - H \\ \hat{\phi}_n(1) - \phi(1) \\ \vdots \\ \hat{\phi}_n(T) - \phi(T) \end{pmatrix} \xrightarrow{\mathcal{L}} \mathcal{N}(0, \Sigma_{\theta}).$$

where $\hat{\theta}_n = (\hat{H}_n, \hat{\phi}_n(1), \hat{\phi}_n(2), ... \hat{\phi}_n(T))$. The covariance matrix Σ_{θ} is of the form $\Sigma_{\theta} = V_H \widetilde{\Sigma}_{\theta}$ and V_H is the asymptotic variance of $\sqrt{m}(\hat{H}_n - H)$, $\widetilde{\Sigma}_{\theta}$ is a built-in singular matrix.

Remark 4. (Hariz et al., 2024) represents $\frac{1}{2} < \delta < \frac{2}{3}$, and Hurvich et al. (1998) states that if $m = n^{\delta}$, where $0 < \delta < 1$, it can ensure the asymptotic normality of \hat{H}_n . The condition $\frac{1}{2} < \delta$ is to ensure that $\hat{\phi}_n(1)$ and $\hat{\phi}_n(2)$ are asymptotically normal. But according to Kutoyants & Motrunich (2016), if $\frac{2}{3} < \delta$, a multi-step estimator may

be required, which contradicts our consideration of a one-step estimator. Thus, we consider restricting δ to the interval $(\frac{1}{2}, \frac{2}{3})$.

Remark 5. These results can be extended to the SFAR(p), provided that $\underline{X}(u)$ is stationary.

Remark 6. Additionally, the estimation of ϕ can be also approached using methods from Brouste et al. (2014) and Soltane (2024).

3. One-step estimator of SFAR(1) models

In this section, we explore modifications to the initial estimator $\hat{\theta}_n$ to develop a onestep estimator $\tilde{\theta}_n$.

We assume that Y_n is stationary with a spectral density $g_{H,\underline{\phi}}(\lambda)$, as obtained in equation (13). For $g_{H,\underline{\phi}}(\lambda)$ to satisfy the necessary regularity conditions as follow,

Conditon.1 For any $\theta = (\theta_{j_1}, \theta_{j_2}, \dots, \theta_{j_{T+1}}) \in \Theta^l$, where Θ^l be an open subset of R^{T+1} , $g_{H,\phi}(\lambda)$ is three times continuously differentiable on Θ^l . In addition, for any $0 \le k \le 3$ and j_1, \dots, j_{T+1} , the partial derivative

$$\frac{\partial^k}{\partial \theta_{j_1}, \dots \partial \theta_{j_k}} g_{H,\underline{\phi}}(\lambda),\tag{29}$$

is a continue equation on $\Theta^l \times [-\pi, \pi] \setminus \{0\}$, is continuously differentiable with respect to λ and its partial derivative

$$\frac{\partial^{k+1}}{\partial\lambda\partial\theta_{j_1},\dots\partial\theta_{j_k}}g_{H,\underline{\phi}}(\lambda),\tag{30}$$

and is continuous on $\Theta^l \times [-\pi, \pi] \setminus \{0\}.$

Conditon.2 There also exists a continuous function $\alpha: \Theta^l \longrightarrow (-1, 1)$, such that for any compact set $\Theta^{l^*} \subset \Theta^l$ and $\delta > 0$, the following conditions hold for every $(\theta, \lambda) \in \Theta^* \times [-\pi, \pi] \setminus \{0\}$ are

$$c_{1,\delta,\Theta^{l^{\star}}}|\lambda|^{-\alpha(\theta)+\delta} \le g_{H,\underline{\phi}}(\lambda) \le c_{2,\delta,\Theta^{l^{\star}}}|\lambda|^{-\alpha(\theta)-\delta},\tag{31}$$

and

$$\left|\frac{\partial}{\partial\lambda}g_{H,\underline{\phi}}(\lambda)\right| \le c_{2,\delta,\Theta^{l^{\star}}}|\lambda|^{-\alpha(\theta)-1-\delta},\tag{32}$$

for any $k \in \{1, 2, 3\}$ and any $j \in (1, ..., T + 1)^k$. where

$$\left|\frac{\partial^{k}}{\partial\theta_{j_{1}},...\partial\theta_{j_{k}}}g_{H,\underline{\phi}}(\lambda)\right| \leq c_{2,\delta,\Theta^{l^{\star}}}|\lambda|^{-\alpha(\theta)-\delta},\tag{33}$$

here, $c_{1,\delta,\Theta^{l^*}}$ and $c_{2,\delta,\Theta^{l^*}}$ is some positive finite constant which only depends upon δ and Θ^{l^*} . We will prove the spectral density of Y_n satisfy regular condition in auxiliary results.

Proposition 3.1. We let l_n be the log-likelihood function of a stationary process $(Y_n)_{n \in \mathbb{N}}$. We assume that $g_{H,\underline{\phi}}(\lambda)$ satisfies the regularity conditions and let $B(\theta, R)$ (open ball of center θ and radius R) for some R > 0. For any $t \in B(\theta, R)$, $u \in \mathbb{N}$

$$l_n(\theta + \frac{t}{\sqrt{n}}) - l_n(\theta) = t \frac{\nabla l_n(\theta)}{\sqrt{n}} - \frac{t\mathcal{I}(\theta)t^*}{2} + r_{n,\theta}(t),$$
(34)

when $n \to \infty$, the score function $\nabla(\cdot)$ satisfies

$$\frac{\nabla l_n(\theta)}{\sqrt{n}} \xrightarrow[n \to \infty]{\mathbb{P}} \mathcal{N}(0, \mathcal{I}(\theta))$$
(35)

and

$$r_{n,\theta}(t) \xrightarrow[n \to \infty]{a.s.} 0,$$
 (36)

uniformly on each compact set. The Fisher information matrix is given in our case by

$$\mathcal{I}(\theta) = \frac{1}{4\pi} \left(\int_{-\pi}^{\pi} \frac{\partial \log g_{H,\underline{\phi}}(\lambda)}{\partial \theta_k} \frac{\partial \log g_{H,\underline{\phi}}(\lambda)}{\partial \theta_j} d\lambda \right)_{1 \le k, j \le T+1}.$$
(37)

This result is a direct consequence of Theorem from Cohen et al. (2011).

Since $g_{H,\underline{\phi}}(\lambda)$ satisfies the regularity conditions, the elements of the Fisher information matrix $\mathcal{I}(\theta)$ are finite. After obtaining the Fisher information matrix $\mathcal{I}(\theta)$ and the log-likelihood function of $(Y_n)_{n\in\mathbb{N}}$, we can compute the one-step estimator as follows

$$\tilde{\theta}_n = \hat{\theta}_n + \mathcal{I}(\hat{\theta}_n)^{-1} \frac{1}{n} \nabla l_n(\hat{\theta}_n), \qquad (38)$$

We can now analyze the asymptotic properties of the one-step estimator.

Theorem 3.2. Let $\hat{\theta}_n$ is the initial estimator of θ , $\tilde{\theta}_n$ is the one-step estimator of θ . When $g_{H,\underline{\phi}}(\lambda)$ satisfy regular condition, we have a asymptotic normal distribution of $\tilde{\theta}_n$ that

$$\sqrt{n}(\tilde{\theta}_n - \theta) \xrightarrow[n \to \infty]{\mathbb{P}} \mathcal{N}(0, \mathcal{I}(\theta)^{-1}).$$

Remark 7. The parameter θ should not lie on the boundary of the parameter space Θ^l .

Remark 8. The one-step estimation can be applied more generally even if the initial estimator $\hat{\theta}_n$ does not satisfy asymptotic normality. According to proposition 2.3 in Hariz (2025), if the initial estimator with convergence speed lower than \sqrt{n} and the spectral density of time series meets the regular condition, then the one-step estimator $\tilde{\theta}_n$ can still achieve asymptotic normality.

Remark 9. One-step estimator can achieve Hájek's lower bound, thus it is asymptotically efficient in the local minimax sense. We can find related conclusions in Brouste et al. (2020), Cohen et al. (2011).

4. Simulation study

According to equation (11), the likelihood function based on the sample $\underline{Y}^{(n)} = (Y_0, Y_1, \dots, Y_{n-1})$ is given by

$$l_n(\theta) = -\frac{1}{2}\log\det\left(\Gamma_n^Y(\theta)\right) - \frac{1}{2}\underline{Y}^{(n)^*}\Gamma_n^Y(\theta)\underline{Y}^{(n)},\tag{39}$$

where $\Gamma_n^Y(\theta)$ is the covariance matrix of $\underline{Y}^{(n)}$. For any $K \in \mathbb{N}$,

$$Cov(Y_0, Y_k) = \int_{-\pi}^{\pi} \exp(ik\lambda) g_{H,\underline{\phi}}(\lambda) d\lambda, \qquad (40)$$

where $Cov(\cdot, \cdot)$ denotes the covariance. The score function with respect to θ is given by

$$\frac{\partial l_n(\theta)}{\partial \theta_i} = -\frac{1}{2} Tr\left(\left(\Gamma_n^Y(\theta)\right)^{-1} \frac{\partial \Gamma_n^Y(\theta)}{\partial \theta_i}\right) + \frac{1}{2} \underline{Y}^{(n)^*} \left(\Gamma_n^Y(\theta)\right)^{-1} \frac{\partial \Gamma_n^Y(\theta)}{\partial \theta_i} \left(\Gamma_n^Y(\theta)\right)^{-1} \underline{Y}^{(n)},\tag{41}$$

where $Tr(\cdot)$ denotes the trace of a matrix. The Fisher information matrix (FIM) can be deduced from equation (37). We simulate the spectral density and its derivatives using the method described in Hariz et al. (2024), then plug the FIM and score functions into equation (38) to compute the one-step estimator numerically.

For each set of parameters, specifically $(\phi(1), \phi(2), H) = (0.6, 0.2, 0.8)$ and $(\phi(1), \phi(2), H) = (0.2, 0.8, 0.6)$, we conduct M = 1000 Monte Carlo simulations. The sample sizes considered are n = 100, n = 1000, and n = 2000. The number of Fourier frequencies for the initial estimations is set as $m = [n^{0.6}]$ and remains fixed throughout the simulations. Without loss of generality, we assume T = 2, and the spectral density of Y_n in this case is given by

$$g_{H,\phi(1),\phi(2)}(\lambda) = \frac{2 + \phi^2(1) + \phi^2(2) + A\cos\lambda - B\cos2\lambda - C\cos3\lambda}{(1 - 2\phi(2)\cos2\lambda + \phi^2(2))(1 - 2\phi(1)\cos2\lambda + \phi^2(1))} f_{\epsilon_n^H}(\lambda), \quad (42)$$

where $A = 2 + 2\phi(1)\phi(2) - 2\phi(1)$, $B = 2(\phi(1) + \phi(2))$, and $C = 2\phi(2)$.



Figure 1. The simulation of initial estimator and one-step estimator where $\theta = (0.6, 0.2, 0.8)$ for $m = [n^{\frac{3}{5}}]$, n = 100.



Figure 2. The simulation of initial estimator and one-step estimator where $\theta = (0.6, 0.2, 0.8)$ for $m = [n^{\frac{3}{5}}], n = 1000$.



Figure 3. The simulation of initial estimator and one-step estimator where $\theta = (0.6, 0.2, 0.8)$ for $m = [n^{\frac{3}{5}}], n = 2000$.

Table 1. The Bias and RMSE of Initial estimator and One-step estimator for $\theta = (0.6, 0.2, 0.8)$ when n = 100

(0.0, 0.2, 0.0)				
n = 100	B IE	B OS	RMSE IE	RMSE OS
H	0.1462	0.0683	0.2656	0.1106
$\phi(1)$	-0.0143	0.0064	0.0807	0.0237
$\phi(2)$	-0.0082	-0.0055	0.0972	0.0234

Table 2. The Bias and RMSE of Initial estimator and One-step estimator for $\theta = (0.6, 0.2, 0.8)$ when n = 1000

n=1000	BIE	BOS	RMSE IE	RMSE OS
H	-0.0599	0.0471	0.1101	0.0660
$\phi(1)$	-0.0015	-0.0002	0.0248	0.0212
$\phi(2)$	-0.0010	-0.0081	0.0304	0.0218

Table 3. The Bias and RMSE of Initial estimator and One-step estimator for $\theta = (0.6, 0.2, 0.8)$ when n = 2000

n=2000	B IE	B OS	RMSE IE	RMSE OS
H	-0.0497	0.0112	0.0864	0.0545
$\phi(1)$	-0.0004	0.0001	0.0180	0.0212
$\phi(2)$	0.0005	0.0003	0.0210	0.0186



Figure 4. The simulation of initial estimator and one-step estimator where $\theta = (0.2, 0.8, 0.6)$ for $m = [n^{\frac{3}{5}}]$, n = 100.



Figure 5. The simulation of initial estimator and one-step estimator where $\theta = (0.2, 0.8, 0.6)$ for $m = [n^{\frac{3}{5}}], n = 1000$.



Figure 6. The simulation of initial estimator and one-step estimator where $\theta = (0.2, 0.8, 0.6)$ for $m = [n^{\frac{3}{5}}], n = 2000$.

One-step estimator for $\theta = (0.2, 0.8, 0.6)$ when $n = 100$.					
	n=100	B IE	B OS	RMSE IE	RMSE OS
	H	0.3597	0.1846	0.4227	0.2036
	$\phi(1)$	-0.0009	0.0010	0.0962	0.0530
	$\phi(2)$	-0.0140	0.0028	0.0651	0.0471

Table 4. The Bias and RMSE of Initial estimator and One-step estimator for $\theta = (0.2, 0.8, 0.6)$ when n = 100.

Table 5. The Bias and RMSE of Initial estimator and One-step estimator for $\theta = (0.2, 0.8, 0.6)$ when n = 1000.

n=1000	B IE	B OS	RMSE IE	RMSE OS
H	0.1351	0.0312	0.1644	0.0736
$\phi(1)$	-0.0014	-0.0009	0.0309	0.0088
$\phi(2)$	-0.0019	0.0014	0.0193	0.0104

Table 6. The Bias and RMSE of Initial estimator and One-step estimator for $\theta = (0.2, 0.8, 0.6)$ when n = 2000.

n=2000	B IE	B OS	RMSE IE	RMSE OS
H	0.0883	0.0274	0.1146	0.0735
$\phi(1)$	0.0011	0.0006	0.0305	0.0245
$\phi(2)$	-0.0032	0.0003	0.0186	0.0135

Figure 1,2 and 3 depict the frequency distribution of statistical errors for the initial estimation and one-step estimation of the SFAR(1) model with parameters $\phi(1) = 0.6$, $\phi(2) = 0.2$, and H = 0.8. Figure 4,5 and 6 depict the frequency distribution of statistical errors for the initial estimation and one-step estimation of the SFAR(1) model with parameters $\phi(1) = 0.2$, $\phi(2) = 0.8$, and H = 0.6.

In all the tables, B stands for Bias, IE represents initial estimator, and OS denotes one-step estimator. From the above tables, it can be seen that the OS estimator shows a significant improvement in the estimation of H. From these figures and the accompanying table, it is evident that the one-step estimation outperforms the initial estimation, with a particularly notable improvement in estimating the parameter H, at the same time, we found that as the sample size increases, the estimation becomes more efficient. According to Hariz et al. (2024) and our simulations, the one-step estimation also has a faster running speed.

5. Conclusions and perspectives

In this paper, we propose a simple and effective method for estimating the parameters of the SFAR model individually, and we derive the asymptotic properties of this method. We address the difficulty of parameter estimation caused by the nonstationarity of the model by creating new subseries and obtaining an explicit form for the spectral density of the additive series.

The one-step procedure is essentially a gradient descent approach, achieving the \sqrt{n} rate with optimal variance.

Our results can be extended to SARIMA models by adjusting the calculation of the covariance matrix of the noise and the spectral density of X_n . Additionally, more effective initial estimators can be utilized for the one-step procedure, similar to the approach taken by Hariz et al. (2024) in the estimation of FARIMA models.

An interesting aspect to consider is that when T is sufficiently large, even larger than n, but still finite, the effectiveness of this gradient descent approach may diminish. In such cases, alternative methods for optimizing the initial estimator should be explored.

6. Application on Real Data

In this section, we will conduct practical modeling and analysis to examine the application effectiveness of the seasonal autoregressive model driven by fractional Gaussian noise in real data.

The data on the Colorado River runoff in Arizona selected in this paper are from the public data of the United States Geological Survey. This dataset records the monthly river runoff of the Colorado River from 1922 to 2022, with the unit of cubic feet per second. To facilitate modeling, we average the data of each of the 12 months on a quarterly basis, obtaining the quarterly runoff data for the first, second, third, and fourth quarters respectively. First, we calculate and obtain the autocorrelation function (ACF) plot and partial autocorrelation function (PACF) plot of the quarterly runoff data as follows:



Figure 7. Autocorrelation and partial autocorrelation coefficient plots of the Colorado River runoff in Arizona

From the above figure, we can observe that the autocorrelation function shows a trailing pattern with a slow decay rate, while the partial autocorrelation function cuts off. Therefore, it is appropriate to consider using a fractional AR model with long memory properties.

To avoid data over crowding and considering that the river runoff around 1963 changed significantly for unknown reasons, we extract the runoff data from 1922 to 1962 and draw the following sample path plot.



Figure 8. Sample path plot of the Colorado River runoff in Arizona from 1922 to 1962

As can be seen from Figure 8, the runoff of this river exhibits obvious seasonality. Considering the above two points, in this empirical analysis, we consider using the SFAR(1) model to simulate the above observations and compare it with the simulation of the seasonal autoregressive model driven by white noise.

The seasonal autoregressive model driven by white noise is as follows:

$$X_{4n+u} = \alpha(4n+u)X_{4(n-1)+u} + \epsilon_{4n+u}, \quad u = 1, 2, 3, 4, \quad n \in \mathbb{Z}^+,$$
(43)

where ϵ_{4n+u} is white noise, and $\alpha(1)$, $\alpha(2)$, $\alpha(3)$, $\alpha(4)$ are the model coefficients, satisfying $\alpha(4n+u) = \alpha(u)$.

We utilized the data from 1922 to 1962 to derive the parameter estimations of the two models. Subsequently, we computed their RMSEb and MAE against the real data. Finally, we randomly simulated 20 data points within these forty years using these two models. The results are shown in the following table and figure.

Model	SFAR	SAR
Parameters Values RMSE MAE	$(\phi(1), \phi(2), \phi(3), \phi(4), H) \\ (0.96, 0.82, 0.80, 0.90, 0.60) \\ 9439.37 \\ 6107.16$	$\begin{array}{c} (\alpha(1),\alpha(2),\alpha(3),\alpha(4)) \\ (0.80,0.61,0.16,0.53) \\ 16773.58 \\ 12264.90 \end{array}$

 Table 7. Fitting results of different models



Figure 9. Model fitting plot

In the above figure, the values represents the parameters fitted by the SFAR and SAR model. From Figure 9 and Table 7, we can see that the seasonal autoregressive model driven by fractional noise has smaller RMSE and MAE values and better fitting performance. Therefore, the seasonal autoregressive model with long memory properties is more suitable for the study of the Colorado River runoff.

7. Proofs of the main results

For clarity, we divide the technical results into two parts. The first part addresses the stationarity and spectral density of the SFAR(1) model, as well as the asymptotic properties of the initial estimator. The second part focuses on the asymptotic properties related to the one-step estimator.

7.1. Proof of Proposition 2.1

We will utilize the following lemma to demonstrate the stationarity of Y_n .

Lemma 7.1. For any $u \in \mathbb{N}$, the SFAR(1) model is defined by the recursive scheme

$$X_{nT+u} = \phi(u)X_{(n-1)T+u} + \epsilon_{nT+u}^{H}, \tag{44}$$

where ϵ_{nT+u}^{H} is a fractional Gaussian noise, $\phi(u) = \phi(u+nT) \leq 1$, $n \in \mathbb{N}$, then $(X_{nT+u})_{n \in \mathbb{N}}$ is a stationary process.

Proof. We verify that the process satisfies the three conditions for weak stationarity individually.

(1) For any $u \in \mathbb{N}$, $E(X_{nT+u}) = \mu$ is a finite constant.

Because the equation $(1 - \phi(u))z = 0$ has a root outside the unit circle, the process

 $(X_{nT+u})_{n\in\mathbb{N}}$ is said to be an SFAR(1) process if it can be represented as follows

$$X_{nT+u} = \sum_{j=0}^{\infty} \phi^{j}(u) \epsilon^{H}_{(n-j)T+u},$$
(45)

without loss of generality, we assume $E(\epsilon_n^H) = 0$. For any time series $(X_{nT+u})_{n \in \mathbb{N}}$ under the monotone convergence theorem and the Cauchy-Schwarz inequality, we obtain

$$E|X_{nT+u}| \leq E\sum_{j=0}^{\infty} |\phi^{j}(u)\epsilon^{H}_{(n-j)T+u}| = \sum_{j=0}^{\infty} E|\phi^{j}(u)\epsilon^{H}_{(n-j)T+u}|$$

$$\leq \sum_{j=0}^{\infty} |\phi^{j}(u)|E|\epsilon^{H}_{(n-j)T+u}|$$

$$\leq C\sum_{j=0}^{\infty} |\phi^{j}(u)|.$$
(46)

We know that $\phi^j(u) = o(\rho^{-j})$ as $j \to \infty$ for $1 < \rho < \frac{1}{\phi(u)}$. Consequently, $\phi^j(u)$ is absolutely summable, i.e., $\sum_{j=0}^{\infty} |\phi^j(u)| < \infty$. Thus, $E|X_{nT+u}| < \infty$ as shown in equation (46). By the monotone convergence theorem, $\sum_{j=0}^{\infty} \phi^j(u)$ is absolutely convergent almost surely.

Considering that

$$\left|\sum_{j=0}^{k} \phi^{j}(u) \epsilon^{H}_{(n-j)T+u}\right| \leq \sum_{j=0}^{k} \left|\phi^{j}(u) \epsilon^{H}_{(n-j)T+u}\right|$$

$$\tag{47}$$

with the dominated convergence theorem,

$$E(X_{nT+u}) = \lim_{k \to \infty} E\left(\sum_{j=0}^{k} \phi^j(u)\epsilon^H_{(n-j)T+u}\right) = 0.$$
(48)

(2) For any $u \in \mathbb{N}$, $E(X_{nT+u})^2 \leq \infty$. From equation (45), we derive

$$E(X_{nT+u})^{2} = E\left(\sum_{j=0}^{\infty} \phi^{j}(u)\epsilon^{H}_{(n-j)T+u}\right)^{2}$$

$$= E\left(\sum_{s=0}^{\infty} \sum_{k=0}^{\infty} \phi^{s}(u)\phi^{k}(u)\epsilon^{H}_{(n-s)T+u}\epsilon^{H}_{(n-k)T+u}\right),$$
(49)

by applying the conclusion above, we obtain

$$E |X_{nT+u}|^2 = \sum_{s=0}^{\infty} \sum_{k=0}^{\infty} |\phi^s(u)\phi^k(u)| E \left| \epsilon^H_{(n-s)T+u} \epsilon^H_{(n-k)T+u} \right|,$$
(50)

and the covariance of $\epsilon^{H}_{(n-s)T+u}$ and $\epsilon^{H}_{(n-k)T+u}$ is

$$\rho(\epsilon_{(n-s)T+u}^{H}, \epsilon_{(n-k)T+u}^{H}) = \frac{1}{2} \left(|(s-k)+1|^{2H} - 2|(s-k)T|^{2H} + |(s-k)T-1|^{2H} \right).$$
(51)

Since $\phi^j(u)$ is absolutely summable, it is also square summable. Additionally, as $s-k \to \infty$, $\rho(\epsilon^H_{(n-s)T+u}, \epsilon^H_{(n-k)T+u}) \to 0$, implying that there exists a constant M such that $E\left|\epsilon^H_{(n-s)T+u}\epsilon^H_{(n-k)T+u}\right| \le M$. Based on the above discussion and equation (50), we have established that $E(X_{nT+u})^2 \le \infty$.

(3) For any $k, s \in \mathbb{N}$, $E(X_{kT+u} - \mu)E(X_{sT+u} - \mu) = \gamma_{(k-s)T}$, which means that the autocovariance of X_{kT+u} and X_{sT+u} depends only on the time interval (k-s)T.

Without losing of generality, we assume $\mu = 0$ and the covariance of $(X_{nT+u})_{n \in \mathbb{N}}$ be rewritten as

$$E(X_{kT+u}X_{sT+u}) = E(\sum_{i=0}^{\infty}\sum_{j=0}^{\infty}\phi^{i}(u)\phi^{j}(u)\epsilon^{H}_{(s-i)T+u}\epsilon^{H}_{(k-j)T+u})$$

$$= \sum_{i=0}^{\infty}\sum_{j=0}^{\infty}\phi^{i}(u)\phi^{j}(u)\frac{1}{2}(|(s-k+j-i)T+1|^{2H} - 2|(s-k+j-i)T|^{2H} + |(s-k+j-i)T-1|^{2H}),$$
(52)

for any $q \in \mathbb{N}$, it follows directly from the above equation that

$$E(X_{(k+q)T+u}X_{(s+q)T+u}) = E(X_{kT+u}X_{sT+u}).$$
(53)

Thus, we have shown that $(X_{nT+u})_{n\in\mathbb{N}}$ is stationary. Since Y_n is a combination of X_{nT+u} in a cyclic manner, its stationarity naturally follows.

7.2. Proof of Proposition 2.2

Since the stationarity of $(X_{nT+u})_{n\in\mathbb{N}}$ has been established, we can determine its spectral density using Theorem 4.4 (Brockwell & Davis, 1991). $(X_{nT+u})_{n\in\mathbb{N}}$ satisfies the recursion

$$X_{nT+u} = X_{(n-1)T+u} + \epsilon_{nT+u}^{H}$$

$$= \sum_{j=0}^{\infty} \phi^{j}(u) \epsilon_{(n-j)T+u}^{H}$$

$$= \sum_{j=0,T,2T,...} \phi^{\frac{j}{T}}(u) \epsilon_{nT+u-j}^{H}.$$
(54)

From the above expression, we obtain the transfer function $H(e^{-i\lambda})$ as follows

$$H(e^{-i\lambda}) = \sum_{k=0}^{\infty} \phi^k(u) e^{-i\lambda kT}.$$
(55)

Thus, the spectral density function $f_{H,\phi(u)}(\lambda)$ is given by

$$f_{H,\phi(u)}(\lambda) = |H(e^{-i\lambda})|^2 f_{\epsilon_n^H}(\lambda) = \frac{f_{\epsilon_n^H}(\lambda)}{1 - 2\phi(u)\cos(\lambda T) + \phi^2(u)}.$$
 (56)

7.3. Proof of Proposition 2.3

Because the stationarlity of $(Y_n)_{n\in\mathbb{N}}$ has been proved above, Y_n has the following expression

$$Y_{n} = \sum_{u=1}^{T} X_{nT+u}$$

$$= \sum_{j=0}^{\infty} \phi^{j}(1) \epsilon^{H}_{(n-j)T+1} + \sum_{j=0}^{\infty} \phi^{j}(2) \epsilon^{H}_{(n-j)T+2} + \dots + \sum_{j=0}^{\infty} \phi^{j}(T) \epsilon^{H}_{(n-j)T+T}$$

$$= \sum_{k=0}^{\infty} \tilde{h}_{k} \epsilon^{H}_{(n+1)T-k},$$
(57)

and the coefficient of transfer function has the form of

$$\tilde{h}_{k} = \begin{cases} \phi^{\frac{k}{T}}(T) & \text{if } k = 0, T, 2T, \dots \\ \phi^{\frac{k-1}{T}}(T-1) & \text{if } k = 1, 1+T, 1+2T, \dots \\ \vdots \\ \phi^{\frac{k-(T-1)}{T}}(1) & \text{if } k = T-1, 2T-1, 3T-1, \dots \end{cases}$$
(58)

Then the transfer function is given by

$$H(e^{-i\lambda}) = \sum_{j=kT}^{\infty} \phi^{\frac{j}{T}}(T)e^{-ij\lambda} + \sum_{j=1+kT}^{\infty} \phi^{\frac{j-1}{T}}(T-1)e^{-ij\lambda} + \dots + \sum_{j=(k+1)T-1}^{\infty} \phi^{\frac{j-T+1}{T}}(1)e^{-ij\lambda}.$$
(59)

To simplify the notation, we denote

$$\Phi_{\phi(T-p)}(\lambda) = \sum_{j=kT+p}^{\infty} \phi^{\frac{j-p}{T}}(T-p)e^{-ij\lambda} = \frac{e^{-ip\lambda}}{1-\phi(T-p)e^{-i\lambda T}}, \quad p = 0, 1...T - 1.$$
(60)

Then, we have

$$H(e^{-i\lambda}) = \left(\sum_{P=0}^{T-1} \Phi_{\phi(T-p)}(\lambda)\right),\tag{61}$$

and the spectral density of $(Y_n)_{n\in\mathbb{N}}$ has the representation

$$g_{H,\underline{\phi}} = |H(e^{-i\lambda})|^2 f_{\epsilon_n^H}^H(\lambda) = |\sum_{P=0}^{T-1} \Phi_{\phi(T-p)}(\lambda)|^2 f_{\epsilon_n^H}^H(\lambda).$$
(62)

Remark 10. $|\cdot|$ denote the modulus of $H(e^{-i\lambda})$.

7.4. Proof of Theorem 2.4

The first part of the proof to to establish the consistency of \hat{H}_n , while second part is to verify consistency of $\hat{\phi}_n(u)$.

(1) Consistency of \hat{H}_n

This proof is based on Lemma 5.5 (Hariz et al., 2024) and the corollary (Hurvich et al., 1998). We can express $f_{H,\phi(u)}$ in the following form

$$\tilde{f}_{H,\phi(u)}(\lambda) = (1 - \cos\lambda T)^{2d} f_{H,\phi(u)}(\lambda)$$

$$= (1 - \cos\lambda T)^{2d} (1 - 2\phi(u)\cos\lambda T + \phi^{2}(u))^{-1} f_{\epsilon_{n}^{H}}(\lambda)$$

$$= C_{H}(1 - \cos\lambda T)^{2d+1} (1 - 2\phi(u)\cos\lambda T + \phi^{2}(u))^{-1} \sum_{j \in \mathbb{Z}} \frac{1}{|\lambda + 2j\pi|^{2H+1}}.$$
(63)

According to Hurvich et al. (1998), it can be concluded that

$$\hat{d}_n - d = -\frac{1}{2S_m} \sum_{j=1}^m (a_j - \overline{a}_m) \log(\tilde{f}_{H,\phi(u)}) - \frac{1}{2S_m} \sum_{j=1}^m (a_j - \overline{a}_m) \epsilon_j,$$
(64)

where ϵ_j is the error defined in Equation (3) of Hurvich et al. (1998). According to the theorem 1 from the aforementioned sources, we have

$$\hat{d}_n \xrightarrow[n \to \infty]{\mathbb{P}} d. \tag{65}$$

Hence, it is evident that

$$\hat{H}_n \xrightarrow[n \to \infty]{\mathbb{P}} H.$$
(66)

(2) Consistency of $\hat{\phi}_n(u)$ Assuming

$$\tilde{\Phi}_i^j(u) = (\epsilon_{u+iT}^H, \epsilon_{u+(i+1)T}^H, \dots \epsilon_{u+jT}^H), i \le j,$$
(67)

we can derive the following expression

$$\hat{\phi}_n(u) - \phi(u) = \frac{\tilde{\Phi}_2^{n^*}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_n)\Phi_1^{n-1}(u)}{\Phi_1^{n-1^*}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_n)\Phi_1^{n-1}(u)}.$$
(68)

We apply the taylor expansion of the matrix $\Gamma_{(n-1)T}^{-1}(\hat{H}_n)$ at H to the numerator,

yielding

$$\tilde{\Phi}_{2}^{n^{*}}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_{n})\Phi_{1}^{n-1}(u) = \tilde{\Phi}_{2}^{n^{*}}(u)\Gamma_{(n-1)T}^{-1}(H)\Phi_{1}^{n-1}(u) + \tilde{\Phi}_{2}^{n^{*}}(u)A_{nT}^{(1)}(H)\Phi_{1}^{n-1}(u)(\hat{H}_{n} - H) + \frac{1}{2}\tilde{\Phi}_{2}^{n^{*}}(u)A_{nT}^{(2)}(H)\Phi_{1}^{n-1}(u)(\hat{H}_{n} - H)^{2} + \frac{1}{6}\tilde{\Phi}_{2}^{n^{*}}(u)A_{nT}^{(3)}(\overline{H}_{n})\Phi_{1}^{n-1}(u)(\hat{H}_{n} - H)^{3},$$
(69)

thanks to the work of Hariz et al. (2024), we have the following three conclusions

$$\frac{1}{n}\tilde{\Phi}_{2}^{n^{*}}(u)A_{nT}^{(1)}(H)\Phi_{1}^{n-1}(u) \xrightarrow{\mathbb{P}} k_{H,\phi(u)}^{(1)}, \tag{70}$$

$$\frac{1}{n}\tilde{\Phi}_{2}^{n^{*}}(u)A_{nT}^{(2)}(H)\Phi_{1}^{n-1}(u) \xrightarrow[n \to \infty]{\mathbb{P}} k_{H,\phi(u)}^{(2)},$$
(71)

$$n^{-\frac{3}{2}}\tilde{\Phi}_{2}^{n^{*}}(u)A_{nT}^{(3)}(\overline{H}_{n})\Phi_{1}^{n-1}(u) = O_{\mathbb{P}}(1),$$
(72)

where $k_{H,\phi(u)}^{(1)}$, $k_{H,\phi(u)}^{(2)}$ are constants, $\overline{H}_n \in B(H, |\hat{H}_n - H|)$, and $A_{nT}^{(1)}(H)$, $A_{nT}^{(2)}(H)$, $A_{nT}^{(3)}(H)$ are

$$A_{nT}^{(1)}(H) = -\Gamma_{(n-1)T}^{-1}(H) \frac{\partial \Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H),$$
(73)

$$A_{nT}^{(2)}(H) = \Gamma_{(n-1)T}^{-1}(H) \frac{\partial^2 \Gamma_{(n-1)T}(H)}{\partial^2 H} \Gamma_{(n-1)T}^{-1}(H) + 2\Gamma_{(n-1)T}^{-1}(H) \frac{\partial \Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H) \frac{\partial \Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H),$$
(74)

$$\begin{aligned} A_{nT}^{(3)}(H) &= -\Gamma_{(n-1)T}^{-1}(H) \frac{\partial^{3}\Gamma_{(n-1)T}(H)}{\partial^{3}H} \Gamma_{(n-1)T}^{-1}(H) \\ &\quad - 3\Gamma_{(n-1)T}^{-1}(H) \frac{\partial\Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H) \frac{\partial^{2}\Gamma_{(n-1)T}(H)}{\partial^{2}H} \Gamma_{(n-1)T}^{-1}(H) \\ &\quad - 3\Gamma_{(n-1)T}^{-1}(H) \frac{\partial^{2}\Gamma_{(n-1)T}(H)}{\partial^{2}H} \Gamma_{(n-1)T}^{-1}(H) \frac{\partial\Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H) \\ &\quad - 6\Gamma_{(n-1)T}^{-1}(H) \frac{\partial\Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H) \frac{\partial\Gamma_{(n-1)T}(H)}{\partial H} \\ &\quad \times \Gamma_{(n-1)T}^{-1}(H) \frac{\partial\Gamma_{(n-1)T}(H)}{\partial H} \Gamma_{(n-1)T}^{-1}(H). \end{aligned}$$
(75)

It has been demonstrated in Esstafa (2019) that

$$\frac{1}{n}\tilde{\Phi}_{2}^{n^{*}}(u)\Gamma_{(n-1)T}^{-1}(H)\Phi_{1}^{n-1}(u) \xrightarrow[n \to \infty]{\mathbb{P}} 0,$$
(76)

the combination of equations (70), (71), (72), and (76) allows us to deduce that

$$\frac{1}{n}\tilde{\Phi}_{2}^{n^{*}}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_{n})\Phi_{1}^{n-1}(u) \xrightarrow{\mathbb{P}}{n\to\infty} 0.$$
(77)

Next, we consider the asymptotic properties of the denominator of equation (68). We can similarly expand the denominator using a Taylor series around H, resulting in

$$\Phi_{1}^{n-1^{*}}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_{n})\Phi_{1}^{n-1}(u) = \Phi_{1}^{n-1^{*}}(u)\Gamma_{(n-1)T}^{-1}(H)\Phi_{1}^{n-1}(u) + \Phi_{1}^{n-1^{*}}(u)A_{nT}^{(1)}(H)\Phi_{1}^{n-1}(u)(\hat{H}_{n}-H) + \frac{1}{2}\Phi_{1}^{n-1^{*}}(u)A_{nT}^{(2)}(H)\Phi_{1}^{n-1}(u)(\hat{H}_{n}-H)^{2},$$
(78)

similarly, this part of the proof aligns with Lemma 1 (Esstafa, 2019) and satisfy

$$\frac{1}{n}\Phi_1^{n-1^*}(u)A_{nT}^{(1)}(H)\Phi_1^{n-1}(u) \xrightarrow[n \to \infty]{\mathbb{P}} k_{H,\phi(u)}^{(3)},$$
(79)

$$n^{-\frac{3}{2}}\Phi_1^{n-1^*}(u)A_{nT}^{(2)}(H)\Phi_1^{n-1}(u) = O_{\mathbb{P}}(1), \tag{80}$$

$$\frac{1}{n}\Phi_1^{n-1^*}(u)\Gamma_{(n-1)T}^{-1}(H)\Phi_1^{n-1}(u) \xrightarrow{\mathbb{P}} \frac{1}{n\to\infty} \frac{1}{1-\phi^2(u)},$$
(81)

where $k_{H,\phi(u)}^{(3)}$ is a constant. The denominator in equation (68) converges in probability as follows

$$\frac{1}{n}\Phi_1^{n-1^*}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_n)\Phi_1^{n-1}(u) \xrightarrow[n \to \infty]{\mathbb{P}} \frac{1}{1-\phi^2(u)}.$$
(82)

Combining the above equations, we find that when the numerator of equation (68) is multiplied by $\frac{1}{n}$, it approaches 0, while the denominator, also multiplied by $\frac{1}{n}$, converges to a constant. Furthermore, since convergence in probability implies convergence in distribution, we conclude that

$$\hat{\phi}_n(u) \xrightarrow[n \to \infty]{\mathbb{P}} \phi(u).$$
 (83)

This establishes a clear relationship between the asymptotic behavior of the numerator and denominator, leading to the convergence of the estimated function.

7.5. Proof of Theorem 2.5

According to Theorem 2 (Hurvich et al., 1998), without loss of generality, we can assume $m = [n^{\delta}]$ for some $\frac{1}{2} < \delta < \frac{2}{3}$. denotes convergence in distribution. We thus have

$$\sqrt{m}(\hat{H}_n - H) \xrightarrow[n \to \infty]{\mathcal{L}} \mathcal{N}(0, U_{K,\delta}),$$
(84)

where $U_{K,\delta}$ is a constant related to K and δ . Building on the results from equation (68), we establish that

$$\sqrt{m}(\hat{\phi}_n(u) - \phi(u)) = \sqrt{m} \frac{\tilde{\Phi}_2^{n^*}(u)\Gamma_{(n-1)T}^{-1}(H)\Phi_1^{n-1}(u)}{\Phi_1^{n-1^*}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_n)\Phi_1^{n-1}(u)} + R_n^{(1)},$$
(85)

according to the proof of consistency and some results on Esstafa (2019), the denominator of the first term on the right side of the above equation satisfies

$$\frac{1}{n}\Phi_1^{n-1^*}(u)\Gamma_{(n-1)T}^{-1}(\hat{H}_n)\Phi_1^{n-1}(u) \xrightarrow{\mathbb{P}} \frac{1}{n\to\infty} \frac{1}{1-\phi^2(u)},$$
(86)

the nominator converge to a normal distribution

$$\frac{1}{\sqrt{n}}\tilde{\Phi}_{2}^{n^{*}}(u)\Gamma_{(n-1)T}^{-1}(H)\Phi_{1}^{n-1}(u) \xrightarrow{\mathbb{P}} \mathcal{N}(0,\frac{1}{1-\phi^{2}(u)}),$$
(87)

when $n \to \infty$, the reminder $R_n^{(1)}$ converges to 0. Thus, we can rewrite equation (85) as follows

$$\sqrt{m}(\hat{\phi}_{n}(u) - \phi(u)) = \sqrt{m} \frac{\frac{1}{n} \tilde{\Phi}_{2}^{n^{*}}(u) \Gamma_{(n-1)T}^{-1}(H) \Phi_{1}^{n-1}}{\frac{1}{n} \Phi_{1}^{n-1^{*}}(u) \Gamma_{(n-1)T}^{-1}(\hat{H}_{n}) \Phi_{1}^{n-1}(u)} + R_{n}^{(1)}$$

$$= \frac{\sqrt{m}}{\sqrt{n}} (1 - \phi^{2}(u)) \frac{1}{\sqrt{n}} \tilde{\Phi}_{2}^{n^{*}}(u) \Gamma_{(n-1)T}^{-1}(H) \Phi_{1}^{n-1}(u) + R_{n}^{(1)},$$
(88)

by slutsky theorem, we can conclude that $\sqrt{m}(\hat{\phi}_n(u) - \phi(u))$ converges to a normal distribution.

Lastly, we aim to present these results in the form of a joint normal distribution. Drawing on the findings from Hariz et al. (2024), the asymptotic distribution of $\sqrt{n}(\hat{\phi}_n(u) - \phi(u))$ can be expressed as a constant multiple of the asymptotic distribution of $(\hat{H}_n - H)$. Moreover, according to the Cramer-Wold theorem, the asymptotic distribution of $\sum_{u=1}^{T} (\hat{\phi}_n(u) - \phi(u))$ still adheres to an asymptotic normal distribution. Thus, the vector

$$((\hat{\phi}_n(1) - \phi(1)), (\hat{\phi}_n(2) - \phi(2)), ... (\hat{\phi}_n(T) - \phi(T)), ... \hat{H}_n - H),$$

converges to a Gaussian vector, tending towards a joint normal distribution. The covariance matrix of this vector is

$$\tilde{\Sigma}_{\theta} = U_{\theta} U_{\theta}^*, \tag{89}$$

where

$$U_{\theta} = \begin{pmatrix} 1 \\ \frac{C_{H,\phi(1)}^{(1)}}{(1-\phi^{2}(1))} \\ \vdots \\ \frac{C_{H,\phi(T)}^{(1)}}{(1-\phi^{2}(T))} \end{pmatrix}, \qquad (90)$$

 $C^{(1)}_{H,\phi(u)}$ is the constants related to $\phi(u)$ and H.

7.6. Proof of Theorem 3.1

To prove the theorem 3.1, we need to establish the following three lemmas and verify whether $g_{H,\underline{\phi}(\lambda)}$ is regular. The regularity conditions of $g_{H,\underline{\phi}(\lambda)}$ will be demonstrated in the auxiliary results.

Lemma 7.2. Let $\theta_0 \in \Theta$, $\delta > 0$, such that for any $\theta \in B(\theta_0, \delta)$, it holds that

$$||\mathcal{I}(\theta) - \mathcal{I}(\theta_0)|| \le K ||\theta - \theta_0||, \tag{91}$$

where K is some constant.

Proof. Without loss of generality, let $B(\theta_0, \delta)$ be a convex set in \mathbb{R}^3 . For ease of notation, $g_{H,\underline{\phi}}(\lambda)$ can be denoted as $g_{\theta}(\lambda)$. According to the relevant conclusions in Cohen et al. (2011) and the discussion of regularity conditions for $g_{H,\underline{\phi}}(\lambda)$, it is known that for any $k, j \in \{1, 2, ..., d\}$ that the following inequality holds

$$\left|\frac{1}{4\pi}\left(\int_{-\pi}^{\pi}\frac{\partial \log g_{\theta}(\lambda)}{\partial \theta_{k}}\frac{\partial \log g_{\theta}(\lambda)}{\partial \theta_{j}}d\lambda\right) - \frac{1}{4\pi}\left(\int_{-\pi}^{\pi}\frac{\partial \log g_{\theta_{0}}(\lambda)}{\partial \theta_{0,k}}\frac{\partial \log g_{\theta_{0}}(\lambda)}{\partial \theta_{0,j}}d\lambda\right)\right| \le K||\theta - \theta_{0}||,$$
(92)

K is defined as

$$K = \sup_{\theta \in B(\theta_0, \delta)} \left\| \left(\frac{\partial}{\partial \theta_i} \left(\int_{-\pi}^{\pi} \frac{\partial \log g_{\theta}(\lambda)}{\partial \theta_k} \frac{\partial \log g_{\theta}(\lambda)}{\partial \theta_j} d\lambda \right) \right)_{1 \le i \le d} \right\|, \tag{93}$$

which is related to k and j. Furthermore, since the conditions (A1) and (A2) (Cohen et al., 2011) hold, it follows that $K < \infty$, hence the lemma holds.

Lemma 7.3. For any $\theta \in \Theta^l$, it follows from the distribution of the parameter θ that

$$\frac{\Delta l_n(\theta)}{\sqrt{n}} + \sqrt{n}\mathcal{I}(\theta) = O_{\mathbb{P}}(1).$$
(94)

Proof. The Lemma 3.6 (Cohen et al., 2011) implies that, from the distribution of θ , we have

$$E\left(\frac{\Delta l_n(\theta)}{n}\right) \to -\mathcal{I}(\theta).$$
 (95)

To determine the convergence rate of the above expression, Lemma 3 and Lemma 4 (Lieberman et al., 2012) yield the following conclusion

$$E\left(\frac{\Delta l_n(\theta)}{n}\right) + \mathcal{I}(\theta) = O(n^{-1+\delta}),\tag{96}$$

where δ is a positive real number. Therefore,

$$E\left(\frac{\Delta l_n(\theta)}{\sqrt{n}}\right) + \sqrt{n}\mathcal{I}(\theta) = O(n^{-\frac{1}{2}+\delta}).$$
(97)

Furthermore, by utilizing Lemma 3.6 (Cohen et al., 2011) once again, we obtain

$$Var\left(\frac{\Delta l_n(\theta)}{\sqrt{n}}\right) = O(1).$$
(98)

Thus, the proof is concluded.

Lemma 7.4. Let $\{\overline{\theta}_n\}_n$ be a stochastic sequence satisfying $\overline{\theta}_n - \theta = o_{\mathbb{P}}(1)$. Then, according to the distribution of parameter θ , for any k > 0, it holds that

$$\frac{\Delta l_n(\theta_n)}{n} - \frac{\Delta l_n(\theta)}{n} = O_{\mathbb{P}}(n^k(\overline{\theta}_n - \theta)).$$
(99)

Proof. Let $C_{k,\theta}$ be a compact convex set depending on k and θ , and $\overline{\theta}_n \in C_{k,\theta}$. According to the proof of Lemma 3.7 (Cohen et al., 2011), we have

$$\sup_{\overline{\theta}_n \in C_{k,\theta}} \left| \frac{\partial^3}{\partial^{i_1} \theta_1 \partial^{i_2} \theta_2 \dots \partial^{i_d} \theta_d} \frac{l_n(\overline{\theta}_n)}{n^{1+k}} \right| = O_{\mathbb{P}}(1), \tag{100}$$

where $(i_1, i_2, ..., i_d) \in \{0, 1, 2, 3\}^d$, satisfying $i_1 + i_2 ... + i_d = 3$. In conclusion, for a finite positive random variable K, we have

$$P\left(\left\|\frac{\Delta l_n(\overline{\theta}_n)}{n} - \frac{\Delta l_n(\theta)}{n}\right\| \le Kn^k(||\overline{\theta}_n - \theta||\right) \ge P(\overline{\theta}_n \in C_{k,\theta}),\tag{101}$$

which implies $\frac{\Delta l_n(\overline{\theta}_n)}{n} - \frac{\Delta l_n(\theta)}{n} = O_{\mathbb{P}}(n^k(\overline{\theta}_n - \theta))$ holds.

According to the hypothesis of this theorem, we can deduce

$$\sqrt{n}(\tilde{\theta}_n - \theta) = \sqrt{n}(\hat{\theta}_n - \theta) + \mathcal{I}^{-1}(\hat{\theta}_n) \frac{\nabla l_n(\hat{\theta}_n)}{\sqrt{n}},$$
(102)

applying mean-value theorem to $\nabla l_n(\theta)$, we have

$$\nabla l_n(\hat{\theta}_n) = \nabla l_n(\theta) + (\hat{\theta}_n - \theta) \int_0^1 \triangle l_n(\theta + v(\hat{\theta}_n - \theta)) dv, \qquad (103)$$

Substituting equation (103) to equation (102), we produce

$$\sqrt{n}(\tilde{\theta}_n - \theta) = \sqrt{n}(\hat{\theta}_n - \theta)\mathcal{I}^{-1}(\hat{\theta}_n)(\mathcal{I}(\hat{\theta}_n) + \frac{\int_0^1 \Delta l_n(\theta(v))dv}{n}) + \mathcal{I}^{-1}(\hat{\theta}_n)\frac{\nabla l_n(\theta)}{\sqrt{n}}, \quad (104)$$

where $\theta(v) = \theta + v(\hat{\theta}_n - \theta), v < 1$. Next, we will discuss the consistency and asymptotic normality of one-step estimator. (1) Consistency of $\tilde{\theta}_n$

Observing equation (104), the first and second terms on the right-hand side can be expressed as

$$A_{n} = \sqrt{n}(\hat{\theta}_{n} - \theta)\mathcal{I}^{-1}(\hat{\theta}_{n})(\mathcal{I}(\hat{\theta}_{n}) + \frac{\int_{0}^{1} \bigtriangleup l_{n}(\theta(v))dv}{n})$$

$$= \sqrt{n^{\delta}}(\hat{\theta}_{n} - \theta)\mathcal{I}^{-1}(\hat{\theta}_{n})\sqrt{n^{1-\delta}}(\mathcal{I}(\hat{\theta}_{n}) + \frac{\int_{0}^{1} \bigtriangleup l_{n}(\theta(v))dv}{n})$$

$$(105)$$

and

$$B_n = \mathcal{I}^{-1}(\hat{\theta}_n) \frac{\nabla l_n(\theta)}{\sqrt{n}} = \mathcal{I}^{-1}(\theta) \frac{\nabla l_n(\theta)}{\sqrt{n}} + (\mathcal{I}^{-1}(\hat{\theta}_n) - \mathcal{I}^{-1}(\theta)) \frac{\nabla l_n(\theta)}{\sqrt{n}}.$$
 (106)

Fristly, we analyze the properties of A_n and derive the following equation

$$\mathcal{I}(\hat{\theta}_n) + \frac{\int_0^1 \Delta l_n(\theta(v)) dv}{n} = (\mathcal{I}(\hat{\theta}_n) - \mathcal{I}(\theta_n)) + (\mathcal{I}(\theta_n) + \frac{\Delta l_n(\theta)}{n}) + \frac{1}{\sqrt{n}} \int_0^1 (\frac{\Delta l_n(\theta(v)))}{\sqrt{n}} - \frac{\Delta l_n(\theta)}{\sqrt{n}}) dv,$$
(107)

based on equation (107) and lemmas 6.2, 6.3, and 6.4. The convergence order of $\frac{A_n}{\sqrt{n}}$ is

$$\frac{A_n}{\sqrt{n}} = n^{-\frac{\delta}{2}} (O_{\mathbb{P}}(n^{-\frac{\delta}{2}}) + O_{\mathbb{P}}(n^{-\frac{1}{2}}) + O_{\mathbb{P}}(n^{k-\frac{\delta}{2}})),$$
(108)

when $k - \delta < 0$, we have $\frac{A_n}{\sqrt{n}} \xrightarrow{\mathbb{P}} 0$. Secondly, we consider the property of B_n and it has the form of

$$B_n = \mathcal{I}^{-1}(\hat{\theta}_n) \frac{\nabla l_n(\theta)}{\sqrt{n}} = \mathcal{I}^{-1}(\theta) \frac{\nabla l_n(\theta)}{\sqrt{n}} + (\mathcal{I}^{-1}(\hat{\theta}_n) - \mathcal{I}^{-1}(\theta)) \frac{\nabla l_n(\theta)}{\sqrt{n}},$$
(109)

according to Hariz et al. (2024) and theorem 1 in Lieberman et al. (2012), we have

$$\frac{\nabla l_n(\theta)}{\sqrt{n}} \xrightarrow[n \to \infty]{\mathbb{P}} 0.$$
(110)

When $\mathcal{I}n(\cdot)$ is a non-degenerate continuous function, as indicated by the above equation, it can be observed that both the first and second terms of B_n tend to 0. Consequently, $\frac{B_n}{\sqrt{n}}$ converges in probability to 0, and naturally, it also converges in distribution to 0.

Combining the above results, we can conclude the consistency of $\tilde{\theta}_n$. (2) Asymptotic normality of $\hat{\theta}_n$

According to the results of Hariz et al. (2024), the equation

$$\mathcal{I}^{-1}(\theta)\frac{\nabla l_n(\theta)}{\sqrt{n}} + (\mathcal{I}^{-1}(\hat{\theta}_n) - \mathcal{I}^{-1}(\theta))\frac{\nabla l_n(\theta)}{\sqrt{n}}$$
(111)

converges in probability to a bounded limit as $n \to \infty$. Simultaneously, the second term on the right-hand side of equation (111) converges to 0. By applying the Slutsky theorem, we can verify the asymptotic normality of θ_n .

8. Auxiliary results

Lemma 8.1. Under the hypothesis on the parametric space have the following results (1) For any $H \in [0,1]$ and $j \in \{0,1,2,3\}$, $\frac{\partial}{\partial\lambda} \frac{\partial^j}{\partial^j H} g_{H,\underline{\phi}}(\lambda)$. (2) For any $j \in \{0,1,2,3\}$ the functions $\frac{\partial^j}{\partial^j H} g_{H,\underline{\phi}}(\lambda)$ are symmetric with respect to λ . (3) For any $\delta > 0$ and all $(H,\lambda) \in [0,1] \times [-\pi,\pi] \setminus \{0\}$ $a.C_{1,\delta}|\lambda|^{1-2H+\delta} \leq g_{H,\underline{\phi}}(\lambda) \leq C_{2,\delta}|\lambda|^{1-2H-\delta}$. $b.|\frac{\partial}{\partial\lambda}g_{H,\underline{\phi}}(\lambda)| \leq C_{3,\delta}|\lambda|^{-2H-\delta}$. $c.For any j \in \{0,1,2,3\}, |\frac{\partial^j}{\partial^j H}g_{H,\underline{\phi}}(\lambda)| \leq C_{4,\delta}|\lambda|^{-2H-\delta}$, where $C_{i,\delta}$ are constants for i = 1, 2, 3, 4.

Proof. We start from Assertion 3a, which states that

$$g_{H,\underline{\phi}}(\lambda) = C_H |\sum_{p=0}^{T-1} \frac{e^{-ip\lambda}}{1 - \phi(T)e^{-i\lambda T}}|^2 (1 - \cos(\lambda)) \sum_{j \in \mathbb{Z}} \frac{1}{|\lambda + 2j\pi|^{2H+1}},$$
(112)

where $C_H = \frac{1}{2\pi}\Gamma(2H+1)\sin(\pi H)$ and $\Gamma(\cdot)$ denote the Gamma function. According to Lemma 5.4 in Hariz et al. (2024), we have

$$K_{1,\delta}|\lambda|^{1-2H+\delta} \le C_H(1-\cos(\lambda))\sum_{j\in\mathbb{Z}}\frac{1}{|\lambda+2j\pi|^{2H+1}} \le K_{2,\delta}|\lambda|^{1-2H-\delta}$$
(113)

and

$$\frac{\sqrt{2}T}{1 - \phi_{max}^2(u)} \le |\sum_{p=0}^{T-1} \frac{e^{-ip\lambda}}{1 - \phi(T)e^{-i\lambda T}}|^2 \le \frac{\sqrt{2}T}{1 - \phi_{min}^2(u)},\tag{114}$$

where $\phi_{max}^2(u)$ and $\phi_{min}^2(u)$ are the maximum and minimum values of $\phi(u)$, respectively. Thus, Assertion 3a has been proved and assertion 3b follows straightforwardly from Assertion 3a.

Next, we discuss Assertion 3c, which can be obtained directly from Lemma 5.4 in Hariz et al. (2024). The partial derivative of $g_{H,\underline{\phi}}(\lambda)$ does not depend on $|\sum_{p=0}^{T-1} \frac{e^{-ip\lambda}}{1-\phi(T)e^{-i\lambda T}}|^2$, and the modulus is bounded.

References

Beran, J., Feng, Y., Ghosh, S., & Kulik, R. (2013). Long-memory processes. Long-Mem. Process. https://doi.org/10.1007/978-3-642-35512-7

- Bisognin, C., & Lopes, S. R. C. (2009). Properties of seasonal long memory processes. Mathematical and Computer Modelling, 49(9-10), 1837-1851. https://doi.org/10.1016/j.mcm.200 8.12.003
- Brockwell, P. J., & Davis, R. A. (1991). Time series: theory and methods. Springer Science & Business Media. https://doi.org/10.2307/2982983

- Brouste, A., Cai, C., & Kleptsyna, M. (2014). Asymptotic properties of the MLE for the autoregressive process coefficients under stationary Gaussian noise. *Mathematical Methods* of Statistics, 23, 103-115. https://doi.org/10.3103/S1066530714020021
- Brouste, A., Soltane, M., & Votsi, I. (2020). One-step estimation for the fractional Gaussian noise at high-frequency. ESAIM: Probability and Statistics. https://doi.org/10.1007/978-3
- Carlin, J. B., & Dempster, A. P. (1989). Sensitivity analysis of seasonal adjustments: empirical case studies. *Journal of the American Statistical Association*, 84(405), 6-20. https://doi.org/10.2307/2289837
- Chan, N. H., & Terrin, N. (1995). Inference for unstable long-memory processes with applications to fractional unit root autoregressions. *The Annals of Statistics*, 23(5), 1662-1683. https://doi.org/10.1214/aos/1176324318
- Chatfield, C., & Prothero, D. L. (1973). Box-Jenkins seasonal forecasting: problems in a case-study. Journal of the Royal Statistical Society: Series A (General), 136(3), 295-315. https://doi.org/10.2307/2344994
- Cohen, S., Gamboa, F., Lacaux, C., & Loubes, J. M. (2011). LAN property for some fractional type Brownian motion. ALEA: Latin American Journal of Probability and Mathematical Statistics, 10(1), 91-106.
- Esstafa, Y. (2019). Long-memory time series models with dependent innovations (Doctoral dissertation, Université Bourgogne Franche-Comté).
- Fox, R., & Taqqu, M. S. (1986). Large-sample properties of parameter estimates for strongly dependent stationary Gaussian time series. *The Annals of Statistics*, 14(2), 517-532. https://doi.org/10.1214/aos/1176349936
- Franco, G. C., & Reisen, V. A. (2007). Bootstrap approaches and confidence intervals for stationary and non-stationary long-range dependence processes. *Physica A: Statistical Mechanics and its Applications*, 375(2), 546-562. https://doi.org/10.1016/j.physa.2006.08.027
- Geweke, J., & Porter-Hudak, S. (1983). The estimation and application of long memory time series models. *Journal of Time Series Analysis*, 4(4), 221-238. https://doi.org/10.1111/j.1467-9892.1983.tb00371.x
- Gloter, A., & Yoshida, N. (2021). Adaptive estimation for degenerate diffusion processes. https://doi.org/10.1214/20-EJS1777
- Hariz, S.B., Brouste, A., Cai, C., & Soltane, M. (2024). Fast and asymptotically-efficient estimation in an autoregressive process with fractional type noise. *Journal of Statistical Planning and Inference*. https://doi.org/10.1016/j.jspi.2024.106148
- Harrison, P. J. (1965). Short-term sales forecasting. Journal of the Royal Statistical Society: Series C (Applied Statistics), 14(2-3), 102-139. https://doi.org/10.1287/mnsc.13.11.821
- Hosking, J. R. (1984). Modeling persistence in hydrological time series using fractional differencing. Water Resources Research, 20(12), 1898-1908. https://doi.org/10.1029/WR020i012 p01898
- Hurst, H. E. (1951). Long-term storage capacity of reservoirs. Transactions of the American Society of Civil Engineers, 116(1), 770–799. https://doi.org/10.1061/TACEAT.0006518
- Hurvich, C. M., Deo, R., & Brodsky, J. (1998). The mean squared error of Geweke and Porter-Hudak's estimator of the memory parameter of a long-memory time series. *Journal of Time Series Analysis*, 19(1), 19-46. https://doi.org/10.1111/1467-9892.00075
- Kong, J., & Lund, R. (2023). Seasonal count time series. Journal of Time Series Analysis, 44(1), 93-124. doi:10.1111/jtsa.12651
- Kutoyants, Y. A., & Motrunich, A. (2016). On multi-step MLE-process for Markov sequences. Metrika, 79, 705-724. https://doi.org/10.1007/s00184-015-0574-4
- Le Cam, L. (1956). On the asymptotic theory of estimation and testing hypotheses. In Proceedings of the Third Berkeley Symposium on Mathematical Statistics and Probability, Volume 1: Contributions to the Theory of Statistics (Vol. 3, pp. 129-157). University of California Press. https://doi.org/10.1525/9780520313880-014
- Lieberman, O., Rosemarin, R., & Rousseau, J. (2012). Asymptotic theory for maximum likelihood estimation of the memory parameter in stationary Gaussian processes. *Econometric Theory*, 28(2), 457-470. https://doi.org/10.1017/S0266466611000399

Marinucci, D., & Robinson, P. M. (1998). Semiparametric frequency domain analysis of fractional cointegration. https://doi.org/10.1093/oso/9780199257294.003.0015

Robinson, P. M. (1995). Log-periodogram regression of time series with long range dependence. The Annals of Statistics, 1048-1072. https://doi.org/10.1214/aos/1176324636

Robinson, P. M. (2010). Long memory models. In *Macroeconometrics and Time Series Analysis* (pp. 163-168). London: Palgrave Macmillan UK. https://doi.org/10.1093/acrefore/97801906 25979.013.173

Soltane, M. (2024). Asymptotic efficiency in autoregressive processes driven by stationary Gaussian noise. Stochastic Models, 40(1), 70–96. https://doi.org/10.1080/15326349.2023.2202227

Tsay, R. S. (2013). Multivariate time series analysis: with R and financial applications. John Wiley & Sons.